

# Radio Fun

481 2.00

"The beginner's guide to the exciting world of amateur radio."

## in this issue

### features

- 4 Resonance W7KZE
- 7 My Recent Experiences with QRP WA3ULH
- 13 Is It a Cell or a Battery? W3RZD
- 15 A Filter to Eliminate Alternator Whine AA8HS
- 16 Easy Transmitter Protection KEØUL

### reviews

- 18 MFJ's 941D Versa Tuner II KT2B

### kit reviews

- 8 Lectrokit SP-1 Spider WA6GER

### vintage reviews

- 10 The Hallicrafters SX-140K W3UZN, W3WTO
- 12 The National 200 W1DTY
- 14 The Knight T-60 Transmitter W4WKM

### departments

- 26 Activities Calendar Staff
- 17 Ad Index Staff
- 22 Antennas, Etc. K4IPV
- 28 Flea Market Staff
- 5 Letters Staff
- 30 New Products Staff
- 3 QLF W2NSD/I
- 20 Radio Magic WB8VGE
- 19 The Tech Side KB1UM
- 29 Uncle Wayne's Bookshelf Staff
- 24 Upgrade ...
- Don't Stop Now WB6NOA
- 25 What's Next? WB2MGP

## President Clinton To Ham Astronauts: "Good Job!"



President Bill Clinton praised the astronauts aboard NASA shuttle mission STS-57 on a special live hookup to the White House recently. He told the crew their work on the Shuttle Amateur Radio EXperiment (SAREX) was inspiring to young Americans. For more on the story, please turn to "Clinton is High on Hams in Space" on page 16. (Photo courtesy: The White House.)

## FCC Relaxes Business Restrictions

The Federal Communications Commission has enacted a major change in the law restricting amateur radio use for personal business and public service. Under the new rules, it will no longer be a violation to order a pizza or make an appointment via amateur radio. The Commission has acted to amend the Part 97 Amateur Service rules allowing for more flexibility in personal business and public service communications.

The amendment permits li-

censees to use the amateur service frequencies to assist with public service communications at races, parades, and educational activities. Personal communications which will no longer be prohibited include making appointments, ordering food, and collecting data for the National Weather Service.

Effective 30 days after publishing in the Federal Register (approximately September 15th), here is what you can do (with some ex-

ceptions) on the ham bands:

Any amateur-to-amateur communications are now permitted unless:

a. Specifically prohibited. These include:

1. Music (except for incidental space shuttle music);
2. Communications facilitating a criminal act;
3. Messages obscured by codes or ciphers;
4. Obscene or indecent words or language; and

5. False or deceptive messages, signals, or identification.

b. Transmissions for compensation. The following exceptions apply:

1. Morse code practice and information bulletins (special criteria);

2. Classroom teachers using ham radio in the classroom.

c. Transmissions for the pecuniary benefit of the station control operator or his or her employer.

The following communications are permitted, but not on a "... regular basis" (not defined by the FCC):

1. Communications which could be reasonably furnished through other radio services;
2. Notices concerning sale or

trade of amateur station apparatus; and

3. Retransmissions of government-provided space shuttle, propagation, and weather forecast broadcasts.

Here are some examples of the old and new part 97.113, which covers prohibited communications:

**OLD RULE:** No amateur station shall transmit any communications which promotes the business or commercial affairs of any party. If anyone profits financially, it is an illegal transmission.

**NEW RULE:** An amateur may not be paid, direct or indirect, for his voluntarily provided communications.

Continued on page 16





## Put yourself in the winner's circle with the PK-232MBX multi-mode controller.

The PK-232MBX sets the pace for multi-mode controllers. While the competitors are racing to catch up, the PK-232MBX surges into the lead, winning more contests and providing the best value of any multi-mode controller on the market today.

Leave the competition in the dust—with the highest quality filters available (seventeen-pole effective filtering), the PK-232MBX pulls signals out of the noise better than any other controller.

Satisfy your drive for variety with PACTOR, Packet, AMTOR/SITOR, Morse, RTTY (Baudot/ASCII), WEFAX, NAVTEX, and TDM modes.

You won't spin your wheels trying to identify a signal. Our revolutionary SIAM™ technology automatically identifies the incoming signals, switches the PK-232MBX to the recognized mode, and starts displaying the data.

PACTOR, Packet and AMTOR mailboxes—with selective control of third party traffic—are standard to the PK-232MBX.

Our extensive Host Mode control gives you unmatched power and versatility from computer support programs for DOS, Windows™, Macintosh, and Commodore computers.

Our highly trained service crew keeps you on track with helpful advice and in-depth knowledge of amateur radio.


When you're ready for a multi-mode controller with a proven track record, the PK-232MBX is the choice of champions.

For more information on the PK-232MBX, call AEA's Literature Request Line at (800)432-8873 or contact your favorite ham radio equipment dealer.



*Connect with us*





## QLF

by Wayne Green W2NSD/1

### How G.E. bumbled away a billion dollars . . . and fumbled history!

It was a few years ago. Almost 30 years, actually, and amateur radio was right in the middle of this piece of history. I wonder how many amateurs remember what happened back then. Lean back and old Uncle Wayne will spill the beans.

This had to do with the beginnings of single-sideband. It was known as single-sideband suppressed carrier in the early days (SSSC). SSB had actually been around for many years and had been used for some commercial point-to-point communications. But it was a kluge to use. This was before phasing circuits had been invented, so they took an AM signal and got rid of the second sideband and the carrier with filters. In the antenna! For any amount of power this meant big water-cooled filters.

But receivers weren't very stable back then, either. They'd often drift maybe 5-10 kc (this was before Hertz) during the warm-up, so we had to keep retuning our receivers until they warmed up and stabilized. Transmitters would have drifted too, but this was before the invention of stable variable oscillators, so we used crystals. That kept our transmitters on channel, even while the tubes, capacitors, and coils were warming up.

Radar timing circuits used phase-shifting circuits, so it wasn't long after these were declassified after WWII that someone thought of using the circuit to cancel out both the second sideband and the carrier. Voilà, SSSC. The first circuit was developed by a ham, of

course. I built my first SSB rig in 1954. That was back when I still had enough time to build my own gear.

Now, at about the same time as SSB was getting started, pioneered by Wes Schum W9DYV and his Central Electronics 10A exciter, John Costas of G.E. was working on double-sideband suppressed carrier (DSB-SC). G.E. came out with a commercial DSB receiving detector. Now I wish I'd saved mine.

If you're not familiar with sideband technology, it's simple. Our old amplitude modulated (AM) rigs had a carrier, plus upper and lower sidebands. Two-thirds of the power went into the carrier and one-third into the two sidebands. So, by getting rid of the carrier and one sideband a rig could run six times as much effective output power. Six times the punch. Then the carrier would be generated at the receiver and mixed with the sideband. By this time we had enough receiver stability to make this system work.

Two other big benefits were that this got rid of those miserable carriers, which created beat notes when two were within 20 kc of each other, which they always were. It made the phone bands madhouses of heterodynes, wiping out all but the loudest signals. By transmitting only one sideband, the width of the signal was cut in half, making it possible for us to have more contacts in our narrow phone bands.

While receivers did best when they had a sideband detector, it was possible to use the receiver BFO to simulate the missing carrier, so that's the way we did it at first. I remember visiting hams in Germany, Austria,

and Switzerland in 1958 and showing them how they could tune in sideband signals.

But what about this double-sideband stuff? Why would anyone want to transmit two sidebands and occupy twice as much of the band when one sideband was doing so well? That also cut your power in half. The benefits of DSB were not obvious. But the fact is that DSB had an enormous benefit over SSB. It was all in the detector. Let me explain.

With DSB you're transmitting two identical signals, one above the center frequency and one below. Now let's suppose you have two detectors in your receiver, one for each sideband. And then let's use a little gate which will open only when the same signal comes through on both sidebands at once. The result is that you can run signals much closer together in frequency with a minimum of interference. And so, although each transmitter seems to take up twice the bandwidth, you can run around five to 10 times as many signals in the same band with DSB . . . depending on the differences in signal strengths.

G.E. knew this and Costas was trying to get them to support this new technology. At the same time Art Collins W0CXX was pushing SSB for commercial and military communications systems. Art enlisted the help of Don Merten W2UOL/K2AAA to get the military to specify SSB, which he figured (rightly) would be worth a fortune to Collins radio. I'd known Don ever since he'd been selling surplus gear right after the war from his home as Eldico Electronics in Whitestone NY.

They went after General Curtis Lemay, the head of SAC, and General Butch Griswald, his second in command (both hams, naturally). Art set up Collins SSB equipment on Curt's SAC plane, in his office, on his boat, in his home, and so on. Then they climbed aboard a SAC plane and showed Curt and Butch how, for the first time, they could keep in touch with their planes from just about anywhere in the world. SSB beat the hell out of AM and Collins was in. Art brought out the 75A1 receiver and the 32V1 transmitter and made millions. Hundreds of millions. Billions in today's dollarettes.

Don later went into the sideband manufacturing business too, building Eldico rigs. When the 75A1 came out it was by far the

most expensive receiver on the market. I looked at it and predicted it would never sell. That's by far the worst prediction I've ever made. Within a few years it was the most popular ham receiver in the country. And then in the world.

If G.E. had had anyone with vision, they'd have gone after the military market with their DSB system, and gone after it via amateur radio, the way Art Collins did. They had the technically better system, by far, but they goofed it and the rest is history. Oh, I published a few articles on DSB, but it was too late, SSB had won. Without receivers with DSB detectors built in the system was useless.

I mentioned AM, which died a well-deserved death. One thing few amateurs have yet caught on to is that the mode is not really amplitude modulated at all. When you look at an AM signal on an oscilloscope you can see the carrier wave and watch it being modulated, so it looks for all the world like this is what's happening. It isn't. Sometimes you can't believe what you're seeing.

What's actually happening is this. You have an RF final amplifier in the transmitter. This is modulated by the audio signal. If you have a kilowatt of carrier you need 500 watts of audio to modulate it fully. What really happens is that your final amplifier is acting as a mixer. You feed in your carrier frequency and the audio frequencies. The result is what you get from any mixer: the original two frequencies, the sum of them, and the difference. The original audio frequency gets lost in the final tuning and antenna circuits, so all that is transmitted is the carrier frequency, plus the sum and difference frequencies . . . known as the sidebands. The total output is the 1,500 watts you put in, less what's lost in the circuit.

It wasn't until scientists were able to develop very sharp tuning receivers that they discovered that the carrier didn't actually vary with modulation. Everyone had always believed what the oscilloscope seemed to show. Some old-timers will still argue about this, but only if they aren't well read.

If G.E. had gone after the golden ring we'd be able to have several times as many signals on our HF bands and far less interference. Too bad. RF

**Don't miss out on any of the FUN!**  
**Call 1 (800) 257-2346 today and subscribe to *Radio Fun*.**

USED BY OVER 8,000 SATISFIED MILITARY, GOVERNMENT, COMMERCIAL MARINE, AVIATION AND AMATEUR RADIO OPERATORS

## No other antenna matcher can do all that MAXCOM does.

- Get all-band HF coverage with a single dipole or long wire antenna.
- No tuning – ever! Just set it up, then forget it.
- No antenna tuner needed.
- Reduces a significant portion of atmospheric noise.
- Indestructible!
- Five Year Guarantee.
- Perfect for permanent installation, and great for an easy-up portable antenna.



**MAXCOM XLS**  
Single element ungrounded vertical or longwire configuration



**MAXCOM XLD**  
Standard two element dipole or grounded longwire configuration

Prices starting at \$299.  
Call or write for information package.

**MAXCOM**

P.O. Box 502  
Fort Lauderdale, Florida 33302  
Ph. 305-523-6369 • Fax 305-522-8159

CIRCLE 101 ON READER SERVICE CARD



# Resonance

by Larry Luchi W7KZE

[Editor's Note: This technical discussion of resonance is a bit more advanced than what we usually publish in Radio Fun, and it may leave some of you in the dark. If so, read it through a few times—slowly—and things should begin to sink in. If you want to get the most out of amateur radio, you've got to really understand this stuff—not just memorize a bunch of answers for a test. We've asked Mr. Luchi to prepare a series of articles focusing on various electronic components and their properties. We'll publish them from time to time, and if you stick with them, you'll be well on your way to a solid foundation in electronics.—David NIGPH]

Resonant circuits are at the heart of all transmitters, receivers, and antennas. Without resonant circuits there would be no radio communication.

Brief mention was made of resonance in my last article. When the inductive reactance ( $X_L$ ) of a coil equals the capacitive reactance ( $X_C$ ) of a capacitor in a circuit, a condition known as resonance occurs. Figure 1a illustrates a series-resonant circuit and Figure 1b shows a parallel-resonant circuit.

Since resonance is the condition where  $X_L$  equals  $X_C$ , the formula for resonance is:

$$X_L = X_C \text{ or } 2\pi fL = \frac{1}{2\pi fC} \text{ Equation 1}$$

Where  $X_L$  = inductive reactance, in ohms




Figure 2. The voltage drop across the coil and the capacitor is zero. The total source voltage appears across R.




Figure 3. Resonance occurs where  $X_C = X_L$ .

$X_C$  = capacitive reactance, in ohms  
 $f$  = frequency, in hertz  
 $L$  = inductance, in henries  
 $C$  = capacitance in farads

Equation 1 shows that the inductive reactance is directly proportional to frequency, and that capacitive reactance is inversely proportional to frequency. With any given coil and capacitor, as the frequency increases the reactance of the coil increases but the reactance of the capacitor decreases. At some frequency, the two reactances will be equal in value. At this exact frequency resonance occurs. At all other frequencies the circuit shown in Figure 1a is merely a series AC circuit, and Figure 1b is just a simple parallel AC circuit.

To find the frequency at which a coil and capacitor will resonate, the resonance formula may be rearranged to solve for  $f$ :

$$f_r = \frac{1}{2\pi\sqrt{LC}} \text{ Equation 2}$$

This formula can be used to find the resonant frequency of any LC circuit. For example, if we have an  $X_L$  of 1,070 ohms and an  $X_C$  of 1,068 ohms, we can see that  $L$  and  $C$  are at a resonant frequency. [ $X_L \approx X_C$  (close enough)] Using the above formula with an inductor of 8  $\mu$ H and capacitance of 7 pF, we can solve for the resonant frequency.

When using Equation 2 with a calculator, use the [EE] or [EXP] key for the exponent (power of 10). Your calculator will then default to a positive exponent. The sign change key [+/-] will change to a negative exponent for millihenries,  $10^{-3}$  or microhenries, ( $10^{-6}$ ) or picofarad ( $10^{-12}$ ). [ENG] key changes any exponent to a metric value, which is to say any exponent that can be divided by three. All of the above exponents are [ENG]. Practice with the following example:

Example 1:	
ENTER	DISPLAY
[CE/C]	0
8 [EXP] [+/-] 6 [X]	0.000008
7 [EXP] [+/-] 12 [=]	5.6 <sup>-17</sup>
[2nd] [ $\sqrt{\quad}$ ]	0.000000007
[X] [6.28] [=]	0.0000000046
[1/X]	21278761.3
[2nd] or [EE]	21.3° or 21.3 MHz

According to the formula, the frequency at resonance is inversely proportional to the square




Figure 1. (a) A series-resonant circuit. (b) A parallel-resonant circuit.

root of either  $L$  or  $C$ . Any time the  $LC$  product is decreased to one-quarter by any means the frequency will be doubled.

Any time the  $LC$  product is increased four times—by quadrupling  $L$ , by quadrupling  $C$ , by doubling both  $L$  and  $C$ , or by any other means—the frequency will be one-half of the original.

## Series Resonant Circuits

In any series circuit containing both  $L$  and  $C$ , the circuit current is greatest when the inductive reactance  $X_L$  equals the capacitive reactance  $X_C$ . Because, under those conditions, the impedance is equal to  $R$ . When resonance occurs, the reactances are equal, and we can derive an equation to calculate the res-

onant frequency of any inductor-capacitor pair using Equation 2.

If the source sees the coil and capacitor together as having a zero voltage-drop across them, it sees them as perfect conductors, or as having zero impedance (Figure 2).

If the reactances are not exactly equal (a nonresonant condition), the voltages do not exactly cancel. The source sees the two reactances as having a resultant voltage-drop across them and therefore as having some value of reactance or impedance.

Theoretically, if a series LC circuit has no resistance, and is connected across a source of AC to which it is resonant, it presents zero reactance, zero resistance, zero impedance, and infinite current!

Continued on page 6




Figure 4. (a) Parallel-resonant circuit. (b) Voltage maximum at resonance.



# Radio Fun

OCTOBER 1993  
issue #27

## editor/publisher

Wayne Green W2NSD/1

## associate publisher

David Cassidy N1GPH

## managing editor

Hope Carrier

## senior/technical editor

Charles Warrington WA1RZW

## editorial associates

Sue Jewell

Joyce Sawtelle

## contributing editors

Bill Brown WB8ELK

Mike Bryce WB8VGE

Joseph E. Carr K4IPV

Michael Geier KB1UM

Carole Perry WB2MGP

Jeffrey Sloman N1EWO

Gordon West WB6NOA

## advertising sales

## representative

Dan Harper

## advertising coordinator

Judy Walker

603-924-0058

800-274-7373

FAX 603-924-9327

## graphic design

Suzanne Self

## desktop page make-up

Linda Drew

## circulation manager

Harvey Chandler

## subscription services

800-257-2346

## Wayne Green, Inc.

## editorial offices

Radio Fun

70 Route 202-North

Peterborough, NH 03458

603-924-0058

FAX: 603-924-9327

RADIO FUN (ISSN 1055-887X) is published monthly by Radio Fun, a division of Wayne Green, Inc., 70 Route 202-N, Peterborough NH 03458. Subscriptions: \$14.00 per year. Canada add \$8.00. Foreign add \$12.00 surface/\$32.00 airmail. Second class postage pending at Peterborough NH and additional mailing offices.

Printed in the U.S.A. by

Lighthouse Press, Manchester, NH

POSTMASTER: Send address corrections to RADIO FUN, P.O. Box 4926, Manchester NH 03108.

Entire contents ©1993 by Radio Fun. No part of this publication may be reproduced without written permission of the publisher.

Reprints: \$2.00 per article. Back issues: \$3.00 each.

# letters



Write to: Radio Fun, 70 Route 202-N,  
Peterborough, NH 03458

Johnny Vines KD4FTG, Bay Minette AL I am a recently licensed (less than two years) amateur radio operator. I have been a subscriber to your outstanding 73 *Amateur Radio Today* and *Radio Fun* for quite some time. I am very thrilled and excited about getting them each month. Honestly—I read them from cover to cover and can hardly wait to get each issue.

I became interested in ham radio while on active duty (Desert Storm). I haven't regretted a single minute of study and preparation for obtaining my code Tech license. Wayne, I'm having a barrel of fun and I hope to upgrade to General next month.

I tremendously enjoy the technical and general information articles and I have built several projects from your magazines. I enjoy your editorials and agree with your views on several subjects. I know that you are an advocate of no-code licensing and I suppose I can share your views on that. I did learn Morse code. I enjoy code, the dits and dahs and frustrations of learning the language. I have no quarrel at all with no-code licensing but I personally chose to go the code route.

In many of your writings you strongly emphasize your opinion that code has no commercial or military value. Although Morse code may be outmoded, outdated and a slow and primitive method of communication, the Department of Defense does feel that it is the most reliable long-distance communication ever, especially in tactical situations.

The Army's Military Intelligence School at Fort Devens, Massachusetts, teaches a 22-week Morse code intercept course. Could it be that Morse code is a basic communication method in Russian doctrine?

The Army and Marine Corps use Morse in tactical operations, and the Air Force Special Forces use Morse. Also, it is used for ship-to-ship and ship-to-shore communication.

The US Army says (*Soldier Magazine*, Feb. 1993) that Morse is still alive and well in the US Army. It has been used in every major US conflict since its invention, including Desert Storm.

... hmph ... Wayne

John Thompson K6OHM, Tustin CA I read David Laustsen's letter (N3LHY) in the August issue regarding CW and licensing and, although I agree with the general theme, I would like to offer another opinion from someone who will soon celebrate 40 years of being a ham. I was licensed as a Novice soon after that class of license was introduced. I'm sure hams already licensed as Generals were opposed to reducing the entry level requirements, just as today many oppose the no-code entry level.

Somehow, ham radio still exists and, even though way back then my Novice license expired before I upgraded, I soon learned the required theory (code was no problem) to pass my General Class exam. Thirty-eight years later I decided to upgrade again and passed the Advanced and Extra exams in a period of three months.

Bob refers to Morse code as something that only old codgers would insist upon keeping and, because ships no longer use it, should be abandoned from the testing requirement. I happen to be one of many people (I'm not an old codger) who likes Morse code (about a third of my QSOs) for several reasons:

1) I can operate my rig at home even during the night (when conditions are better on some bands) and have QSOs without waking other family members. I don't know why, but they get upset when I try to raise an SSB station at 3 a.m., even though I explain the "rarity" of a DXpedition!

2) The mind is a muscle and, like our other muscles, it needs exercise. Believe me, having a QSO with someone going 20 wpm or faster gives that muscle a good workout.

3) Many stations in smaller countries can't afford SSB equipment and the only way to work them is by CW. Several countries in my DXCC total are only on CW.

4) Understanding someone who would speak in an

Continued on page 9

# MFJ's world famous Ham Radio Accessories

Why do more hams throughout the world  
use MFJ accessories than any other brand?  
Because they are value packed and carry  
MFJ's one year unconditional guarantee!

## MFJ Speaker Mics

Compact or miniature models for all popular HTs

Compact Speaker Mics, \$24.95 each:

Once you try an MFJ Speaker Mic you'll never want to be without it. You'll be able to carry your handheld on your belt and never have to remove it to monitor calls or talk.

You'll never have to turn up your audio annoyingly loud to monitor calls because it's handy lapel/pocket clip lets you keep it close to your ear for easy listening.

And you'll never have to clumsily remove your handheld from your belt holder to talk because you can conveniently take the speaker mic in one hand, press the push to talk button and talk. Measure 1 1/4" x 2" x 3"

They come with a lightweight retractable cord that eliminates the dangling cord problem. They feature excellent audio on both transmit and receive. MFJ-284 for Icom or Yaesu; MFJ-286 for Kenwood.

Miniature Speaker Mics, \$24.95 each:

New miniature speaker mics pack all the features of the compact models into a tiny 2" x 1 1/4" x 1/4" package. The lapel pocket clip swivels for even more convenient positioning. Also features transmit LED. Choose from regular or "L" shaped connector. Order MFJ-285 or MFJ-285L for Icom or Yaesu, MFJ-287 or MFJ-287L for Kenwood. MFJ-283 for dual plug Alinco.

MFJ-284 or MFJ-286

\$2495



MFJ-283, MFJ-285, MFJ-285L, MFJ-287 or MFJ-287L

\$2495



## Deluxe 300 W Tuner



MFJ-949D MFJ-949D is the world's most popular 300 watt PEP tuner. It covers 1.8-30 MHz, gives you a new peak and average reading Cross-Needle SWR/Wattmeter, built-in dummy load, 6 position antenna switch and 4:1 balun -- in a compact 10 x 3 x 7 inch cabinet. Meter lamp uses 12 VDC or 110 VAC with MFJ-1312, \$12.95.

## SWR Analyzer

MFJ's innovative new SWR Analyzer gives you a complete picture of your antenna SWR over an entire band -- without a transmitter, SWR meter or any other equipment!

Simply plug your antenna into the coax connector, set your SWR Analyzer to the frequency you want and read your SWR. You can instantly find your antenna's true resonant frequency, something a noise bridge can't do. Covers 1.8-30 MHz (or choose MFJ-208, \$89.95 for 2 Meters). Use 9 V battery or 110 VAC with MFJ-1312, \$12.95.

## VHF SWR/Wattmeter

MFJ-812B MFJ-812B \$2995

Covers 2 Meters and 220 MHz. 30 or 300 Watt scales. Also reads relative field strength 1-170 MHz and SWR above 14 MHz. 4 1/2 x 2 1/4 x 3 in.

## MFJ Multiple DC Outlet

MFJ-1112 MFJ-1112 \$2995

New MFJ DC Power Outlet saves you space and money. Hook it to your 12 VDC power supply and get 6 DC outlets for connecting your accessories. RF bypassing keeps RF out of power supply from DC line outlet. 13 1/2 x 2 3/4 x 2 1/2 in.

## 12/24 Hour LCD Clocks

MFJ-108B MFJ-108B \$1995 MFJ-107B MFJ-107B \$995

Huge 5/8 inch bold LCD digits let you see the time from anywhere in your shack. Choose from the dual clock that has separate UTC/local time display or the single 24 hour ham clock.

Mounted in a brushed aluminum frame. Easy to set. The world's most popular ham clocks for accurate logs. MFJ-108B 4 1/2 x 1 x 2; MFJ-107B 2 1/4 x 1 x 2 in.

## MFJ Cross-Needle SWR/Wattmeter

MFJ Cross-Needle SWR/Wattmeter has a new peak reading function! It shows you SWR, forward and reflected power in 2000/500 and 200/50 watt ranges. Covers 1.8-30 MHz.

Mechanical zero adjusts for movement. SO-239 connectors. Lamp uses 12 VDC or 110 VAC with MFJ-1312, \$12.95.

## Deluxe Code Practice Oscillator

MFJ-557 MFJ-557 \$2495

MFJ-557 Deluxe Code Practice Oscillator has a Morse key and oscillator unit mounted together on a heavy steel base so it stays put on your table. Portable because it runs on a 9-volt battery (not included) or an AC adapter (\$12.95) that plugs into a jack on the side.

Tone and Volume controls for a wide range of sound. Speaker, earphone jack. Key has adjustable contacts and can be hooked to transmitter. 8 1/2 x 2 1/4 x 3 3/4 in.

Nearest Dealer/Orders: 800-647-1800

MFJ ENTERPRISES, INC.  
Box 494, Miss. State, MS 39762  
(601) 323-5869; FAX: (601) 323-6551  
TELEX: 53 4590 MFJ STKV

• One year unconditional guarantee • 30 day money back guarantee (less s/h) on orders from MFJ • Add \$5.00 each s/h • FREE catalog MFJ... making quality affordable

CIRCLE 86 ON READER SERVICE CARD



# Resonance

Continued from page 4

## Parallel Resonant Circuits

Resonance in parallel circuits occurs when  $X_L = X_C$ , as in series circuit resonance. In Figure 3, for a specific inductor and a specific capacitor, the point where the two curves cross ( $X_L = X_C$ ) is called resonant frequency. When a parallel circuit has equal  $X_L$  and  $X_C$ , the external circuit current is equal to that flowing through the parallel resistance. If the circuit contains no parallel resistance, the external current is zero. A coil and capacitor connected as in Figure 4a form a parallel AC circuit. If  $X_L$  and  $X_C$  have the same reactance to the frequency of the AC source, the circuit is known as parallel resonant. In Figure 4a let  $X_C$  equal 100 ohms and  $X_L$  equal 100 ohms; with a source voltage of 100 volts we can calculate the current.

If the capacitor is temporarily disconnected, leaving the 100Ω reactance coil across the 100 V source, according to Ohm's law the AC circuit current in the coil will be:

$$I = \frac{V}{X_L} = 1 \text{ amp}$$

If the 100Ω reactance capacitor is reconnected across the coil, 1 amp of current will flow in the capacitor. In a parallel resonant circuit you read equal voltage across the coil and the capacitor. In the inductive branch, the cur-

rent lags the source voltage by 90 degrees, and in the capacitive branch the current leads the source voltage by 90 degrees. Since the two currents are 180 degrees out of phase, at any instant that current is flowing down through the coil and equal current must be flowing up into the capacitor.

This circulating current flows between the two reactances, but no current flows into and out of the source. Because the source is supplying no current, it should be possible to disconnect the source and the current should continue to oscillate back and forth between the capacitor and the inductor in Figure 4a indefinitely. With no resistance or losses in the circuit, this would be true. This ability of a resonant circuit to sustain electron oscillation is known as the flywheel effect because of its similarity to the action of a mechanical flywheel, which, once started, tends to keep going until stopped by friction or other losses.

Calculating the resonant frequency of a parallel circuit is exactly the same as for a series resonance circuit.

Remember, in Figure 3, for a specific inductor and a specific capacitor, the point where the two curves cross ( $X_L = X_C$ ) is called resonant frequency. With pure reactance and zero resistance in the circuit, the source current is zero. With resistance in series with either branch, source current increases, and reactive currents decrease. That is to say, at resonance parallel circuit voltage is at maximum!

## Calculating Component Values for Resonance

We can calculate either the inductance L or capacitance C to resonate with a certain component at a specific frequency:

$$L = \frac{1}{(2\pi f)^2 C}$$

Example 1: What value of L resonates with a 106 pF capacitor at 1,000 kHz?

ENTER	DISPLAY
[CE/C] 0	
[I] [6.28] [X] 1 [EXP] 3 [D] [X] <sup>2</sup>	39438400
[X] 106 [EXP] [+/-] 12 [=]	0.00418047
[1/X]	239.2075303 or 239Ω

Example 2: What value of L resonates with a 200 pF capacitor at 7,200 kHz?

ENTER	DISPLAY
[CE/C]	0
[I] [6.28] [X] 7.2 [EXP] 6 [D] [X] <sup>2</sup>	2.044486656 <sup>15</sup>
[X] 200 [EXP] [+/-] 12 [=]	408897.3312
[1/X]	0.000002445
[2nd] [ENG]	2.44 <sup>-06</sup>

Example 3: What value of C resonates with a 239 μH inductor at 1,000 kHz?

ENTER	DISPLAY
[CE/C]	0
[I] [6.28] [X] 1 [EXP] 3 [D] [X] <sup>2</sup>	39438400

[X] 239 [EXP] [+/-] 6 [=]	9425.7776
[1/X]	0.000106092
[2nd] [ENG]	106 <sup>-6</sup>

Finding L from  $X_L$ : Not only can  $X_L$  be calculated from f and L, but if any two factors are known, the third can be found. Very often  $X_L$  can be determined from voltage and current measurements. With the frequency known, L can be calculated as:

$$L = \frac{X_L}{2\pi f}$$

Example 4: A coil with negligible resistance has 62.8 volts across it with 0.01 A of current. What is the inductive reactance  $X_L$ ?

$$X_L = \frac{V_L}{I_L} = \frac{62.8V}{0.01A} = X_L = 6,280\Omega$$

Example 5: Calculate the L of an inductor that has a 15,700Ω  $X_L$  at a frequency of 10 MHz.

ENTER	DISPLAY
[CE/C]	0
[I] [15,700] [D] [+/-] [I]	0
[6.28] [X] 10 [EXP] 6 [D]	62,800,000
[=]	0.00025
[2nd] [Eng]	250 <sup>-06</sup>

If this calculation is performed without parentheses, the algebraic hierarchy completes the multiplication before the addition. Without parentheses the result is 2.5<sup>10</sup>H.

In my next article I will discuss impedance and the Q of a circuit. **RF**

**Sell your product in Radio Fun**  
**Call today 1-800-274-7373**

# BATTERIES

## REPLACEMENT BATTERIES (ALL NEW—MADE IN USA)

### ICOM

7S	13.2v	1400 mah	\$53.00
8S	9.6v	1400 mah	\$51.00
BP7	13.2v	600 mah	\$53.00
BP8	8.4v	1400 mah	\$50.00

### SA/SAT

BP82, BP83			
BP84	7.2v	1000 mah 3"	\$40.00
BP85B	12v	600 mah 3"	\$69.00

### KENWOOD

PB1	12v	@	1100 mah	\$59.00
KNB-3	7.2v	@	1200 mah	\$38.00
KNB-4	7.2v	@	2200 mah	\$59.00
PB6	7.2v	@	750 mah	\$35.00
PB7	7.2v	@	1500 mah	\$49.00
PB8	12v	@	800 mah	\$49.00
PB-13	7.2v	@	750 mah	\$37.00
PB-14	12v	@	800 mah	\$49.00
PB-18	7.2v	@	1500 mah	\$47.00

### YAESU

FNB-2	10.8v	600 mah	
FNB-4	12v	750mah	\$39.00
FNB-4A	12v	1000 mah	\$55.00
FNB-17	7.2v	600 mah	\$30.00
FNB-10S	7.2v	1000 mah	\$42.00
FNB-12S	12v	600 mah	\$42.00
FNB-25	7.2v	600 mah	\$35.00
FNB-26	7.2v	1100 mah	\$44.00
FNB-26S	7.2v	1500 mah	\$49.00
FNB-27S	12v	800mah	\$49.00

### ALINCO

EBP-10N	7.2v	@	700 mah	\$35.00
EBP-12N	12v	@	700 mah	\$47.00
DJ-F1T				
EBP-16N	7.2v	@	750 mah	\$37.00
EBP-18N	12v	@	600 mah	\$47.00
DJ-180 DJ-580				
EBP-20N	7.2v	@	800 mah	\$34.00
EBP-20NX	7.2v	@	1500 mah	\$44.00
EBP-22N	12v	@	800 mah	\$49.00

## FAST AND STANDARD DESK CHARGERS FOR

**YAESU, KENWOOD, ICOM, ALINCO and MOTOROLA.**

These "SMART" Chargers Will Rapid Charge 6 Volt to 12 Volt Batteries in 1/2 Hour To Two Hours (depending on Battery Capacity)

Many Advanced Features Not Available On Any Other Charger.

★ ★ ★ ★ SPECIAL INTRODUCTORY PRICES ★ ★ ★ ★

Made in U.S.A.

### INSERTS

#### CALL FOR LOWEST PRICES

ALINCO 10N, 12N  
AZDEN 3000, 4000  
ICOM BP-2, 3, 5, 7, 8, 7S, 8S  
KENWOOD PB-21, 21H, 25, 26  
REGENCY MT1000, HX1200  
SANTEC 142, 144  
STANDARD BP-1  
TEMPO S-1, 2, 4, 5, BP-15, S-15  
TEN TEC 2991, 2591  
UNIDEN (BEARCAT)

### CAMCORDER

PANASONIC PB 80/88 ORIG. PAN.	\$39.00
SONY NP77H	2400 mah \$39.00
SONY NP55	1000 mah \$29.00
SONY NP221	500 mah \$29.00
CANON 8mm	2000 mah \$36.00
PANASONIC PALM	2400 mah \$39.00
JVC GR TYPE C	1500 mah \$36.00
SHARP BT21/22	\$45.00
RCA/HITACHI 8mm	2400 mah \$39.00

ALL BRANDS AVAILABLE

### NEW HIGH CAPACITY KENWOOD

PB-18	7.2v	1500 mah
<b>YAESU</b>		
FNB-25	7.2v	600 mah
FNB-26	7.2v	1000 mah
FB-26S	7.2v	1500 mah
FNB-27	12v	600 mah
FNB-27S	12v	800 mah

### POWER PACKS

EXTENDED TIME-5 WATT POWER  
12 VOLTS-4 AMPS  
FOR MOST TWO WAY RADIOS  
INCLUDES  
12V-4 AMP BATTERY  
CONNECTOR FOR RADIO  
AC/DC CHARGER  
HEAVY DUTY POUCH & BELT

\*ALL BATTERY PACKS—GUARANTEED TO HAVE THE ADVERTISED CAPACITY

SEND FOR  
FREE CATALOG

DEALER INQUIRIES  
WELCOME

## BATTERY-TECH, INC.

28-25 215 PLACE, BAYSIDE, N.Y. 11360 FAX 718-461-1978

**800-442-4275 — N.Y.S. 718-631-4275**



VISA



MASTER CARD



DISCOVER

CIRCLE 105 ON READER SERVICE CARD



# My Recent Experiences with QRP

by Robert Capon WA3ULH

I launched my amateur radio "career" 19 years ago, but I only recently discovered QRP as a new facet of my hobby. During the past eight months, with 5 watts or less, I have worked all continents, worked 151 DXCC countries (102 confirmed), and established a QSO with a station in South Africa with 20 milliwatts. And I've had a terrific time.

I got started with QRP in a rather odd way. I had worked over 250 DXCC countries, and was lamenting the difficulty of finding new ones. As I told my wife and kids: "All of the easy countries (defined as countries inhabited by humans, not penguins, and having one or more active hams) have been worked." I was spending most of my time waiting for DXpeditions to new countries. In between DXpeditions, I was getting bored.

I reasoned that if I set a new goal, I could re-energize my enjoyment of my hobby. I made a fateful decision to try to work DXCC with 5 watts or less, and the adventure began.

The only new piece of equipment that I needed for my already-equipped HF station was a QRP transceiver. I purchased the modestly priced MFJ-9020 QRP transceiver, a bare-bones CW rig. It doesn't have a lot of bells and whistles, but it transmits a clean signal and has an excellent superhet receiver that compares with my full-featured HF rig. If you select the MFJ, I strongly recommend the inexpensive built-in CW filter and keyer options. Loaded with these options, you can pick up the MFJ-9020 for around \$200. If you really want a full-featured QRP HF transceiver, the Ten-Tec Argonaut II has an excellent reputation.

## Re-Creating the Old Excitement

On May 21, 1992, I made my first tentative calls to DX stations. Two calls. Three calls. Nothing. Did my transceiver work? Was my signal getting out? Can 5 watts really work DX? I was getting nervous about QRP.

I powered up my big HF station, and turned down the power to 10 watts. I easily worked UC2AKP in Byelorussia on my first call. I went back to the MFJ running 5 watts and

called UC1CWH. Success! He came back to me, and gave me a respectable 559. I operated for four hours that evening and worked 11 DXCC countries, including VK2CWS in Australia. Not bad for 5 watts. I was hooked.

A funny thing happened. I began to experience the excitement of working new ones that I had worked when I was a Novice. Now, with QRP, I re-experienced the excitement of working new countries all over again. I worked a station in Belgium for my 51st country, and was thrilled. Thrilled to work Belgium?

Another funny thing happened. A lot of the DX stations that I worked congratulated me for the contact, and shared their excitement. My log includes some of these entries: "Congrats on QRP," "QRP doing nice job," "VFB copy. FB job."

A lot of DX stations also wanted to know what type of antenna I was using. In 19 years, I can't remember a DX station asking me that question. Today, when operating QRP, many people ask me about my station and antenna.

By September 1, 1992, in less than four months, I had logged contacts on all continents and with 90 DXCC countries. My antenna was a simple ground-mounted Butternut vertical, with a pretty good system of underground radials. My countries included some pretty fair DX, including: Tonga, San Andreas, Kuwait, Fernando de Noronha, Lebanon, Kalinograd, Asiatic Russia, New Caledonia and many others.

On September 2, 1992, I put a Cushcraft A3S triband beam into service, and I have been very pleased with the results. (Actually, I refer to my Cushcraft as "my unfair competitive advantage.") With the tribander, operating at a modest 35 feet, I have been able to break through pretty substantial pile-ups to work rare DX with QRP. In good band conditions, I have received excellent reports, including 579 reports from Central African Republic and Mozambique, running 5 watts.

The beam also brought out a latent competitive spirit in my ham hobby. Remember the feeling you had when you broke through your first pile-up? Well, imagine how I felt when C9RJJ in Mozambique came back to




Photo A. The author, Rob WA3ULH, at his station with the MFJ-9020 QRP transceiver. He is holding the QSL card from a QSO with ZS6KO.

WA3ULH/QRP, knowing that the bigger stations were on the sidelines waiting for their turn behind a 5 watt station!

By December, I had worked almost 150 DXCC countries and was thinking about a new challenge. I wondered if I could work DXCC using only 1 watt output.

I'm not a highly technical ham, but the MFJ instructions for tuning down the power seemed easy enough. On December 21 I opened up the radio, found the right thing to turn, and made a simple adjustment to reduce power to 1 watt. I sighed a heavy sigh of relief when I put the radio together, and it still worked fine. I must admit that at 1 watt I began to feel a bit like the proverbial Maytag man: "The loneliest guy in town." However, while many stations couldn't hear my meager 1 watt signal, using the beam I was able to work DX when conditions were favorable. I quickly learned to focus on stations coming in solidly at 579 or better. I realized that if I heard a weak station operating at 100 watts, he was unlikely to hear my 1 watt signal.

## Collaboration at 1 Watt

On December 24, I made a fateful contact that would lead to one of the most rewarding experiences of my 19-year ham career. I heard a rather weak station calling from South Africa. The signal was very light, so I was about to tune past him, realizing that he wouldn't be able to hear my call. However, the station signed ZS6KO/QRP and, assuming that he was using 5 watts or less, I gave him a call. He was actually running only 1 watt, and we had established a two-way 1 watt QSO at a distance of 8,160 miles. I gave him a 339, and in return I received a whopping 419.

This fateful QSO was the beginning of a new friendship with Bill Ingleson ZS6KO. He and I agreed to meet every night at 0400 UTC to see if we could work with less power, and to find one night with superb conditions to see how low we could go. Since we knew each other's callsigns, we established our own minimum standard: For a contact to be valid, we had to copy a signal report.

I purchased an inexpensive Ten-Tec model 290 attenuator to make it easier to reduce power. The attenuator takes a 5 watt input, and enables you to step between seven power output levels: 5W, 2.5W, 1.0W, 500 mW, 250 mW, 100 mW and 20 mW. I was conservative by using only 4.7 watts input to the attenuator.

The attenuator has been a great resource. But be prepared for one surprise: It attenuates both the transmitter and the receiver. This is not a problem when you are working a loud station who starts out at 599 plus 20 dB, but it becomes a problem when you are working another QRP station. I overcame this problem by using my attenuated MFJ transceiver and my ICOM 735 transceiver as a separate transmitter/receiver combination. ZS6KO and I met every night looking for optimum conditions. Bill had copied me at 100 mW, and I had a solid QSO with his station running at 250 mW.

As our project continued, we developed the habits of checking propagation information on station WWV at 18 minutes after each hour, and listening to the 20 meter beacons on 14,100 kHz. The beacons, which are described in Chapter 2 of the ARRL *Operating Manual*, are an excellent resource to QRPers because they broadcast tones at staged power levels:

Continued on page 8




Photo B. Bill Ingleson ZS6KO with his home-brew QRP transceiver.



# RF<sup>kit</sup> review

Lectrokit  
401 W. Bogard Rd.  
Sandusky OH 44870  
Price Class: SP1-BBM (bare PC board with manual)—  
\$12 postpaid  
SP1-PC (PC board, manual, all PC board parts)—\$29  
SP1-Kit (complete kit, including case)—\$39  
SP1-AT (assembled Spider, 80, 40, or 30)—\$59  
AF-1 (audio bandpass filter kit)—\$6  
Shipping (except SP1-BBM)—\$4  
(Ohio residents please add 6% tax)

## Lectrokit SP-1 Spider

by Jim Cates WA6GER

The January 1993 issue of 73 magazine has a cover-feature construction article by Mike Agsten WA8TXT. It is a QRP transceiver—crystal-controlled on BOTH transmit and receive. It is called the “Spider.” It can be set up for 80, 40, or 30 meters.

I read the article, mainly because I read everything related to QRP. But my interest was not aroused, remembering all the frustrations of my crystal-controlled Novice days.

Here the matter remained, until Forest N6ZBZ put one of these Spiders on 40 and asked me to listen for him, portable in Phoenix. He was Q5 copy at my QTH in Sacramento, even though his antenna was a dipole only 10 feet off the ground. Good solid QSO.

This grabbed my attention like a . . . well, a spider bite. Monkey see; monkey do. So naturally I had to have one. On 40, of course, my favorite band. I dug out the issue of 73, checked the old junk box, and got out some catalogs to price a couple of needed parts. Gazooks! These minimum order restrictions! Forget it! And I'm not one for kits; too many irritating past experiences.

But hark! A footnote: Lectrokit offers the board and all surface mounted parts for . . . for only \$29? Hey, for 29 bucks I'm starting to like kits.

This one arrived quickly (like return mail?). So, I snipped open the padded envelope to find out what was inside.

### What's in the Kit?

To begin with, the instructions are so complete as to make assembly 99% foolproof. Definitely a beginner's project. (Blushingly, I confess I am the reason why the kit is not 100%

foolproof. I managed to install Q6 upside-down on the board; not easy with the overlay, which was clearly marked, right in front of me.)


The instructions and the parts are in separate plastic envelopes. And when I say instructions, I mean with CAPITAL LETTERS. Like 16 pages—everything from how to read resistor and capacitor values to a drilling template. Pictorial diagrams, schematic; it's all there. Simply too much to permit a detailed description, so let the table of contents suggest the extent:

1. Fundamentals of component installation
2. PC board assembly
3. Band selection
4. Top panel assembly and wiring
5. Tune-up and operation
6. In case of difficulty
7. Schematic diagram
8. Mechanical drawings
9. Pictorial wiring diagram
10. PC parts overlay

In addition to all the above, there were also step-by-step check-off assembly instructions, making this the most failure-proof kit since Heath.

Is the kit complete? Bet your sweet patootie it is. There's solder included, and even an abrasive pad to scour the circuit board to remove the fingerprints you put on it while turning and eyeballing. All the parts are there. None of this typical product review stuff like: “I phoned XYZ company and they sent the missing parts . . . etc.” This kit is complete; I mean, no missing parts. And, they are supplied in bags, permitting bite-sized assembly chunks, letting you follow a logical-sequence assembly.

OK, so now you have it all assembled. How easy is it to tune up? Apple pie. Peak one trans-



former for RF out, one for maximum received signal strength (loudness). That's it. Period.

### Performance

How well does this rig work? Is it practical? Yes, oh yes, yes, yes. In a month of casual operating, around 0800-0900 Pacific time, on my two crystal frequencies, 7120 & 7125, I have worked and confirmed seven states, and I still snag a QSO almost every day.

At night there are the usual foreign broadcast problems, same as you hear from your megabuck rig. But I've worked east to

the Great Lakes.

Is 1 watt enough? Believe me, 559 to 599 reports are common. Do you need a CW filter? After all, the receiver bandpass is admittedly a tad broad. Hey, this is a simple rig. Naw, the best filter is the one between your ears. Learn to use it!

I now have three Lectrokit Spiders. And they have put fun back into hamming. I love the challenge: 1 watt, crystal control, 40 meter QRM and QRN. Honestly, it isn't that big a deal, but it's entirely practical. And, if 40 isn't your cup of tea, put yours on 80 or 30. You'll love it, and that's a promise. **RF**

## My Recent Experiences with QRP

Continued from page 7

100W, 10W, 1W, and 100 mW. Conveniently, there is a beacon in South Africa for me to monitor, and a beacon on the East Coast for Bill.

Our goal was to work each other at 20 mW, an excruciating 37 dB drop from full power at 100 watts, and a 24 dB drop from 5 watts. Working at 20 mW seemed like working with a 5 watt input into a coat-hanger antenna. Night after night, nothing came through at 20 mW. Not a peep. In the meantime, I did manage to work stations freestyle in Vancouver, Seattle, and San Francisco at 20 mW. These contacts put me over the 100,000 mile per watt mark, but the signal was not audible in Pretoria.

However, on January 14 our patience was rewarded with superb band conditions. Solar Flux was 141, and the A-index of the geomagnetic field was a relatively quiet 08. These represented excellent conditions at this stage of the sunspot cycle. I easily heard Bill's sig-

nal running at 100 mW, and band conditions were still picking up.

I dropped my power to 20 mW, while Bill was operating QRO at 100 watts. At full power Bill was operating at 599 plus 20 dB. But I didn't want to send him a 599 report because I wanted to make absolutely certain that he could hear my 20 mW signal. I threw him a curve ball, and gave him a report of 579. He copied the report: “R R R QSL 579 FB ROB CONGRATS.”

I went QRO and gave Bill a chance to get through at 20 mW. The band was quiet. I put my headphones on and listened for his signal. His signal was extremely light. I half heard it and half felt it as the signal faded above and below the noise level. I asked him to repeat the report and as he strengthened above the noise level, I clearly heard my 589 report. He threw me a curve ball, too! We had achieved a respectable 408,000 miles per watt.

Band conditions were excellent, and we decided to take advantage of propagation by establishing a two-way QSO at ultra low power. We dropped to 250 mW and had “arm-chair” copy. At least it seemed like easy copy after working him at 20 mW. I gave Bill a 429, and I received a 329 in return. While operating at 250 mW we agreed to drop power to 100 mW, and we enjoyed a nice two-way QSO without too much difficulty. On this particular band opening, 100 mW seemed like “arm-chair copy.”

Upon reflection, I realize that I am not the first amateur to work 150 countries with 5 watts, and that working 408,000 miles per watt is by no means a world record. I am not a radio pioneer. But these QRP experiences have re-energized my enjoyment of amateur radio, and have opened a new facet to my enjoyment of our wonderfully diverse hobby. It has given me the opportunity to set and achieve

new goals, to learn new operating techniques, and to make new friends. It's been a lot of fun.

Bill Ingleson and I have talked about building “monster fixed beams” pointed at one another, and shooting for two-way contact with even less power, during the next solar sunspot peak.

I'm still actively chasing new countries on my large HF station, and I am inching forward on my goal of reaching the DXCC honor roll (286 countries worked, and at my present rate, it will only take another 19 years to make the honor roll). In the meantime, QRP has done a great job filling in the spaces between DXpeditions. Lately, I've been having lots of fun with solar power, and am now working DX with a solar-powered battery.

Maybe its time for you to give QRP a try and get in on the fun. In the meantime, do me a favor. Whenever you hear a station signing “/QRP,” give him a call! **RF**



## letters

### Continued from page 5

accent hard to decipher is no problem with CW... there are accents. Even though I took French in school many years ago I only really speak English fluently. Fortunately, most SSB stations speak in English and that helps me, but the accents can quite often make the conversation very hard to understand. CW has distinctive "fists," but unless your QSO is with someone who runs their words together (pet peeve), it is very easy to understand.

I don't have a bumper sticker on my car that says "I Love CW," but I really hope that the fun I have on CW is not denied new amateurs who will be licensed in the years to come.

**Vern Snyder, Duluth GA** I enjoy receiving *Radio Fun* every month—it is a great magazine for new hams.

I will be taking the Novice test next month and I would like to ask you some questions. I don't have a lot of money to invest in equipment. Some hams in the area tell me that I should purchase a transceiver such as a Yaesu or Kenwood. I can swing an SB-102, HW-101, or a Heathkit SB-401 and 303 combination. Since Heath is now out of business, would you advise me to purchase one of the above? I would rather use a rig that is not a cold machine, one that I can get involved with rag-chewing and code on 15 meters. Any advice you may give me will be deeply appreciated.

**Vern—Any of the tube rigs of that vintage will make a neat first rig. I had a used HW-101 for years. As long as you can test before you buy, you'll get years of fun out of those old rigs... David NIGPH**

**Rege Dvorsky WA3LKT, Grasonville MD** Lately I have been seeing bulletins on packet stating that the FCC has relaxed rules as to what type of conversations can take place over amateur radio. I find it very disappointing to see that hams will be ordering pizza and making doctor's appointments on our frequencies. I have been a ham since 1968 and active most of those years and find that the more the rules are relaxed, the more the bands seem to experience a degradation in the quality of operating.

It seems the trend of new radio rules is to ease up on the requirements of radio operators and to let anything go. This, to me, does not seem to be for the best of the hobby. At some point in time there have to be some rules and some discipline. We seem to be leaning more and more towards what could be a business-band radio (ordering pizzas, making doctor's appointments, calling into work sick). I did not realize that this was the intent of our bands. It scares me that the trend is to relax the restrictions so much that gradually there will be no difference between the ham bands and the business bands or citizens band or marine bands. A little discipline and making a few requirements for the privilege of operating does not seem too much to ask. Giving your children anything they want does not always produce the best child.

I would hate to see someone going to take a test for their ham license so that they can call in to work or or make business and personal phone calls for the price of a repeater membership fee. This is not what ham radio is all about. I can see being a public service, but this is now a little extreme as far as I can see. The more ham radio fre-

quencies become intertwined with businesses, it seems inevitable that we are absorbed or taken over. At what point do you separate the two and at what point do you draw the line? We are a hobby... not a necessity to carry on everyday business. That is what keeps us separate and keeps us the special entity we are. I hope

the line is drawn somewhere.

**Rege—I've been hamming since 1938. For years we ordered pizza and made restaurant reservations with no one being hurt. But you can carry any privilege to an extreme and spoil it. The FCC has merely restored things, so stop with the commercial and CB baloney... Wayne** RF

**ASTRON CORPORATION**

9 Autry  
Irvine, CA 92718  
(714) 458-7277 • FAX (714) 458-0826



MODEL VS-50M


### SL SERIES



### RS-L SERIES



### RM SERIES



MODEL RM-35M

### RS-A SERIES




MODEL RS-7A

### RS-M SERIES



MODEL RS-35M

### VS-M AND VRM-M SERIES



MODEL VS-35M

### RS-S SERIES



MODEL RS-12S

## ASTRON POWER SUPPLIES

• HEAVY DUTY • HIGH QUALITY • RUGGED • RELIABLE •

### SPECIAL FEATURES

- SOLID STATE ELECTRONICALLY REGULATED
- FOLD-BACK CURRENT LIMITING Protects Power Supply from excessive current & continuous shorted output
- CROWBAR OVER VOLTAGE PROTECTION on all Models except RS-3A, RS-4A, RS-5A, RS-4L, RS-5L
- MAINTAIN REGULATION & LOW RIPPLE at low line input Voltage
- HEAVY DUTY HEAT SINK • CHASSIS MOUNT FUSE
- THREE CONDUCTOR POWER CORD except for RS-3A
- ONE YEAR WARRANTY • MADE IN U.S.A.

### PERFORMANCE SPECIFICATIONS

- INPUT VOLTAGE: 105-125 VAC
- OUTPUT VOLTAGE: 13.8 VDC  $\pm$  0.05 volts (Internally Adjustable: 11-15 VDC)
- RIPPLE Less than 5mv peak to peak (full load & low line)
- All units available in 220 VAC input voltage (except for SL-11A)

### • LOW PROFILE POWER SUPPLY

MODEL	Colors Gray Black	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
SL-11A	• •	7	11	2 5/8 x 7 1/8 x 9 3/4	12
SL-11R	• •	7	11	2 5/8 x 7 x 9 3/4	12
SL-11S	• •	7	11	2 5/8 x 7 1/8 x 9 3/4	12
SL-11R-RA	• •	7	11	4 3/4 x 7 x 9 3/4	13

### • POWER SUPPLIES WITH BUILT IN CIGARETTE LIGHTER RECEPTACLE

MODEL	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
RS-4L	3	4	3 1/2 x 6 1/8 x 7 1/4	6
RS-5L	4	5	3 1/2 x 6 1/8 x 7 1/4	7

### • 19" RACK MOUNT POWER SUPPLIES

MODEL	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
RM-12A	9	12	5 1/4 x 19 x 8 1/4	16
RM-35A	25	35	5 1/4 x 19 x 12 1/2	38
RM-50A	37	50	5 1/4 x 19 x 12 1/2	50
RM-60A	50	55	7 x 19 x 12 1/2	60
• Separate Volt and Amp Meters				
RM-12M	9	12	5 1/4 x 19 x 8 1/4	16
RM-35M	25	35	5 1/4 x 19 x 12 1/2	38
RM-50M	37	50	5 1/4 x 19 x 12 1/2	50
RM-60M	50	55	7 x 19 x 12 1/2	60

MODEL	Colors Gray Black	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
RS-3A	• •	2.5	3	3 x 4 3/4 x 5 1/4	4
RS-4A	• •	3	4	3 3/4 x 6 1/2 x 9	5
RS-5A	• •	4	5	3 1/2 x 6 1/8 x 7 1/4	7
RS-7A	• •	5	7	3 3/4 x 6 1/2 x 9	9
RS-7B	• •	5	7	4 x 7 1/2 x 10 3/4	10
RS-10A	• •	7.5	10	4 x 7 1/2 x 10 3/4	11
RS-12A	• •	9	12	4 1/2 x 8 x 9	13
RS-12B	• •	9	12	4 x 7 1/2 x 10 3/4	13
RS-20A	• •	16	20	5 x 9 x 10 1/2	18
RS-35A	• •	25	35	5 x 11 x 11	27
RS-50A	• •	37	50	6 x 13 3/4 x 11	46
RS-70A	• •	57	70	6 x 13 3/4 x 12 1/2	48

MODEL	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
• Switchable volt and Amp meter RS-12M	9	12	4 1/2 x 8 x 9	13
• Separate volt and Amp meters				
RS-20M	16	20	5 x 9 x 10 1/2	18
RS-35M	25	35	5 x 11 x 11	27
RS-50M	37	50	6 x 13 3/4 x 11	46
RS-70M	57	70	6 x 13 3/4 x 12 1/2	48

### • Separate Volt and Amp Meters • Output Voltage adjustable from 2-15 volts • Current limit adjustable from 1.5 amps to Full Load

MODEL	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
	@13.8VDC @10VDC @5VDC	@13.8V		
VS-12M	9 5 2	12	4 1/2 x 8 x 9	13
VS-20M	16 9 4	20	5 x 9 x 10 1/2	20
VS-35M	25 15 7	35	5 x 11 x 11	29
VS-50M	37 22 10	50	6 x 13 3/4 x 11	46

### • Variable rack mount power supplies

MODEL	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
VRM-35M	25 15 7	35	5 1/4 x 19 x 12 1/2	38
VRM-50M	37 22 10	50	5 1/4 x 19 x 12 1/2	50

MODEL	Colors Gray Black	Continuous Duty (Amps)	ICS* (Amps)	Size (IN) H x W x D	Shipping Wt. (lbs.)
RS-7S	• •	5	7	4 x 7 1/2 x 10 3/4	10
RS-10S	• •	7.5	10	4 x 7 1/2 x 10 3/4	12
RS-12S	• •	9	12	4 1/2 x 8 x 9	13
RS-20S	• •	16	20	5 x 9 x 10 1/2	18
SL-11S	• •	7	11	2 5/8 x 7 1/8 x 9 3/4	12

\*ICS—Intermittent Communication Service (50% Duty Cycle 5min. on 5 min. off)


CIRCLE 16 ON READER SERVICE CARD



# RF vintage review

## The Hallicrafters SX-140K

by Donald A. Smith W3UZN and Kent A. Mitchell W3WTO



Are you in the market for a receiver in the \$100 to \$125 price range, but undecided whether to purchase a commercially-built set or one in kit form? Why not combine the advantages of both and consider the Hallicrafters SX-140K? This is the companion receiver for the HT-40K transmitter kit as described in the May 1962 issue of *73 Magazine*. A ham-band-only receiver, the SX-140K covers 80 through 6 meters.

Lest you have misgivings concerning constructing a receiver because of the usual associated task of RF and oscillator stage alignments, let us hasten to mention that the SX-140K receiver kit is supplied with a completely aligned and wired bandswitch assembly.

The receiver incorporates a pentode RF amplifier, one half of a 6AZ8, with a manual RF gain control in series with its cathode. A 6U8A is used as the local oscillator-mixer stage, its output fed to a 6BA6 IF amplifier. The oscillator frequency is varied by a main tuning capacitor. No fine-tuning control is necessary, due to the 25-to-1 tuning ratio of the main tuning, which is very adequate for the 6-inch-per-band of slide-rule dial provided. The selectivity-BFO control in the suppressor grid of the IF stage is actually a regeneration control and effectively varies the selectivity of the stage from approximately 8 kHz to 2 kHz. Advancing the control until the stage breaks into oscillation provides a beat note for CW and SSB reception. Operation and adjustment of this control is both simple and effective.

The IF output signal is coupled to a 6T8A, which not only functions as the detector and first audio amplification stages but performs as noise limiter and AVC control stages as well. Noise limiting is by diode action and AVC by the conventional feedback method.

The tetrode section of a 6AW8A is the audio output stage and is connected through an output transformer to a pair of terminals on the rear chassis apron and to a headphone jack on the front panel. Though there is no built-in speaker, there is enough cabinet space for a 3" x 5" speaker to be mounted on the top of the receiver cabinet by the more enterprising builder.

The remaining triode section of the 6AW8A is incorporated as the S-meter amplifier. It must really amplify, too, as the S-meter calibration goes up to 90 dB above S9! The meter is disabled in the CW-SSB mode to prevent the needle from pegging and otherwise flopping around unnecessarily.

An unusual, useful, and welcome feature, especially for a receiver in this price category, is the inclusion of a crystal-controlled calibration oscillator. With the oscillator (the triode section of the 6AZ8) operating at the crystal frequency of 3.5 MHz, fundamental and even harmonic signals are injected into the local oscillator to produce band-edge calibration points at 3.5, 7.0, 14.0, 21.0, and 28.0 MHz. For 6 meters, an odd harmonic must be used, and is heard at 52.5 MHz. The Calibration Reset control on the front panel is a vari-

able capacitor paralleled with the Main Tuning variable.

The power supply is transformer-operated, thereby safely isolating the chassis from the AC line, and has silicon diode rectifiers.

Provisions are made for transmitter control and antenna changeover hook-ups via auxiliary contacts on the function switch. When placed in the standby position, two pairs of terminals on the rear chassis apron are shorted, providing switch action.

Two manuals are furnished with the SX-140K; one is the assembly manual and may be discarded upon completion of the kit, and

the other is an operation and service manual. Keeping these two items under separate cover is a good idea . . . we'd like to see some other kit manufacturers do the same.

All said and done, the authors are very impressed with this little receiver, both in design and performance. Sensitivity and especially selectivity appear to be well above average for receivers of this type. In short, it would be hard to find a comparable receiver at this price, particularly with 6 meter band coverage to boot.

*Reprinted from the November 1963 issue of 73 Amateur Radio.*

### SX-140K Specifications

Frequency Coverage	80, 40, 20, 15, 10, 6 meters (ham bands only)
Tube Complement	6AZ8 RF amplifier/calibration osc. 6U8A local oscillator/mixer 6BA6 IF amplifier 6T8A detector, ANL, 1st audio 6AW8A audio output/S-meter amplifier
Controls	Main tuning, function (Off, Standby, AM, CW-SSB), audio gain, band selector (6 position), RF gain, selectivity/BFO, ANL (on-off), calibrator (on-off), calibration reset, antenna trim
Antenna impedance	50-75 ohms
Audio output impedance	3.2 ohms
Power supply	Transformer operated, silicon diode rectifiers in a doubler circuit
Power requirements	117 VAC, 50-60 cycles @ 47 watts
Dimensions	13-3/8" wide, 8-1/4" deep, 7-3/16" high

### THE FAMED 2 METER A. S. A. 9209

+9 db Co-Linear "MultiWave" Base Station Double 5/8 over 1/4 wave delivers up to +9 db gain. All fiberglass & solid aluminum construction. Fits masts up to 1-1/2". 2 Meter Base Station 10' length.

**\$32.43**

+ \$5.00 S&H

(SC RES. 5% SALES TAX)

CHECK IN ADVANCE OR C.O.D.  
ALSO AVAILABLE IN 220 & 440

ASA

"Service is the Reason For Our Success"

Model 9209 +9db  
Tel: (803)293-7888 P.O. Box 3461  
Watts: 1-800-722-2681 Myrtle Beach, SC 29578

CIRCLE 18 ON READER SERVICE CARD



X-BAND TRANSMITTER

Miniature (2 1/4 x 3 3/4 x 1") GaAs microstrip transmitter provides 10 dBm centered at 10.525 GHz. Integrated microstrip patch antenna eliminates the need for an external antenna. Advanced matching techniques secured good temperature stability with low frequency pulling. Great for long-range testing of radar detectors, calibration of radar receiving equipment, and point-to-point communication links.

Complete Assembled System ..... \$39.00  
Parts & Instruction Kit ..... \$29.00  
Plus \$2.00 Shipping and Handling

INNOTEK Inc.

P.O. Box 80096, Fort Wayne, IN 46898  
(219) 489-1711

Visa • MasterCard • Check • Money Order • COD  
Money-Back Guarantee

CIRCLE 283 ON READER SERVICE CARD

### Simplex Repeater System

- Handle Talkie ready
- 32 or 65 Second operation
- 2 mode operation, Announce or Repeater
- Plugs into spk/mic jacks
- 32K bit operation

- Commercial quality 3.2 kHz pass band
- Amateur supporting emergency communications
- Club meetings announcements
- Test repeater sight locations
- Aeronautical relays
- Security personnel
- Hiking, fishing, back packing, exploring
- Licensed to your call
- Great wired into your mobile



It's Amazing what Simplex can do Better!

US Digital Co  
380 Rougeau Ave  
Winnipeg, MB.  
Canada R2C 4A2  
US Money Order - Prompt Service  
Certified Cheque - Prompt Service  
Personal Cheque - Clearing Time  
phone (204) 661-6859

CIRCLE 190 ON READER SERVICE CARD

### Townsend Electronics, Inc.

presents

C.M. Howes Kits

for

H.F. Amateur Equipment



"RIG SAVER"

H.T. and Mobil Mounts



THE WORLD'S BEST

in ham radio books and publications

28 page catalog \$1.00

Outside USA \$2.00

1-219-594-3661

Townsend Electronics, Inc.

Box 4155 • Pierceton, IN 46562

CIRCLE 299 ON READER SERVICE CARD



## Why buy a TNC?

PC HF FAX + PC SWL \$179.00

### SPECIAL COMBINATION OFFER

For a limited time, if you order PC HF FAX \$99 (see our other ad in this issue), you can add our new and improved PC SWL 3.0 for \$80.00 instead of our regular low price of \$99.00.

PC SWL contains the hardware, software, instructions and frequency lists needed to allow you to receive a vast variety of digital broadcasts transmitted over shortwave radio. All you need is any IBM PC or compatible computer and an SSB shortwave receiver. The product consists of:

**Demodulator**  
Digital Signal Processing Software  
200 Page Tutorial Reference Manual  
World wide Utility Frequency List  
Tutorial Audio Cassette with Samples

PC SWL automatically decodes Morse code, RTTY, AMTOR, SITOR, NAVTEX and ASCII.

PC SWL lets you tune in on world press services, meteorological broadcasts, ham radio operators, coastal shore stations, aviation telex and much more digital action on the shortwave bands. Why pay for another expensive box when a simple interface and your PC can do the job?

#### ADVANCED FEATURES:

Tuning Oscilloscope  
Digital Waveform Presentations  
Auto Calibration and Code Recognition  
Continuously Tunable Filter Frequencies  
Variable Shift  
Adjustable CW Filter Sensitivity  
Unattended Capture and Printing  
Integrated Text Editor  
Integrated Log and Database  
Shell to DOS applications  
Seamless Integration with PC HF Facsimile

Call or write for our complete catalog of products. Visa & MasterCard welcome.

**Software Systems Consulting**

615 S. El Camino Real, San Clemente, CA 92672

Tel: (714) 498-5784 Fax: (714) 498-0568

CIRCLE 244 ON READER SERVICE CARD

Come to the 1993

## AMSAT Space Symposium

La Quinta Inn & Conference Center  
Arlington, Texas

October 8, 9 & 10

Your BEST chance to learn how to work

### Amateur Satellites:

The high orbit DX satellites:

OSCARs 10 & 12

The "Easy birds":

RS 10 & 12

Store & forward PACKET spacecraft

AO 16, LU 19, UO 22, KO 23

and more coming SOON!

Now building:

Phase 3D (The satellite for ALL amateurs)

SEDSAT (Easy to use 2 to 10 meter transponder + digital)

PANSAT (An experiment in amateur spread spectrum)

RS 15 (A new Russian 2 to 10 meter satellite)

More PACKET satellites



Marjorie Swain with Grand Prize won at 1992 Symposium - a Kenwood TR-751A all-mode 2 meter transceiver. OM Carroll W7DU seems pleased with her good fortune.

For more information  
write or call



**AMSAT**

PO Box 27  
Washington, DC 20044  
301-589-6062

CIRCLE 110 ON READER SERVICE CARD

Isn't Your Radio Worth The Investment?

Protect It With



**THE PACK-IT**

FROM TRANSEL TECHNOLOGIES

**TRANSEL TECHNOLOGIES**

Protect your HT's, Cellular Phones, Pagers, and any other devices you carry that may be subject to damage.

The PACK-IT is made of 1/4" neoprene material which is safety belt sewn to the nylon protective backing. The PACK-IT doesn't fray like many other materials and is safe to wash whenever needed.

The strap and 2" beltloop is made from commercial grade webbing and is secured in the front with a Velcro hook and loop assembly.

The PACK-IT doesn't wear the radio like leather and protects the radio from the small falls which occurs in everyday usage. The neoprene material is a cushion material which not only covers the radio but also protects it. Various sizes available so call for the size to fit your need.

Made In The USA!

**\$15.95** + \$3.00 S&H

**1 (800) 829-8321**

Dealers Welcome

CIRCLE 11 ON READER SERVICE CARD

Subscribe To *Radio Fun* Call **1-800-257-2346**

# RAMSEY ELECTRONICS

PHONE ORDERS CALL

**716-924-4560**

FAX 716-924-4555

## RAMSEY IS YOUR QRP KIT HEADQUARTERS

### QRP TRANSMITTERS

only \$29.95!

20, 30, 40, 80 Meter  
CW Transmitters

Join the fun on QRP! Thousands of these mini-rigs have been sold and tons of DX contacts have been made. Imagine working Eastern Europe with a \$30 transmitter - that's ham radio at its best! These CW rigs are ideal mates to our receiver kits. They have two position variable crystal control (one popular QRP crystal included), one watt output (3/4W on 20m) and built-in antenna switch. Runs on 12VDC. Add our case and knob set for a handsome finished look.



#### CW Transmitters

QRP-20, 30, 40, 80 (specify band)

\$29.95

CQRP Matching case & knob set

\$12.95

#### Ham Receivers

HR-20, 30, 40, 80 (specify band)

\$29.95

CHR Matching case & knob set

\$12.95

### HAM RECEIVERS

20, 30, 40, 80 Meter  
All Mode Receivers

Build your own mini ham station. Sensitive all-mode AM, CW, SSB receivers use direct conversion design with NE602 IC as featured in QST and ARRL Handbook. Very sensitive varactor tuned over entire band. Plenty of speaker volume. Runs on 9V battery. Very EASY to build, lots of fun and educational - ideal for beginner or old pro. 30 page manual. Add the case and knob set for well-fitted professional look.

**YOUR SATISFACTION IS GUARANTEED.** Examine your Ramsey product for 10 days. If you're not pleased, return in original condition for refund. Add \$3.95 for shipping handling and insurance. Foreign orders add 20% for surface mail. COD (US only) add \$5.00. Orders under \$20.00 add \$3.00. NY residents add 7% sales tax. Warranty: 90 days on kit parts; 1 year parts and labor on pre-wired units.

PHONE ORDERS CALL  
716-924-4560 FAX 716-924-4555



**RAMSEY ELECTRONICS, INC • 793 Canning Parkway • Victor, NY • 14564**

CIRCLE 34 ON READER SERVICE CARD



# RF vintage review

## The National 200

by Jim Fisk W1DTY

When National came out with their model 200 transceiver at a lower cost than any other five-band transceiver on the market, I just couldn't believe that it would perform as well as the more expensive models. But, after using it for several weeks chasing DX, I find that they have done a superb job and it performs right along with the best of them. The sensitivity is fine, the selectivity afforded by the steep-sided crystal filter is excellent, and the audio reports, if I am to believe the fellows on the other end, have all been good. Reports of "tremendous audio quality," "really sounds good," and "very clean and crisp," have been normal during the time I have had the 200 on the air.

In the National 200, the final amplifier pi network and the driver tuning circuits also double as the RF circuits for the receiver. The VFO and carrier oscillator are common to both transmitter and receiver, and the first IF stage in the receiver also serves as a low-level amplifier in the transmitter. The use of common crystal filter and RF input components results in a sensitive and relatively image-free receiver and highly efficient SSB transmitter. Sideband switching is automatic with lower sideband on 40 and 80, and upper sideband on 20, 15 and 10 meters.

The front end of the receiver starts out with a 6BZ6 RF amplifier, followed by a 12BE6 mixer, the 5.2 MHz crystal filter, two 12BA6 IF stages at 5.2 MHz, a 12AX7 AM detector, product detector and first audio and, finally,

a 6AQ5 audio power stage. The AGC voltage is derived from the second IF stage, run through a semiconductor diode voltage doubler to get it up to the proper level, and then applied to the first IF and RF stages.

The 8.7 to 9.3 MHz high frequency mixing signal from the VFO is premixed in a 6GH8 stage with a crystal-controlled signal on 40, 15 and 10 meters so only one stage of conversion is required in the receiver itself. On 80 and 20, the VFO signal is mixed directly with the incoming RF signal to obtain the 5.2 MHz IF. This procedure somewhat simplifies things and eliminates many problems with spurious responses and birdies that might appear in the receiver tuning ranges.

The tube lineup in the transmitter begins with a 6GH8 microphone preamp, then to a 6GH8 speech amplifier and solid-state balanced modulator where it is mixed with the 5.203 MHz signal from the 12BA6 carrier oscillator. The sidebands at the output of the balanced modulator are fed into a 12BA6 transmitting IF amplifier and then into the crystal lattice filter. The sideband output of the filter goes through another 12BA6 for further amplification, then to a 6JF6 transmitting mixer where it is mixed with the VFO and carrier oscillator signal available from the 6GH8 pre-mixer. A 6GK6 driver and two 6JB6s in the final complete the layout of the 200 watt SSB transmitter. The excellent sideband qualities are a direct result of the very steep-sided crystal lattice filter and the use of double-tuned

circuits in the transmitting IF stages.

The National 200 incorporates a very sensitive automatic level control (ALC) circuit in the final. This circuit makes use of the fact that when the control grids of the power amplifier tubes are overdriven on voice peaks, the resultant positive voltage on the grid causes grid current to flow. This current in turn causes a negative voltage change in the bias network; the resulting audio signal on the bias circuit is capacitively coupled to a voltage doubler for rectification and fed back to the first IF stage to control the audio gain. When the final amplifier is overdriven, the gain of the first IF stage is reduced, resulting in less driving signal at the final. The ALC voltage cannot discharge through the voltage doubling circuit, so the resultant action is a fast attack and slow release. The circuit is designed to provide an automatic leveling control for 10 dB variations in the audio signal. This makes the setting of the microphone gain quite non-critical and changes in the voice level or large background noises are controlled without distortion. When the National 200 is used with a linear amplifier, there is provision for using an external ALC signal from the linear to control the audio stages of the 200.

The variable frequency oscillator used in the National 200 uses a straightforward grounded-cathode Hartley oscillator. To minimize the effects of warm-up drift and to insure long-term frequency stability, all the frequency determining components in the VFO have been carefully selected. To further insure the frequency stability of the unit, the output is taken from the screen grid of the oscillator tube. After a 30-minute warm-up, the stability seems

to be very good. Variations in line voltage have only a very slight effect, not enough to require retuning the station you're working. After an initial five-minute warm-up, the unit drifted about 1000 Hz over the next 25 minutes; after this 30-minute period the drift was insignificant.

In addition to operating on single sideband, the 200 may be used on CW or even AM. A simple adjustment on the back sets the carrier insertion for CW and AM. Once this control has been set for one band it may be left alone. The mode switch on the front panel automatically suppresses this control for SSB operation but permits full carrier insertion on AM and CW. Actually, when this pot is switched into the circuit in the AM and CW modes, it is used to upset the balance of the diode modulator. In addition, for AM or CW, the bias is removed from the 12BA6 transmitting IF stage, providing full carrier insertion of 60 to 300 mA.


This transceiver is designed to load into a 40 to 60 ohm unbalanced load. When the load is within these limits, it loads up very nicely and quite quickly with the three controls required. In this respect, the National 200 is similar to many other transceivers on the market—peak the exciter, load the power amplifier and tune for a dip. Since the receiver uses the transmitter-tuned circuits in its input, when the transmitter is tuned up, the receiver is also matched to the transmission line. In the transmit mode, the meter reads final amplifier cathode current; in the receive mode it functions as an S-meter.

The National 200 may be used either in a fixed station from the 115 volt line with the AC-200 power supply, or mobile with a power supply that furnishes all the necessary voltages. To aid the mobileers, National has thoughtfully included a mobile mount in the package with the 200. This mount is a U-shaped bracket that may be clamped under the dash of your car; the transceiver fits into the bracket and is held in place with a couple of large knurled thumb nuts. To remove the unit for fixed station operation, all you have to do is disconnect the antenna and power plug and remove the thumb nuts.

All in all, the National 200 transceiver seems like a very good investment for those of you who are shopping around for a good all-band transceiver. It is compact, lightweight, easy to use and, best of all, it works well. It's not often that you get all these attributes in one package!

Reprinted from the February 1967 issue of 73 Magazine.

National 200 Specifications	
Frequency Coverage	3.5-4.1 MHz, 7.0-7.5 MHz, 13.9-14.5 MHz, 21.0-21.6 MHz, 28.5-29.1 MHz with crystals provided.
Types of Emission	SSB (upper sideband on 20, 15 and 10 meters; lower sideband on 80 and 40 meters), AM, CW.
Power Input	200 watts PEP SSB, 200 watts CW, 100 watts AM.
Power Output (Nominal)	120 watts PEP SSB, 120 watts CW, 30 watts AM.
SSB Generation	Crystal lattice filter; 6-50 dB shape factor 2.2:1. Bandwidth 2.8 kHz at 6 dB. Carrier suppression -50 dB; unwanted sideband suppression -40 dB; 3rd order distortion products suppressed -30 dB at full output.
Receiver Sensitivity	0.5 $\mu$ V for 10 dB S/N in SSB mode.
Features	Full AGC and S-meter on receive, push-to-talk or manual operation on transmit with ALC for SSB. Automatic carrier insertion for AM or CW. Product detector for SSB and CW, AM detector for AM on receive. Grid block keying on CW.
Tuning dial	45:1 tuning ratio. Dial calibrated at 5 kHz points on all bands.
Tubes and semi-conductors	16 tubes, 10 semiconductors, parallel 6JB6s in the power amplifier.
Accessories	AC-200 power supply for either 117 or 234 VAC, 50/60 Hz; XCU-27 100 kHz crystal calibrator.
Size and weight	6-3/16" x 13-3/8" x 11"; 15 pounds.
Power requirements	700 volts DC at 300 mA, 280 volts DC at 200 mA, -80 volts DC at 10 mA, 12.6 volts at 5 A.
Price	\$359





# A Filter to Eliminate Alternator Whine

An easy method of quieting your mobile rig.

by Bruce Hammond AA8HS

Alternators and other electrical devices in today's cars produce pulses of changing frequency that can be transferred along the vehicle's electrical system. This creates what is commonly called "alternator whine." It changes pitch with the speed of the engine. This particularly affects digital radios and can become worse with high power draws while transmitting. The usual solution has been to power the HT or mobile rig directly from the car battery. This method may be inconvenient, impossible, or may not eliminate the problem at all! The pulses can be transmitted directly through the battery, depending on how devices are wired into the electrical system.

Since my car's digital AM-FM stereo radio had no alternator whine and is connected to the fuse box, I knew that filtering was a solution to severe "whine" in an HT or mobile rig. The filter shown is very effective and works to a 10 amp current drain. It is extremely simple to build and costs about \$21 with new parts, although junk box devices could also be used effectively. Larger capacitors and chokes can be used for higher current. It essentially duplicates the type of filtering used in high power stereo equipment where a flat DC voltage is needed with extremely little AC component.

Capacitors C1, C2 and C3 on the input side filter AC signals of low, medium and high frequencies. The Radio Shack 270-051 noise filter blocks AC components from the positive or negative side. I don't know the exact contents of the Radio Shack filter unit but resistance measurements show 0.3 ohms between each of the red and black leads, which is con-




Figure 1. A filter to eliminate alternator whine. All capacitors are 35 volts or more. C1 and C4 are electrolytics.

sistent with reasonably large chokes. There may also be some parallel capacitance. Connecting the two black leads together would eliminate the minimal voltage drop across the negative side choke but this does not appreciably affect performance. C4, C5 and C6 remove any residual AC signal. C4 is particularly large and helps to eliminate the effects of transient changes in the electrical system voltage. It's a good idea to tap into the fuse box at an accessory outlet or cigar lighter since these points are more likely to be independent of the ignition switch. The radio should be grounded as directly as possible to the car body, as the mobile antenna should be. For tempo-

rary operation, a cigar lighter plug alone can be used for both positive and negative leads.

Be sure to select the right size fuse for the radio that you plan to use. The filter can be built in any enclosure that you like. After sol-

dering all leads together, I insulated the exposed wire leads with electrical tape and wrapped the entire assembly in thick cloth, placing it under the car seat. Good luck! **RF**

itor the RF envelope. The gain control was advanced to the point where distortion was apparent. This occurred at between 90% and 100% modulation, depending on tuning and loading. Measured peak power output was roughly equal to the CW output for identical tuning and loading conditions.

On the air tests produced good results. No attempts were made to establish any DX records, the objective being to obtain critical reports on signal quality. Comments on the controlled carrier modulation system were typical. "Your audio quality is good, OM, but your carrier seems to be going up and down." Those operators familiar with controlled carrier AM signals gave good reports. Constructive, "on the air" help in finding the proper setting of the audio gain control was difficult to obtain. The proper point, verified by the scope, is just below the setting where audio distortion becomes noticeable.

There are very few complaints with the transmitter. The comments on the metering system cannot be taken too seriously since the system works and works well. The reduced output on 6 meters is more serious. However, since 6 meter coverage is a bonus anyway, we can afford to be philosophical and not look a gift horse in the mouth. The writer has personal objections to the RCA phono jack used as the mike connector and it is suspected that many users will change it to a type to fit their microphones.

All in all, the Knight T-60 is a very good buy. For the Novice, it is an ideal first transmitter, and it is very attractive to the more experienced amateur as an emergency or standby unit. The rugged construction and simplicity of the unit make it probable that this little rig will be in service long after more

sophisticated equipment is "down for maintenance." **RF**

Reprinted from the March 1962 issue of 73 Amateur Radio.

## THE HOTTEST CB/10 METER RIG GOING AM/FM/CW UP TO 100 WATT SSB



### HR2510 WITH EASY TO FOLLOW INSTRUCTION BOOKLET


1. HOW TO ADD CB/26-30 MHz
2. CONVERT RIT TO SLIDER
3. BOOST UP TO 100 WATTS SSB
4. ADD VARIABLE POWER
5. ADD TALK BACK

ONLY ONLY ONLY \$ 229.95

WITH VHS VIDEO EASY STEP BY STEP INSTRUCTIONS ONLY \$ 239.95 + S/H \$ 5.00  
TAPE ALONE ONLY \$19.95

### ULTIMATE MODIFICATION BIBLE

MOST COMPLETE, GREATEST IN IT'S TIME !!!  
OVER 800 MIKE WIRINGS CB/HAM.  
OVER 400 CB POWER BOOST.  
OVER 200 MOD. CB CHANNELS.  
OVER 125 MOD. HAM RADIOS.  
OVER 50 COMPLETE CRYSTAL CHARTS.  
OVER 20 MOD. CRYSTAL CHARTS.  
OVER 15 SCANNER MOD.  
TEN METER RADIO MOD.  
LINEAR/COAX/ANT. INFO.  
OVER 200 PAGES OF INFO.  
KDC SOUND 1-800-256-9895  
5 PINE MEADOW \$ 29.95  
CONROE, TX 77302



CIRCLE 151 ON READER SERVICE CARD

## 24 HOUR SHIPPING ELENCO • HITACHI • B&K PRODUCTS GUARANTEED LOWEST PRICES

TO ORDER  
CALL TOLL FREE  
1-800-292-7711  
1-800-445-3201 (Can.)

### AFFORDABLE - HIGH QUALITY 2 YEAR WARRANTY



**STANDARD SERIES**  
S-1325 25MHz \$349  
S-1340 40MHz \$495  
S-1365 60MHz \$849

- Features:
- High Luminance 6" CRT
  - 1mV Sensitivity
  - X-Y Operation
  - Voltage, Time, + Frequency differences displayed on CRT thru the use of cursors (S-1365 only)
  - Plus much, much more
  - TV Sync
  - 2 - x1, x10 Probes
  - Complete Schematic

### ELENCO OSCILLOSCOPES



**DELUXE SERIES**  
S-1330 25MHz \$449  
S-1345 40MHz \$575  
S-1360 60MHz \$775

- Features:
- Delayed Sweep
  - Automatic Beam Finder
  - Z Axis Modulation
  - Built-in Component Test
  - Plus all the features of the "affordable" series
  - Dual time base
  - Illuminated internal grid

### Hitachi Compact Series Scopes

V-212 - 20MHz Dual Trace	\$399
V-525 - 50MHz, Cursors	\$995
V-523 - 50MHz, Delayed Sweep	\$949
V-522 - 50MHz, DC Offset	\$895
V-422 - 40MHz, DC Offset	\$795
V-222 - 20MHz, DC Offset	\$649
V-660 - 60MHz, Dual Trace	\$1,149
V-665A - 60MHz, DT, w/cursor	\$1,325
V-1060 - 100MHz, Dual Trace	\$1,395
V-1065A - 100MHz, DT, w/cursor	\$1,649
V-1085 - 100MHz, QT, w/cursor	\$1,995
V-1100A - 100MHz, Quad Trace	\$2,495
V-1150 - 150MHz, Quad Trace	\$2,395

### B&K OSCILLOSCOPES

2120 - 20MHz Dual Trace	\$389
2125 - 20MHz Delayed Sweep	\$539
1541B - 40MHz Dual Trace	\$695
2160 - 60MHz Dual Trace, Delayed Sweep, Dual Time Base	\$949
2190 - 100MHz Three Trace Dual Time Base, Delayed Sweep	\$1,395
2522A - 20MHz / 20MS/s Storage	\$875

### Digital Capacitance Meter

CM-1550B by Elenco  
\$58.95  
9 Ranges  
1pF-20,000uF  
5% basic acy.  
Big 1" Display Zero control w/ Case

### Digital LCR Meter

LC-1801 by Elenco  
\$125  
Measures:  
Coils 1uH-200H  
Caps 1pF-200uF  
Res. 0.1-20M

### Digital Multimeter

DVM-638 by Elenco  
\$39.95  
11 Functions with Case

### FLUKE MULTIMETERS

Scopemeters (All Models Available Call)			
Model 93	\$1,225.00	70 Series	
Model 95	\$1,549.00	Model 70II	\$65.00
Model 97	\$1,795.00	Model 77II	\$149.00
10 Series		Model 79II	\$169.00
Model 10	\$62.95	80 Series	
Model 12	\$79.95	Model 87	\$289.00

### Digital Triple Power Supply

Elenco XP-765  
\$289  
0-20V @ 1A  
0-20V @ 1A  
5V @ 5A  
Fully regulated, Short circuit protected with 2 limit control, 3 separate supplies XP-660 with Analog Meters \$195

### Video Head Tester

Elenco HT-200  
\$44.95  
Tells you if VHS head is defective or worn.

### Digital Multimeter w/ Inductance & Capacitance

LCM-1850 by Elenco  
\$75.00  
Ten Functions

### Color Convergence Generator

Elenco SG-250  
\$89.95  
Kit \$69.95  
Finest in the industry 10 rock steady patterns RF & video output

### Sweep/Function Generator with Freq. Counter

Elenco Model GF-8026  
\$239  
Sine, Square, Triangle, Pulse, Ramp  
2 to 2MHz, Freq Counter .1-10MHz  
Internal Linear & Logic Sweep

### Function Generator

Blox \$9600 by Elenco  
\$28.95  
Provides sine, triangle, square wave from 1Hz to 1MHz  
AM or FM capability  
Kit \$26.95

### XK-500 Digital / Analog Trainer

A complete mini-lab for building, testing, prototyping analog and digital circuits. Elenco's Digital/Analog Trainer is specially designed for school projects, with 5 built-in power supplies. Includes a function generator with continuously variable, sine, triangular, square wave forms. All power supplies are regulated and protected against shorts.

**Power Supplies**  
Variable Power Supply  
+1.25 to 20VDC @ 5 Amp  
+1.25 to 15VDC @ 1 Amp  
+1.25 to 20VDC @ 5 Amp  
+1.25 to 15VDC @ 1 Amp  
+12VDC @ 1 Amp  
+5VDC @ 1 Amp  
30VAC Center tapped @ 15VAC at 1 Amp

**Analog - Section**  
Function Generator Sine, Triangular, Square wave forms  
Frequency adjustable in five ranges from 1 to 100kHz  
Fine frequency adjust  
Amplitude adjust  
DC offset  
Modulation FM-AM

**Digital - Section**  
Eight data switches  
Two no bounce logic switches  
8 LED readouts TTL buffered  
Clock frequency 1 to 100kHz  
Clock amplitude 5VPP square wave

**Breadboards**  
2 breadboards, each contain 840 tie points (total 1,680)  
\$159.95

**Assembled**  
\$129.95 Kit

**15 DAY MONEY BACK GUARANTEE**  
FULL FACTORY WARRANTY  
WRITE FOR FREE CATALOG

C&S SALES INC.  
1245 ROSEWOOD, DEERFIELD, IL 60015  
FAX: 708-520-0085 • (708) 541-0710

WE WILL NOT BE UNDERSOLD  
UPS SHIPPING: 48 STATES 5% OTHERS CALL  
IL RES add 7.75% TAX  
PROBES INCL. ALL SCOPES & METERS

CIRCLE 184 ON READER SERVICE CARD



# Easy Transmitter Protection

*Don't cook your TX with a strange impedance.*

by Andy Loomis KEØUL

Do you cringe at the thought of transmitting into a completely unknown load? Are you concerned that the automatic high-SWR shutdown circuit in your expensive rig isn't going to work? Would you like to feel at ease if you make a really BIG mistake when adjusting your antenna? This article describes a truly simple method of minimizing the SWR as "seen" by your transmitter, while allowing you to tinker to your heart's content with your antenna system or any other load you wish to play with. No matter

what you do, your transmitter will be happy!

Our task is to provide a reasonably constant load to our transmitter, even at the extremes of our folly, which could be the condition of no load at all (an open circuit), or a dead short circuit.

First, we must define what we mean by a "reasonably constant load." Most transmitters are made to drive a 50 ohm load with a maximum 2:1 VSWR. What this means is that the transmitter will do just fine with a load rang-

ing from 25 to 100 ohms. In fact, most transmitters won't suffer any harm if operating into a 3:1 VSWR (17 to 150 ohms). But, for the sake of the more squeamish among us, let's stick to the 2:1 maximum and concoct a device to ensure that our transmitter cannot see, under any circumstances, a higher ratio.

The trick to accomplishing this is to introduce enough attenuation between the transmitter and the load so that the reflected energy is absorbed and dissipated as heat before it can return to the transmitter and upset the impedance matching. Unfortunately, any attenuation we introduce will also have an equal effect on the forward energy, but that is the price we must pay. During antenna adjustments we don't need our full power capacity anyway, so we accept the signal loss in trade for keeping our transmitters happy.

A cable with 5 dB matched loss will show a maximum 2:1 VSWR to an RF source when the far end of the cable is short-circuited. Well, it turns out that 85 feet of RG-58 cable has an attenuation of about 5 dB on the 2 meter band. A 40-foot length of RG-58 gives the same attenuation on the 70cm band. If you connect your transmitter to your antenna using these (or greater) lengths of RG-58 cable, then the SWR at your transmitter cannot exceed 2:1, no matter what!

On the HF bands, however, even RG-58 cable isn't very lossy. It then becomes necessary to construct an attenuator from discrete components. The simplest attenuator is called an "L"-pad. It contains two resistances—a series element and a shunt element. By feeding our transmitter into a series element of 25 ohms, and then shunting the output connection with a 75 ohm resistor, we will satisfy the 5 dB

loss requirement and ensure that our transmitter sees a maximum VSWR of 2:1.

The next step is to build the attenuator. Be sure to use only carbon resistors and not wire-wound resistors. It is very tempting to use the wirewound variety because they are the ones that come in the higher-power ratings, but don't do it! We must build up our resistors by series or parallel combinations of smaller-wattage resistors.

The series element can be made up of a cluster of seven 180 ohm, 1 watt or 2 watt resistors all wired in parallel in a tight, neat bundle. If you use 1 watt resistors, then the maximum power you can use for testing purposes should be 7 watts. The larger resistors will dissipate 14 watts total. Remember that these are MAXIMUM power levels—resistors are rated for free-air ventilation and by bundling them together we lose a lot of cooling efficiency. On the other hand, we really won't be loading our device with a dead short circuit for very long, either!

The shunt element can be built using a parallel combination of seven 560 ohm, 1/2 watt or 1 watt resistors. The shunt element isn't required to dissipate as much heat as the series element, so use the 1 watt resistors only if you have chosen the 2 watt style for the series element.

Use a small, aluminum box (such as the Radio Shack 270-235) and install your favorite coaxial connector on each end. Take special care to keep the lead lengths of the resistor elements as short as possible, especially at the transmitter input connector. The shorter you can make the leads the better. Sloppy construction will exhibit poor performance on the higher frequency bands.

To use the attenuator when adjusting an antenna, be sure to place your SWR bridge between the attenuator and the antenna. You will want to see the "true" SWR variance as you tune the antenna. For the curious, go ahead and insert the bridge between the transmitter and the attenuator—you will see confirmation of the fact that the SWR at the transmitter cannot exceed 2:1 under any circumstances. **RF**




Figure 1. Careful construction of this L-pad attenuator will pay off in performance.

## FCC Relaxes Restrictions

**OLD RULE:** Except for emergency communications, the ham bands may not be used as an alternative to other authorized radio services.

**NEW RULE:** Amateur-to-amateur communications which could reasonably be furnished alternatively through other radio services will now be permitted on the ham bands—although not on a regular basis. This will allow amateurs to legally participate with the Weather Service, police and fire departments, parks and forestry service, and many other local, state, and federal agencies. *TNX Westlink Report, No. 654, July 29, 1993 and W5YI Report, Issue 16, August 15, 1993.*

## Clinton is High on Hams in Space

The president of the United States, no less, took time out of his busy schedule recently to extol the virtues of the Shuttle Amateur Radio EXperiment (SAREX) program. While talking to the STS-57 mission astronauts on a special hookup, President Bill Clinton said: "I understand that later in the mission Janice (Voss) and Brian (Duffy N5WQW) are going to be talking with schoolchildren around the world. I just want to tell you how much I appreciate the fact that you're making an international education project out of this mission. That's very important to me."

Astronaut Brian Duffy responded: "Mr. President, we find that using amateur radio is an

## Continued from page 1

excellent way of communicating with children all around the world, and we're also able to excite them by using space and science."

President Clinton concluded: "You may be on this mission, creating thousands of scientists for the future just by the power of your example and by this direct communication. I think sometimes we underestimate the impact that human contact in an enormously impressive setting like this can have on children across the world—not only those with whom you talk, but millions of others who will just see it and know that it happened." *TNX Westlink Report No. 653, July 15, 1993 and W5YI Report, Issue 13, July 1, 1993.*

## Vanity Callsigns Authorized

Both the House and Senate have approved legislation authorizing the FCC to issue unique amateur radio callsigns, at a cost of \$7 per year, to the ham community. The surprise measure was inserted into the recently signed deficit reduction bill of President Clinton.

According to a congressional aid close to the plan, "We envision that the legislation will probably be implemented so that an amateur pays \$35 every five years, although there is no language in the bill that says they have to do it that way. It only says they have the authority because they do not have this authority right now. . . . As I understand it, the proceeds will go to the FCC to augment their budget, . . . pay for

equipment, staff, and stuff." The only amateurs who would be subject to the new fees are those requesting special, distinctive callsigns.

Another little-known tack-on to the deficit plan provides for spectrum auctions. The government is set to receive more than \$10 billion over the next five years when it sells radio spectrum to the highest bidder for new communications services. *TNX W5YI Report, Issue 16, August 15, 1993.*

## Technician is Hot Ticket

The Technician Class amateur radio license is maintaining its accelerated growth rate of 20%—by far the fastest growing ham class. Before 1991, amateur radio overall grew at only a sluggish 3% rate. Today, that figure is a healthy 10%. If the rate of growth of amateur radio continues on the track it's on now, we will surpass one million licensed ham operators by 1998.

In 1985, only one amateur in five was a Technician. But since the arrival of the Codeless Technician Class in 1991, the demographics have shifted significantly. Today, one third of all hams are Techs. *TNX W5YI Report, Issue 13, July 1, 1993.*

## Codeless Coast Guard

For the first time since 1924, the United States Coast Guard has closed down its Morse code operations on 500 kHz. The final CW trans-

mission ended an era at 000Z, July 31, 1993. Coast Guard radio operators first began listening for distress signals on 500 kHz at the turn of the century, and set up its permanent station nearly 70 years ago to monitor the frequency continuously.

Officials say the advent of satellite and digital technology has made Morse code obsolete on the high seas. A misty-eyed Coast Guard radioman tapped out the final 73, saying "We now look forward to serving you on the next generation of communications equipment and systems via the Global Marine Distress and Safety System (GMDSS)." *TNX W5YI Report, Issue 16, August 15, 1993.*

## Lunar Repeater

Northern California's Project OSCAR group has proposed installing the first repeater on the moon. Project OSCAR is the group that built and orbited the world's first amateur radio satellite. During recent meetings, the organization has decided to revive "Project Moonray" to take amateur radio into the 21st century.

Moonray is short for Moon Relay, a concept first proposed by W6OLO back in 1965. The idea was to build a repeater that would fit under the seat of the Lunar Rover. But, the project was shelved after Congress cut funding for manned moon missions beyond Apollo 17.

No specific timetable has been offered, although organizers hope to get the project off the ground by the turn of the century—which is only six years and a few months away. *TNX Westlink Report No. 655, August 13, 1993.*



# advertiser index

RS#	ADVERTISER	PG	RS#	ADVERTISER	PG	RS#	ADVERTISER	PG
18	A.S.A.....	10	• J.M.S.....	24	35	Sign On.....	19	
196	A.S.A.....	17	2 Kawa Productions.....	20	244	Software Systems.....	11	
351	Absolute Value Systems.....	25	151 KDC Sound.....	15	250	Software Systems.....	27	
•	Advanced Electronic Applications.....	CV2	234 Lentini Communications.....	22	245	Techniks, Inc.....	28	
319	Antennas West.....	24	25 Madison Electronic Supply.....	20	119	Tiare Publications.....	26	
16	Astron Corporation.....	9	101 Maxcom, Inc.....	3	299	Townsend Electronics.....	10	
105	Battery Tech, Inc.....	6	86 MFJ Enterprises.....	5	371	Trader.....	13	
184	C & S Sales, Inc.....	15	114 Mr. Nicad.....	27	11	Transel Technologies.....	11	
146	Creative Control Products.....	25	1 Number One Systems Ltd.....	26	190	U.S. Digital.....	10	
114	E. H. Yost.....	27	73 Orchid City Software.....	23	136	Unadilla Antenna Manufacturing		
353	Emars.....	25	• P.C. Electronics.....	21		Company.....	20	
83	EUR-AM Electronics.....	25	117 Paktek.....	21	•	Uncle Wayne's Bookshelf.....	29	
33	FB Enterprises.....	17	68 Periphex.....	18	•	Universal Radio.....	26	
•	Gap Antenna Products.....	23	394 PKT Electronics.....	27	•	US Radio.....	21	
193	GGTE.....	26	145 QSO Software.....	20	•	Vanguard Labs.....	21	
72	Glen Martin Engineering.....	28	110 Radio Amateur Satellite.....	11	14	VHF Communications.....	27	
291	Gracilis.....	22	• Radio Fun.....	17	104	Vis Study Guides, Inc.....	13	
331	Hardin Electronics.....	23	34 Ramsey Electronics.....	11	347	Xionix.....	22	
179	Icom.....	CV4	• RT Systems.....	23	•	Yaesu Electronics Corporation.....	CV3	
283	Innotek, Inc.....	10	• Sams.....	23				

## Are You Having Enough Radio Fun?

Are you having enough fun with amateur radio? *Radio Fun* is the *only* amateur radio magazine written especially for you – the newcomer, or any one else who wants to get more enjoyment out of amateur radio. We pack every issue of *Radio Fun* with easy to understand construction projects, interesting news and great reviews of new and vintage gear. We'll help you learn about all of the fascinating areas of amateur radio – packet, amateur television, VHF/UHF and dozens more. We'll get you fired up to try DX chasing, contests and public service. We'll even help you learn more about radio and electronics, and we'll do it in a way that everyone can understand.

So what are you waiting for? It's only \$12.97 for a whole year of fun!

**1 year – 12 issues – of *Radio Fun* for only \$12.97! That's 46% off the cover price!**

**Call 1-800-257-2346**


... or send your check to *Radio Fun*, P.O. Box 4926, Manchester NH, 03108 - 9839.



### MODEL 410 DUAL BAND VERTICAL BASE STATION ANTENNA 2m / 70cm

#### SPECIFICATIONS:

FREQUENCY: 144-148 MHz, 435-450 MHz  
GAIN: 6.0dB (2m), 8.0dB (70cm)  
BEAMWIDTH: 42 Deg. (2m), 17.5 Deg. (70cm)  
POWER: 200 Watts (Max.)  
IMPEDANCE: 50 ohms  
VSWR: Less than 1.5:1  
WIND RATING: 112 MPH (Max.)  
MAST DIA.: 1-3/16" to 2-7/16"  
LENGTH: 98.4"  
WEIGHT: 2.6 lbs  
CONNECTOR: UHF



**\$97.50**

+ \$5.00 S&H (SC Residents Add 5% Sales Tax)  
Check in Advance or C.O.D.

**ASA PO Box 3461 Myrtle Beach, SC 29578**

**1 - 800 - 722 - 2681**

CIRCLE 196 ON READER SERVICE CARD

**CALL NOW! 1-800-377-2339**

#### REPEATER MAPS



Use the **QUICK-N-EASY REPEATER MAP** to find the repeater you are looking for! **HIGH QUALITY** laminated plastic card with map of your state (California residents specify North or South CA) with 2m repeaters on the front and other bands on the back. Because it's laminated, it's tough and rugged. **YOU'LL LOVE IT!**

**INCLUDES:**  
**\$3.95** 144 MHz 220 MHz  
PER CARD 440 MHz 900 MHz  
**ORDER 3 CARDS FOR JUST \$10**

#### NEW REGIONAL REPEATER MAP GUIDES

A whole new way to enjoy our map cards! **SETS AVAILABLE**  
#1- AK, WA, OR, ID, MT, NV  
#2- AZ, CA, HI, NM, UT, TX  
#3- CO, MT, ND, SD, WY  
#4- IA, KS, MN, MO, NE, OK  
#5- AL, AR, LA, MS, MO, OK  
#6- AL, GA, FL, LA, MS, TN  
#7- KY, MD, NC, SC, VA, WV  
#8- IL, IN, KY, MI, OH, WI  
#9- DE, MD, NJ, NY, OH, PA  
#10- CT, ME, MA, NH, RI, VT

**\$9.95**

**FB Enterprises**  
23801 NW 1st Ave.  
Ridgefield, WA 98642-8830  
CALL TODAY! 1(800) 377-2339  
Dealer Inquiries Welcome

#### REPEATER MAPBOOK



**NEW! 1993-94**  
**INCLUDES:**  
10M, 2M  
220 MHz  
440 MHz  
900 MHz  
1.2 GHz

**ORDER TODAY! \$9.95**

Our quality Repeater Maps are now available in book form! That's right, our new book includes all U.S. States, all Canadian Provinces, Mexico, Central America and the Caribbean! Maps show city location, repeaters, highways, ham dealers, and tourist information! **PERFECT FOR TRAVEL!** More than 175 pages!

**QUICK-N-EASY SHORTWAVE**

New book includes everything you need to know to have fun with shortwave radio! Great book for beginners and also experienced listeners  
**ORDER TODAY! \$9.95**

**CATALOG \$2**  
REFUNDED WITH PURCHASE  
CARD ORDERS  
ADD 50¢ SHIPPING  
BOOK ORDERS  
ADD \$3.00 SHIPPING

CIRCLE 33 ON READER SERVICE CARD



## MFJ's 941D Versa Tuner II

*Antenna tuner/SWR bridge in one versatile unit.*

by Pete Putman KT2B

We amateur radio operators are fairly smart fellows, aren't we? After all, we have to master Morse code and comprehend a wide variety of technical topics ranging from baud rates to beamwidth. We understand feedpoint impedance, reactance, resonance, angles of radiation, and the care, feeding and use of baluns, right?

So how do we account for all these guys who load up gutters as antennas, operate 160 meters using 15 feet of longwire in the attic, and insist on using a tribander to call CQ on 75 phone? Hmmmm?

The truth is that our world is full of compromise. Sure, we know darn well that a half-wave dipole for 160m takes up 240 feet, and it should be at least 60 feet above the ground to do any good, and we must use a balun at the feed point. Then we go outside, toss 30 feet of wire across some tree branches, just out of reach, and try to work 4X4s with it. (Sigh...)

If necessity is the mother of invention, then compromise is the mother of the antenna tuner. There are probably more variations of this device on the market today than there are handie-talkies—a staggering thought! And yet without them, many amateurs would not have worked those 4X4s on 160, 80 or even 40

meters. The antenna tuner is indeed a key part of an amateur's station. And so it is for me with the MFJ 941D Versa Tuner II, a 300W PEP tuner incorporating an SWR bridge, power meter and 4:1 balun all in a tidy box.

### Lured by Sunspots

After spending the better part of the last six years on VHF and UHF, I've grown accustomed to broad-banded 50 ohm antenna feeds. But the siren song of sunspots has lured me back to HF and the attendant problems with antennas. I recently erected a Cushcraft A3 tribander with a 40 meter add-on kit, and while it works quite well, my Kenwood TS-430S doesn't like to load into it at several points in the 40 and 15 meter bands.

As a compromise, I set the elements on the A3 for coverage of the middle portion of 40 meters, resulting in VSWR readings of over 2:1 below 7.090 and above 7.220 MHz. I also obtained 2:1 readings below 21.375 MHz (10 meters and 20 meters are under 2:1 across each band). Time to pick up an antenna tuner!



### Why Use a Tuner?

Modern solid-state transceivers want to see a range of 50 to 75 ohms in everyday operation. Internal ALC circuits measure increased collector current as a function of VSWR mismatches and "throttle back" the drive to keep maximum current below a specified value, thus insuring long life for your final transistors. Most transceivers have their ALC circuits set to "kick in" at about a 1.5:1 VSWR (75 ohms), but the truth is that with ballasted emitter devices in the finals, 2:1 mismatches don't present much of a problem.

I've reset the ALC circuit in my HG radios to allow as much as a 2:1 mismatch, thereby allowing greater frequency excursions for a given antenna. It's only when impedances reach above 2:1 that things get tricky, and here's where an antenna tuner really helps out. But the important point to remember is to optimize your antenna for the chosen band. Get it as high as possible, strive for the longest possible physical length with respect to optimum, and use a good ground. If your tuner is looking at realistic impedances, it can be a potent tool.

### MFJ Tuners, and the 941D in Particular

MFJ manufactures a bewildering array of tuners, starting with the 16010 Random Wire model and stretching all the way up to the MFJ 989C 3 kW version. I considered using the scientific method of closing my eyes and throwing a dart at the page to make a choice, but after careful study decided on the 941D for several reasons: (1) I only run 100 watts on HF; (2) it has a built-in SWR bridge/power meter; and (3) it will handle two coaxial lines, one balanced and one unbalanced.

The 941D Versa Tuner packs quite a bit in a small package. It checks in at 3" H x 10" W x 7" D, and weighs just a couple of pounds. The chassis is finished in black, fitting right in with most of today's transceivers. Front panel controls from left to right are: SWR SENSITIVITY, ANTENNA SELECTOR, TRANSMITTER MATCHING, INDUCTOR SELECTOR, and ANTENNA MATCHING. In addition, push-buttons select FWD/REV, 300/30W range, or POWER/SWR functions on the front panel meter.

Rear panel connections are for BYPASS COAX, COAX 1, COAX 2, and a combination of binding posts that allow connection of an unbalanced

wire, balanced feedline and ground. The 941D has a built-in 4:1 balun for a 200 or 300 ohm ladder or ribbon line, with a maximum rating of 300 watts PEP. Theoretically, you could have two coax lines and one longwire connected at the same time to the 941D. (Note that the BYPASS COAX does just that and is routed around the tuner.)

Electrically, the tuning circuit is a "T-match" system, using two variable capacitors in series with a tapped inductor shunted to ground. One would expect this circuit to exhibit a moderately high Q, similar to a "T section" filter. And it does, as the optimum settings for a given match are quite narrow—that is, one setting of the inductor is usually best. Where the mismatch is more severe, the settings on the 941D become critical. Conversely, when presented with impedances in the 75 to 100 ohm range, the tuning is quite broad.

So far, I've been able to match up random 500-600 ohm longwire antennas, using a good ground connection as a counterpoise. The settings are very sharp, but stable and repeatable... very important when contesting and jumping around between bands. And there's been no evidence of the balun core saturating at this power level. The 941D's power and SWR meter agree quite closely with a Bird 43 Thruline on all bands from 160 through 10 meters. A toroidal coupler is used, as the sensitivity of wattmeters is usually quite low in the HF range. SWR is calculated by setting the front panel control for a full meter deflection, then switching to REF.

Using the 941D, I'm able to set up the A3 on 40 meters to operate under 2:1 from 7.200 to 7.300, or from the low end of the band up through 7.125, just by changing the inductor setting. Fifteen meters is similarly covered with one setting, resulting in under 2:1 performance across most of the band. In either case, you can get the A3's original settings by switching either coax line to DIRECT on the front panel, so rapid QSYing is a breeze.

For 160 and 80 meter operation, I'll use an end-fed 250' longwire, connecting a balun at the feed point to eliminate RF burns in the shack. By attaching the counterpoise outside and transforming down to open wire line, the internal 4:1 balun will be matching 150-200 ohms to 50 ohms unbalanced, and it should tune fairly smoothly. Pretty versatile!

Reprinted from the February, 1990 issue of 73 Amateur Radio.

# \$40 Special To Charge You Up...

## Periphex Power Packs for Longer QSO Time



replacements for	regular price
<b>FNB-12 YAESU 600ma</b>	\$ 54.50
<b>BP-84S ICOM 1400ma</b>	\$ 63.00
<b>PB-13S KENWOOD 1200ma</b>	\$ 49.75
<b>EBP-24S ALINCO 1500ma</b>	\$ 62.00

Now Only \$40 Each

- One Year Warranty
- Matched cell construction
- Case re-build service
- Long life, extended operating time
- Made for HAMS, by HAMS

Add \$4.00 Shipping & Handling for first battery.  
\$1.00 for each add'l battery - U.S. only  
Connecticut residents add 6% tax.

Available  
from your  
dealer...

Buy your radio  
from the manufacturer.  
Buy the battery pack  
from Periphex—where batteries  
are our only business!

**PERIPHEx inc.**  
the only thing low about our charge is the cost...  
**1-800-634-8132**

115-1B Hurley Road • Oxford, CT 06478 • (203) 264-3985 • FAX (203) 262-6943

CIRCLE 68 ON READER SERVICE CARD





# the tech side

by Michael Jay Geier KB1UM

## Getting Heard

Last month, we were discussing RF power and how to use it to your best advantage. Let's continue:

## Efficiency

Obviously, you want to get as much of your RF power to the listener's receiver as you can. Between your transmitter and the other ham's receiver are five things: two antennas, two feedlines and space itself. But how much of the power you are generating is even making it out into space?

You have control over only two of those elements, so it pays to do the best you can with them. First, how much power are you losing in your feedline? If you're losing, say, 3 dB, half your power is getting wasted warming up your coax! On the HF bands, cable loss usually is very low, but on VHF and UHF it can be quite significant. Second, there's the matter of SWR (standing wave ratio). SWR refers to the ratio of how much power is being accepted by the antenna and radiated into space to how much is being rejected and sent back down the feedline. It is one of the most controversial subjects in all of ham radio. Essentially, your SWR is a function of how well-tuned your antenna is to your operating frequency. Antennas resonate electrically in the same sense that violin strings resonate mechanically; both resonances occur because it takes a certain amount of time for the energy to get from one end of the antenna or string to the other. If you try to excite a string with a pitch different from the one to which it is tuned, it won't vibrate along with it. Likewise, a mistuned antenna will not accept much of the RF energy applied to it.

So where does that energy go? Like I said, it goes back down the feedline to your transmitter! Now, here's where the controversy comes in. Some people say that, as long as you have a way of protecting the transmitter from being damaged by all that returning energy (an antenna tuner is the usual solution), SWR really doesn't matter because the energy will just bounce back and forth on the feedline until it gets accepted, little by little, by the antenna and sent into space. Other people say that even a moderate SWR is like the bubonic plague: to be avoided at all costs. Who's right?

The truth seems to be somewhere in between. A moderate SWR, perhaps 1.4 to 1, doesn't seem to make much, if any, difference in how your signal appears at the receiving end. On the other hand, a 5 to 1 SWR will make for poor performance no matter what kind of tuner you use. If the energy really does bounce back and forth on the feedline until it gets radiated, why does that high SWR cause so much reduction in radiated signal?

## I'm Getting Weaker . . .

We're back to cable losses again. As the

signal bounces back and forth, it gets weaker and weaker because of the resistance and other losses in the feedline, with the result that only *some* of it finally gets radiated; the rest just warms the coax. If that weren't true, you could inject some RF at one end of a cable, short the other end, walk away and still find it zinging back and forth days later! Obviously, that won't happen. By the same token, two mirrors facing each other won't keep reflecting a single pulse of light for any observable period of time. (Admit it, you tried this as a kid, didn't you? I did.)

## The Skyhook

Antennas are a complex, fascinating subject about which many hams know more than I do. Lots of hams love them. They love designing and building them, talking about them and even fighting about them. I do not; I'm a circuit guy and find antennas a nuisance. So, I won't attempt to go into any great detail about them; I'll just bring up a few basic points. If you like antennas, there are plenty of books and articles on the subject to get you started.

First, some kinds of antennas concentrate your RF power in a particular direction. These directional antennas are generally called beams. If you aim most of your energy at the receiver, it works the same as if you had lots more power into an omnidirectional antenna. Beam antennas are used by virtually all the "serious" HF operators. I mean the ones who spend thousands for their stations and operate in contests and such. Plenty of VHF and UHF operators use them, too. Beams have the added benefits of limiting interference from stations in other directions (because the beam effect is there in receive, too) and reducing interference to other stations not in the beam's path.

Second, the vertical angle at which an HF antenna sends a signal determines, to some degree, the distance at which it will be refracted back to earth. The lower the angle of radiation, the farther the skip distance. Since you can't get anywhere pointing into the earth, the best you can do is point at the horizon and make that horizon as far away as possible by putting the antenna up as high as you can.

## The Signal Itself

I mentioned that, on SSB, the "loudness" of your signal does depend, at least to a degree, on the signal strength. The reason I qualify that statement is because how loud you sound depends more on certain characteristics of your modulated signal than on your absolute signal strength.

## Just an Average Signal

If you've ever talked into a microphone and watched your voice waveform on an oscilloscope, you know that the human voice makes a remarkably complex series of

sounds. One of the peculiar facets of the voice waveform is that it has occasional strong peaks, with most of the sounds being significantly softer. In fact, there's quite a dynamic range (the difference between the softest and loudest sounds) between some phonemes (the 64 sounds comprising human speech) and others. A big dynamic range may sound awesome on a classical music CD, but it's the last thing we want on ham radio!

How come? The HF radio bands are filled with noise and static, not to mention interference from other stations. It's a real zoo out there! If your signal has a big dynamic range, the softer sounds simply will get lost under all the noise. Unfortunately, your receiver's automatic gain control (AGC) will make sure of it. Here's why:

## Clamping Down

SSB, being a special form of AM, sends your voice by modulating (changing) the strength of the RF power coming from your transmitter, in step with your voice waveform. Because your signal may go halfway around the world, though, the absolute strength of it can vary quite a bit from moment to moment. If we make our receiver respond only to the signal's strength, the resulting volume changes resulting from fading, interference, etc., will drive us out of our minds. One moment the signal may be barely audible and the next moment it may blast us out of our chairs. We certainly can make receivers that way, and many were like that in the early days. But there's a way out, and virtually all modern radios employ it.

It's called AGC. Luckily for us, the fading in and out of radio signals occurs much slower than the frequencies present in voice signals. The lower end of the vocal spectrum is about 200 to 300 Hz, while fading occurs in the 0.25-to-2-second range, which corresponds to between about 4 to 0.5 Hz. So, it's easy to make a circuit which ignores the fast changes of voice modulation but can follow the slow fades.

And that's just what AGC does. As the signal fades up and down, the circuit controls the radio's overall gain inversely. In other words, when the signal gets weak, the gain goes up, and when the signal booms in, the gain goes down. The result is that the signal appears to stay at a fairly constant level, and thus a fairly constant volume. Ahhh, much more comfortable.

I know I've taken the long way around here, but the point I'm trying to make is that your apparent loudness depends on the range between your softest and loudest sounds, not on your signal strength (unless, of course, it's very, very weak). The bigger the vocal dynamic range, the softer you sound, because your average voice level is so much lower than the peak level.

## Sometimes Faster Isn't Better

So, why not simply speed up the response of the AGC circuit and let it reduce the dynamic range of your voice signal so that you can hear the softer sounds? Well, you can do that, but, of course, it also brings up all that noise and static, too! If you have a radio with a FAST/SLOW AGC control, try putting it on FAST and you'll see what I mean. It does indeed make the voice signal sound compressed, but all that extra noise pumping up and down more than offsets any benefit.

## At the Source

But why not compress the dynamic range at the transmitter, causing the various vocal sounds to be nearly at the same level

before you even send them into the ether? That way, the receiver will hear them all and the background noise will not be increased. That's exactly what a speech processor does. All but the lowest-cost HF rigs made today have some form of a speech processor. Using one makes your signal sound a *lot* louder, without actually increasing the maximum power output of your rig. Of course, what you're doing is increasing the *average* power, which was fairly low before you turned the processor on.

## Abuse


Speech processors are great, but they are easily abused. If you turn one up too high, it really distorts your voice and can even cause "splatter" by increasing your transmit bandwidth. That's not only annoying, it's illegal!

## Voice Tailoring

Another way to increase your apparent signal strength is to adjust the frequency response of your microphone. We get most of our intelligibility from the higher sounds in our speech. I don't mean the hi-fi range out at 20 kHz, I mean the range from maybe 1 to 3 kHz. A microphone or equalizer that is made to weaken the lower sounds, thereby comparatively increasing the higher ones, gives you "punch" and makes you very intelligible, even with a weak signal. Be careful, though. Just as with speech processing, you can carry this too far and ruin your signal.

Well, I think we've covered most of the essentials of getting yourself heard. Happy transmitting and see you all next time. 73 from KB1UM. **RF**

## Removable Call Signs 2 1/4"x8" PLASTIC



AMATEUR RADIO

**W1AW**

ORDER NOW

## Great Xmas Gift

- Magnetic or Suction-Cup Mounted
- Your Call Letters or Repeater Freq
- Display Sign on Trunk or Rear Window
- Transferable From Car to Car
- No Call Lettering Remains on Vehicle

Order -Magnetic or Suction-Mounted Version! Select -Black, Blue or Red Background!

PRICE: \$9.95. . . . 2/\$18



1923 Edward Lane  
Merrick, NY 11566  
Phone 516-546-4362

Serving Ham Radio Over 12 Years  
CIRCLE 35 ON READER SERVICE CARD





# radio magic

by Michael Bryce WB8VGE

Here's another antenna project for you to enjoy before autumn's gentle days drift into winter's frozen night. This time it's an antenna called the "center feed zepp," and it is really easy to build. It is so easy, in fact, that you can get ALL the parts at your local Radio Shack and there is *nothing* to cut or measure.

You will need a heavy-duty soldering iron or a small propane torch for soldering the connections together. But the soldering isn't complicated—you won't even have to solder a PL239 connector. But you will have to use an antenna tuner and the tuner will need a 4:1 balun or, as it is sometimes called, the "open wire" feed option. An external SWR meter might also come in handy (Figure 1), although some newer rigs have these built-in.

This antenna design will cover all the main ham bands except for 160 meters (1.8 MHz). You can even add 160 meters if you want to by increasing the length of the antenna. As it is now, you get coverage from 80 to 10 meters (3.5 MHz to 28 MHz), including the WARC bands.

You can install this antenna either as a horizontal dipole or as an inverted Vee. It depends on your lot size and preferences. You can also shorten the elements, but

you'll lose some band coverage, especially on the lower frequencies such as 80 and 75 meters.

## Construction is Simple

The only part for this antenna you'll have to cook up yourself is the center block. (See Figure 2.) I made mine out of a small hunk of plastic. A piece of sealed wood would work just as well. So would just about any other type of non-conductor. Whatever you choose, make it something easy to work with that will stand up to the weather and the UV light from Mr. Sun. You would be surprised at the amount of damage just one year's exposure to the elements can do to an antenna!

On your shopping trip, pick up two packages of antenna wire, each 70 feet long. (So, from end to end, the antenna will be 140 feet long, not including the support lines.) Get one package of 300 ohm TV twin lead. A roll or two of support line will be required also. I use nylon cord for this as it is both lightweight and survives exposure to the sun. Only you will know how much line to get. One package of antenna end insulators, a roll of electrical tape, and a tube of RTV sealer will complete your shopping trip.

## The Center Insulator

In Figure 2, you will see the dimensions of the plastic block I used to make my version of this antenna. You don't have to duplicate these exact dimensions—we're not launching missiles here.

Start by drilling out the center insulator. I used a drill press and some hand files to get the job done. The idea is to provide two slots in the material so we can wrap the twin lead through and back again on itself. This will help keep the strain off of the feedline. Two holes in the ends allow us to tie off the ends of the antenna wire while providing a

strain-free place to solder our twin lead to. A hole may be drilled in the center to support the antenna as an inverted Vee.

After you have drilled the center insulator, attach one end of each coil of antenna wire to the center insulator. Do not uncoil the wires yet! If you do, you'll end up with a giant mess on your hands. Attach the twin lead, one wire to each side of the insulator, and solder the connections. Be sure you have a good connection on both sides; this is not the place to have a cold solder joint, especially when it's hanging 40 feet in the air. Now, apply a large glob of RTV sealer to the entire insulator, especially on the soldered connections we just made. After you have allowed the RTV to set for about 24 hours, tape up the entire mess with your roll of electrical tape. The tape will protect the ends of the twin lead and will prevent damage by the sun to the insulator block.

Finish construction by adding the end insulators to the wires. Don't uncoil the wires just yet. Solder these to keep them from pulling apart. Add your support lines to the ends of each insulator. Now comes the fun part—getting the thing in the air




Figure 1. Adjusting the antenna tuner for lowest SWR.

**UNADILLA ANTENNA MANUFACTURING CO.**  
PO Box 4215 BV • Andover, MA 01810

(508) 474-8949  
24 Hour FAX

**THE BIG SIGNAL**  
Amateur Antenna Baluns

(508) 475-7831  
9-5 EST M-F

For over 20 years, preferred by Amateur, Military and Commercial Operators. Assembled with all stainless steel hardware and a built-in lightning arrester minimizes your TVI, maximizes your power.

Transformer Baluns	
For medium power (1000 watts RF minimum) and broadband operation 3-40 MHz.	
<b>W2AU 1:1</b> 50/50 or 75/75Ω Dipoles, V's Beam Models, Quads	<b>W2AU 4:1</b> 200/50 or 300/75Ω Hi-Impedance Antennas (ie: Folded Dipoles)

Non-Transformer Baluns	
<b>W2DU-HF</b> 1.8-30 MHz 3000-9000W 1500-5000W	<b>W2DU-VHF</b> 30-300 MHz 2000-4000W 1200-2400W

**Contact Your Local Ham Dealer Today!!!**

Baluns-Antenna Kits-Filters-Center Insulators-ENDsulators™-Coaxial Relays  
All products come with a 30 Day Warranty

**-NOTICE-**  
We are the **NEW** manufacturers of the original  
**JAMES MILLEN™** Products  
(508) 975-2711 9am-5pm EST M-F

CIRCLE 136 ON READER SERVICE CARD

★ **MADISON SHOPPER** ★

**ORDERS: 1 (800) 231-3057**  
1 (713) 729-7300 or 729-8800  
FAX 1 (713) 729-4766

New and Used Meters,  
Tubes, Transformers,  
Filter Capacitors  
And More

**FREE List Call**

**Madison Electronics**  
12310 Zavalla Street  
Houston, TX 77085

**CIRCLE 25 ON READER SERVICE CARD**

**MORSE CODE MUSIC!**

**SENSATIONAL NEW WAY TO LEARN CODE—Do Aerobics, Sing, Jog, or Drive while learning code!** A fun & easy way to learn or retain Morse Code skills. Now the secret is yours with this amazing synchronized breakthrough! Great for Novice, Technician or the classroom. Order:

**"THE RHYTHM OF THE CODE"**  
Version 2 cassette today!

Send \$9.95 and we'll pay the shipping to:

**KAWA RECORDS**  
P.O. Box 319-RF  
Weymouth, MA 02188

Check or money order only. We ship all orders within 5 days.  
Overseas please add \$2.00 for air mail.  
MA residents add 5% sales tax.

CIRCLE 2 ON READER SERVICE CARD

**QSO Tutor®**  
Study Aid for the Amateur Radio Exams

**No-Code Tech. Package - \$39.95**

Mac IBM Now Available, New No-Code Question Pool

• Runs on IBM compatibles or Macintoshes  
• Programs are available for Novice, Technician, No-Code Technician, General, Advanced and Extra Amateur class exams as well as Commercial Radiotelephone and Commercial Radar Endorsement. Each program sold separately.  
• Work with the entire question pools, or study questions automatically selected by the program from your weakest areas.  
• Questions current as of July 1993  
• Includes full screen graphics, explanations on appropriate questions and, on the IBM version, a pop-up calculator.  
• Logs multiple study sessions and allows resuming at a later time. Returns to review missed questions if desired.  
• Creates randomly generated sample tests on-line or printed with graphics on Epson/IBM or Macintosh printers.  
• Public Domain Morse code tutor is included on request at no extra charge.

**\$29.95** per class for Novice thru Extra and Comm. Radar  
PA residents add 6%. Price includes shipping.

**QSO Software**  
208 Partridge Way  
Kennett Square, PA 19348  
215-347-2109 (Voice or FAX)

**\$39.95** per class for No-Code Tech. (Novice and Tech. programs) and Commercial Radiotelephone

**QSO Software**  
Specialist in Software for the Micro. by WB3R

CIRCLE 145 ON READER SERVICE CARD



without getting all tangled up in one huge knot.

### Safety First!

Before you install any antenna, check your location for overhead wires. *If your antenna falls across a power line, you are in danger of being killed.* If you do drop your antenna across any power lines, don't touch it, let it fall—don't try to remove it. Call your local power company.

If you're lucky enough to install the antenna as a horizontal dipole, then fasten one end of one 70-foot wire to your support using the support line. Unwind the coil carefully as you walk it out. This copper-weld wire tangles very easily. Now, do the same for the other side as you pull the antenna up into the air.

Inverted Vee style installation requires a bit more skill and perhaps a helper, too. Hoist the center insulator up about 12 feet or so as you play out the ends of the coils. Try (and it's much easier said than done) not to get the wires tangled together or with the feedline. Again, watch out for those power lines!

### Tune Up

Connect the open line feed to your antenna tuner at the proper location. Most antenna tuners have the location marked very clearly for open line feeders. Start with the controls in the middle positions and, while you're listening to the rig, tune for maximum sound from the receiver. This will put you real close to the resonant point of the tuner. Apply a small amount of RF (after listening to be sure the frequency is clear) and adjust the antenna tuner for the lowest SWR as shown on a wattmeter or SWR bridge. Some of the newer transceivers have an SWR bridge built in. Figure 1 shows a complete setup of rig, SWR meter and

antenna tuner.

### Why It Works

The key to this antenna is the feedline. The open line feed has very low loss characteristics. It's much better than coax and much cheaper too. When coupled to a tuner, you match the antenna's impedance to the rig's 50 ohm output. All the RF then gets radiated into the air with very little being lost. Of course, there is always some loss when using an antenna tuner, but it's a small trade-off for this kind of performance.

Well then, if open line feed is so great, why don't we see it more often? That's a good question—and the answer is quite simple. Open line feed is harder to handle than coax. If it gets wet, it won't work as well as when it's dry. The wind blowing the feedline around will change its operating characteristics. You can see the results as you watch the SWR change while the wind is blowing.

You must keep open wire feedline away from metal objects. This includes mast pipes, spouting, aluminum siding, and so on. Remember the old standoffs you used to use for TV twin lead on your outside TV antenna? Coax is much easier to work with. You can tape the stuff to the mast pipe and practically tie it in knots, it won't affect the output of your gear.




Figure 2. Antenna insulator block construction detail.

### Does It Work?

The center feed zepp works great across all bands. During this year's Field Day operation, I used this antenna strung up between two trees. Running my usual QRP power of 2.5 watts, I could answer just about everything I could hear. I was especially pleased by our success on 80 meter CW. I even managed to work quite a few SSB stations running my


QRP power. Operating SSB while running QRP is not an easy task, especially during Field Day.

Have fun building this antenna project. Most hams find building antennas a great part of the hobby. Antennas like this are fun, simple and cost effective.

Next month we'll check out what to do when the bands are just plain dead. Stay tuned for more "Radio Magic."

RF

## AMATEUR TELEVISION



**TVC-4G**  
only \$89

### SEE THE SPACE SHUTTLE VIDEO

Many ATV repeaters and individuals are retransmitting Space Shuttle Video & Audio from their TVRO's tuned to Satcom F2-R transponder 13. Others may be retransmitting weather radar during significant storms. If it is being done in your area on 70 CM - check page 413 in the 91-92 ARRL Repeater Directory or call us, ATV repeaters are springing up all over - all you need is one of the TVC-4G ATV 420-450 MHz downconverters, add any TV set to ch 2, 3 or 4 and a 70 CM antenna. We also have downconverters and antennas for the 900 and 1200 MHz amateur bands. In fact we are your one stop for all your ATV needs and info. Hams, call for our complete ATV catalog - antennas, transceivers, amplifiers. We ship most items within 24 hours after you call.

(818) 447-4565 m-f 8am-5:30pm pst. Visa, MC, COD  
P.C. ELECTRONICS Tom (W6ORG)  
2522-WG Paxson Ln Arcadia CA 91007 Maryann (WB6YSS)

SAVE on ALL **REALISTIC**

### SCANNERS & RADIOS

Will you  
pay too-much?  
For pricing,  
CALL FREE  
**800-433-SAVE**

SINCE 1981



**PRO43**  
\$298

**USRADIO**

377 PLAZA, GRANBURY TX, 76048

### SPY ON THE EARTH



See live on  
your PC  
what  
satellites in  
orbit see

Learn how you can benefit greatly from this exciting new technology. Send \$39 check or M.O. (\$45 air, \$50 overseas) for our fantastic 12 diskette set of professional quality copyrighted programs (IBM type) that does satellite tracking, image acquisition, image processing, 3-D projections and more. Direct reception from the satellites guaranteed worldwide without a satellite dish. Schematics included for interface. For FREE information log-on to our bulletin board anytime at: (718) 740-3911.

**VANGUARD Electronic Labs**  
Dept. RF, 196-23 Jamaica Ave.  
Holliis, NY 11423 Tel. 718-468-2720

## THE TOOL PAKS™



**\$89.97**

### The Original backpack for tools

Organize over 100 tools in multiple pockets, compartments, and fold-out panels. All Tool Paks™ are designed to be tough, made from 1000 denier Cordura.

**\$24.97**



### The Fanny Pak

With 3 internal tool compartments, a fold-out tool panel, and a heavy-duty buckle, it's the perfect Tool Pak™ for smaller jobs.

### The new Tool Tote

It's a tool box with a soft side. Featuring 14 external pockets for easy tool accessibility.



**\$24.97**

**TOOL PAK™**


**1-800-258-8458**

PAKTEK 7307 82nd St. Ct. S.W., Tacoma, WA 98498



CIRCLE 117 ON READER SERVICE CARD





*Joe Carr*

# antennas, etc.

by Joseph J. Carr K4IPV

## Antenna Angle of Radiation

Long-distance radio propagation occurs in the high frequency (HF) shortwave bands (and lower VHF bands) because of ionospheric "skip." Radio signals from the surface are refracted in the ionosphere, and some of them

refract enough to undergo total internal reflection, i.e. they head back towards the surface. The skip distance (Figure 1) determines how far one can work other stations. The radio wave is transmitted at the angle of radiation into the ionosphere, where it is refracted

enough to bend back to earth, where it can be received. In the distance between where the local ground wave dies out and where the sky wave is received is a dead zone of no reception. At higher frequencies (e.g. 10-20 meters), the ground wave may die out quite rapidly (on-

agation between Australia (VK) and England (G) using professional ionospheric sounding methods.

One of the factors that affects the length of the skip distance is the angle of radiation of the radio wave. This angle is partially a function of the operating frequency, and partially a function of the natural radiation angle of the antenna. The frequency effects are seen as a function of the ionization level, and how much a given frequency is refracted. Thus, skip distance can be determined by frequency selection.

The antenna radiation angle is the angle of the vertical lobe with respect to the earth's surface (Figure 2), and is partially a function of its design and partially of its installation configuration. For example, a 5/8-wavelength vertical antenna tends to have a lower angle of radiation than a 1/4-wave vertical antenna. Similarly, the dipole's angle of radiation is a function of its height above ground. By selecting the type of antenna, and its mount-




Figure 1. The skip distance is a function of the angle of radiation.


*"An annular eclipse differs from a total eclipse because the perceived diameter of the moon as it blocks the sun's light is smaller than the solar disk, so the result is a 'ring of fire' in the sky."*

ly a few miles), and the skip distance is very long. As a result, it is not uncommon to find two stations 40 miles apart unable to hear each other, and therefore have their QSO relayed by a DX station. I've had many a QSO where stations in Baltimore, Maryland, only 35 miles from my QTH, had to have a South American station relay messages to me! Very long distance communications occur when multihop skip occurs. An Australian radio scientist, who I met at an engineering conference, recently told me of observing seven and nine hop prop-

ing height, you can regulate whether you are going to see longer or shorter distances on each "hop" of your signal. In general, lower angles of radiation provide longer DX contacts.

Figure 3 shows how angle of radiation affects skip distance. Low angle of radiation signals tend to travel farther with respect to the earth's surface before refracting, so they produce the longest skip distances. Higher angles of radiation (1) have shorter skip distances (A-B) because they tend to return to earth rapidly. In summertime, some high frequency bands

## Fast Packet Ticket!



The PackeTwin™ Wireless Communications System

Thinking about the move to packet radio? Or have you already tried 1200 baud packet only to become quickly discouraged?

At Gracilis, we've got the ticket to the kind of speed you're looking for.

Using our PackeTwin system with your existing IBM®-PC or compatible, you'll easily be able to communicate with other packet radio stations at rates of 9600 or 19,200 baud. If higher speeds are desired, the popular WA4DSY modem can be constructed and added to provide operation at 56,000bps.

When you order our PackeTwin Wireless Communications System, you'll get a plug-n-play 9600/19,200 baud system, complete with modem and palm-size two watt UHF transceiver. You supply the PC and antenna—We supply the rest!

Consider these important features...

- Exclusive use of the PC's DMA channels provides an upgrade path to 1Mbps
- A second channel is included that can be used to provide a separate RS-232 or RS-422 interface
- Free software provides access to AX.25 and TCP/IP networks
- Free firmware updates

For information contact your distributor, or...



The new name in Packet Radio

623 Palace Street, Aurora, IL 60506 Ph: (708) 801-8800/FAX: (708) 844-0183  
Email: info@gracilis.com

IBM is a registered trademark of International Business Machines Inc.; PackeTwin is a trademark of Gracilis, Inc.



CIRCLE 291 ON READER SERVICE CARD

## Say You Saw It In Radio Fun

### Power Filter for Mobile Radios

✂ NOISE !!

- Suitable for virtually any make/model of amateur mobile radio !
- Provides exceptional ignition, alternator, fan motor noise filtering !
- Installs easily between the battery and radio's DC power input
- Handles up to 15A @ 14VDC (w/fuse)
- Solid-state clamping for voltage spikes
- Equipped with Velcro for easy mounting to almost any surface
- 16 gauge leads, 10 inches long
- Connectors allow for radio portability
- 4 in. x 3 in. x 1.5 in., rugged construction

☺ ORDER TODAY ! ☺

\$29.95 plus \$5.00 S/H (OH add 6.25%)

Check or Money Order to:

Xionix

1544 Craigwood Road  
Toledo, OH 43612-2255  
(419) 476-7334

CIRCLE 347 ON READER SERVICE CARD

TOLL FREE 1-800-666-0908 PRICING AND ORDERS ONLY

### KENWOOD




CALL FOR ALL KENWOOD

### YAESU



CALL FOR ALL YAESU  
RADIOS & ACCESSORIES

### ALINCO



CALL  
FOR  
ALL  
ALINCO

### ICOM



CALL FOR ALL ICOM

### STANDARD



CALL FOR ALL STANDARD

AEA • ASTRON • AZDEN • COMET • CUSHCRAFT • DIAMOND • KANTRONICS

MFJ • SANGEAN • SONY SHORTWAVE • DRAKE • MANY MORE...

NEW EQUIPMENT PRICING AND ORDERS 1-800-666-0908 OUT OF STATE  
TECHNICAL, USED GEAR, INFO 203-666-6227 24HR. FAX 203-667-3561

**LENTINI COMMUNICATIONS INC.**  
21 GARFIELD STREET, NEWINGTON, CT 06111


Hours: M-F 10-6,  
SAT. 10-4



C.O.D.s Same Day  
OK Shipping

CIRCLE 234 ON READER SERVICE CARD





**Figure 2.** The angle of radiation is the angle between the maximum signal line of the elevation lobe and the earth's surface.


(e.g. 10 meters) offer high-angle "short skip," and longer skip during the other months. The difference is the level of ionization of the ionosphere. At higher angles of radiation, there will be a critical angle wave and escape angle waves that are not returned to earth. These waves are not used for terrestrial communications or broadcasting. Figure 3 also shows the difference between single-hop skip and multi-hop skip as a function of incident angle. While multi-hop signals offer greater distances, it is also generally true that a multi-hop transmission is more subject to fading, and weaker, than a single-hop transmission.

#### Wanna Watch an Eclipse on Your Radio?

There will be an annular solar eclipse in the

USA on 10 May 1994. It will be the last such eclipse until 2017. An annular eclipse differs from a total eclipse because the perceived diameter of the moon as it blocks the sun's light is smaller than the solar disk, so the result is a "ring of fire" in the sky. Eclipses affect radio propagation for a brief period. The reason why ionospheric skip occurs is that ionization of the earth's upper atmosphere results from the bombardment of the sun's energy on it. That's why daytime and nighttime propagation are so different: During the day ionization levels are high, but after dark the levels drop off rapidly. During an eclipse, the region along the eclipse path thinks it's nighttime, so nighttime conditions appear.

Several different types of observation are open to the scientifically-minded amateur.



**Figure 3.** Skip distance is a function of the angle of radiation and the number of hops the signal makes.

Some simply involve monitoring the bands for changes in DX patterns. Others involve transmitting test signals and setting up networks of observers. My "Carr's Corner" column in *73 Amateur Radio Today* for October 1993 provides details. Also, if you want a bibliography of past articles that you can look up (mostly for the 1970, 1976 and 1979 eclipses), then send me a self-addressed stamped envelope (SASE) with two first-class stamps on it (I did your literature search for you). Alternatively, I've provided the biblio to *Radio Fun* and they can bang it onto their computer bulletin board (603-924-9343). Ham science teachers might want to use their radios to help students learn something of the physics of eclipses as they interact with earth's atmosphere.


Radio-literate science teachers might also want to learn about very low frequency

monitoring of solar events and about natural signals called "whistlers." These events can be monitored with simple home-brew receivers. Also, the VLF radio stations can be monitored on ham receivers if a frequency converter is used ahead of the receiver. A 1991 book on VLF circuits, titled *The Low and Medium Frequency Radio Scrapbook*, 7th Edition, is available from its author, Ken Cornell W2IMB (225 Baltimore Avenue, Point Pleasant Beach NJ 08742). I paid \$17.95 for the book from EEB (323 Mill Street N.E., Vienna VA 22180; 1-800-368-3270). Information on whistlers can be obtained from Mike Mideke (POB 123, San Simeon CA 93452). He offers *Whistler Hunter's Guide* for \$6, and a narrated 60-minute cassette tape for \$10 (the tape is invaluable for determining what you are hearing).

RF

THE ANSWER IS GAP TECHNOLOGY • THE ANSWER IS GAP TECHNOLOGY

**Q** An Antenna with No Earth Loss?  
**A** Yes... the answer is GAP's revolutionary technology.



If you're looking for an antenna that can out perform the others and give you the edge, you're looking for a GAP. The Challenger DX-VIII is the revolutionary design that answers your demands for multi-band operation and unequal efficiency with low noise. This is the technology that eliminates Earth Loss. GAP delivers from an elevated feed; your power doesn't disappear into the ground. Put it up. Turn it on. No tuning. No frustration. GAP delivers everything but the hassles. And — GAP delivers at a fraction of the cost of the "so-called" competition.

The Challenger DX-VIII  
80m 40m 20m 15m 12m 10m 6m 2m

**\$249**  
plus shipping

All out efficiency.  
All out performance.  
GAP gets it all out.



6010 Bldg. B  
N. Old Dixie Hwy.  
Vero Beach, FL 32967  
(407) 778-3728  
Commercial Frequencies Available

THE ANSWER IS GAP TECHNOLOGY • THE ANSWER IS GAP TECHNOLOGY

#### GREAT SWBC SOFTWARE!

**NEW SWBC DATABASE AND LOGGING UTILITY**  
Contains thousands of changeable records for SWBC radio stations with their frequencies, schedules, languages, countries. This program prints LOGGING REPORTS for submission to your favorite clubs. With the data entered only once, logging reports can be printed in different formats with only a keystroke. **only \$29.95**

Specify IBM compatible 3.5 or 5.25 disks

**SWBC STATION DATABASE**  
Contains thousands of radio station records which can be updated, deleted, or create new. Sorts by Station, Frequency, Schedule, Language, Country, or Continent. **only \$19.95**

**DX-SWL PROGRAM DATABASE**  
Radio station schedules and frequencies for all SWL programs on Shortwave. Don't miss your favorite shows! **only \$9.95**

**ORCHID CITY SOFTWARE**  
P.O. BOX 18402  
WEST PALM BEACH, FL 33416

CIRCLE 73 ON READER SERVICE CARD

#### SAM Amateur Radio Callsign Database

For your PC Compatible. Find Hams by Callsign or Name. Browse thru calls. Full export by QTH with custom output. All U.S. and Canada Calls. Ideal for mailing lists, QSLs, etc. Uses 16 MB Hard Disk. High Density Floppy (1.44 or 1.2) required for install. Updates and options available. Interfaces to LOGic, LogMaster, HyperLog and others. Demo disk \$3.00.

County Cross Reference Option adds county to address info. Lookup or export all Hams in a county. Only \$7.50.

**\$39.95**  
\$5 s/h. VISA/MC

**RT Systems Inc.**  
Box 8, Lacey's Spring, AL 35754  
**205-882-9292**

# KENWOOD

Amateur Radio Sales and Service

## TH-78A

# \$420

cash price

orders &  
price  
quotes

**1-800-433-3203**



Proudly serving the Amateur Community for over 25 years.

5635 E. Rosedale St. Fort Worth, Texas 76112

FAX(817)457-2429


Questions (817)429-9761

VISA • MASTERCARD • DISCOVER • AMERICAN EXPRESS

Prices and availability are subject to change without notice.

CIRCLE 331 ON READER SERVICE CARD





# upgrade . . . don't stop now

by Gordon West WB6NOA

## What's on 2 Meter SSB Anyway?

Your typical 2 meter hand-held and mobile transceivers operate in only one mode: frequency modulation, abbreviated FM. Other equipment may use phase modulation (PM) for transmit, but frequency modulation and phase modulation all sound about the same. PM emission occupies a narrow band of frequencies, typically plus-or-minus 5 kHz from the center frequency. You usually see this specification noted as "+/-5 kHz DEV," indicating the carrier deviates up to 5,000 cycles up and down from the resting frequency.

FM is great for local communication through repeaters and simplex communication over the VHF or UHF bands. But FM emissions suffer from phase distortion when the signal goes more than a couple hundred miles. Can you get 200 miles out of an FM set? Sure, try listening in on the space shuttle when the astronauts transmit down to us on 145.55 MHz.

There is a unique group of 2 meter operators who run "multimode" mobile and base transceivers. Besides FM, these sets may also tune in CW and single sideband. On 2 meters, single sideband is used for many long-range contacts:

- Satellite reception and communications
- Long-haul tropospheric ducting
- Meteor burst communications
- CW for moonbounce
- SSB and CW for sporadic-E communications

Two meter single sideband activity is not compatible with FM. A 2 meter SSBer can't talk to an FMer, and an FMer can't talk to a station operating on 2 meters SSB. The two don't mix.

The frequencies from 145.80 MHz to 146.00 MHz are reserved exclusively for weak signal SSB satellite communications. Never run FM between 145.80 and 146.00 MHz! No FM here!

With an SSB multimode 2 meter transceiver,

it's easy to tune in to orbiting satellites. Even a small ground plane can easily receive hams thousands of miles away chatting over the orbiting OSCARs. It takes multimode 2 meter SSB gear to tune them in. Just a simple ground plane is plenty for receive, and a relatively simple beam antenna lets everyone with a no-code Technician Class license and higher work off of the "birds."

Down around 144.20 MHz is the hangout for 2 meter SSB stations who are working direct over distances of up to 500 to 800 miles away. They use horizontal beam antennas, and with the right conditions they can talk for hours on the 2 meter band in excess of 500 miles away. Most 2 meter multimode operators use a 100 watt "brick," another name for that block amplifier that needs a 12 volt battery to keep it going. Although 100 watts output is handy, it's not absolutely necessary. I have worked many stations well over 400 miles away on my 25 watt Kenwood 751 multimode 2 meter transceiver "barefoot" (without an amplifier). A long boom beam, semi-rigid coax, and a hot transceiver is all that's necessary for extra-long range on 2 meter SSB.

And if you really get serious about your weak signal operation, you can plan ahead for meteor showers or the monthly moonbounce "window" that lets you hear signals literally out of this world. Most of this activity takes place below 144.10 MHz.

Since FM and weak signal 2 meter SSB is NOT compatible on the same frequency, never use your FM hand-held, mobile, or base transceiver below 144.30 MHz. Everything at the bottom of the 2 meter band below 144.30 has been band-planned for weak signal SSB or CW. No FM below 144.30 MHz!

If operating through 2 meter FM repeaters has lost its excitement, and it's no big deal to work FM across town on simplex, do consider a new or used 2 meter multimode transceiver for 2 meter SSB communications. It's a small, elite group down around 144.20,





Photo A. SSB signals on 2 meters are best tuned in using horizontal polarization.

MHz	Use
*144.00-144.05	EME (CW)
*144.05-144.06	Propagation beacons (old band plan)
*144.06-144.10	General CW and weak signals
*144.10-144.20	EME and weak-signal SSB
*144.20	National SSB calling frequency
*144.20-144.30	General SSB operation, upper sideband
*144.275-144.300	New beacon band
*144.30-144.50	New OSCAR subband plus simplex
144.50-144.60	Linear translator inputs
144.60-144.90	FM repeater inputs
144.90-145.10	Weak signal and FM simplex
145.10-145.20	Linear translator outputs plus packet
145.20-145.50	FM repeater outputs
145.50-145.80	Miscellaneous and experimental modes
*145.80-146.00	OSCAR subband—satellite use only!
146.01-147.37	Repeater inputs
146.40-146.58	Simplex
146.61-146.97	Repeater outputs
147.00-147.39	Repeater outputs
147.42-147.57	Simplex
147.60-147.99	Repeater inputs

Table 1. 2 meter band plan with "\*" denoting CW-and-SSB-only areas of operation.

and an ever-growing fraternity of satellite operators up at 145.80 MHz, and you are encouraged to expand your operating skills by switching over to a mode that will let you literally work out of this world on sideband of CW or 2 meters. **RF**

## Is Your Shack Grounded?



Ground all of your equipment chassis to a single earth ground in one easy installation. Money back guarantee, if not satisfied! J. Martin Systems

Solid Copper Buss  
Stainless Steel Hardware  
Grounding Stud Every 6 Inches  
Top or Back Installation

2 ft.	\$11.95	Custom
3 ft.	\$16.95	Lengths
4 ft.	\$21.95	Available

Add \$3.00 S/H  
Mail check/money order to:  
J.M.S.  
35 Hilltop Ave., Dept. RF  
Stamford, CT 06907

## Where's the Tower?

• No Holes • No Guys • No Damage •

Patent Pending Roof Crest Mount holds yagis, corners, parabolas, rotators, beams, wire antennas, up to 10 sq ft at 90 mph. Complete, easy to install & remove.

**Antennas West**  
Box 50062-S, Provo UT 84605

Info  
\$1

\$230 + \$14 S&H  
Order Hotline:  
801-373-8425







# what's next?

by Carole Perry WB2MGP

## From the Mouths of Babes

One of the nice things about having many friends and acquaintances through ham radio is that I also get to meet the offspring or "harmonics" of these folks. Because I teach an amateur radio program to over 400 kids every term at a local intermediate school, I get to have many of the children of ham radio friends in my classes. It's always fun to rise to the challenge of motivating these youngsters to get licensed after their dads have tried every trick in the book to get them interested in ham radio.

One exception to the "frustrated-ham-radio-dad" club is Mike Siegel WB2FCP. Mike has been a staunch supporter of my radio efforts at Intermediate School 72 in Staten Island for many years. We first met when Mike volunteered to help out with our SSTV contact with the *Challenger* space shuttle on August 1, 1985. Since that time, Mike has come to my school to talk with my ham radio classes and to share his interesting background with the children. Mike is an engineer at ABC television studios who has won an Emmy for his work with computer video graphics.

Mike is a ham who is worthy of having a column written all about him, but this month's *Radio Fun* "What's Next?" column is going to focus on Mike's young daughter, Debbie. Debbie wasn't in my class, but she did do a wonderful job speaking to my class one morning in June as she conducted a 2 meter demo from her own school. Children always enjoy speaking with other kids on the radio. Never underestimate the importance of peer group influence with young people!

Debbie is N2SIJ. She obtained her Novice

license in 1991 when she was just eight years old. Mike tells me that her original motivation for getting a ham radio license was to be able to speak with her dad as he traveled home from work every day. Debbie found it difficult to get the Novice license as she struggled with the theory. Interestingly, though, she enjoyed the code and found it to be fun.

At the end of July 1992 she obtained her HF/Technician license and was finally able to speak with her father as he made his daily commute home each afternoon. When working with young people in ham radio, it is important to show the practical use of what they are studying for. Talking to other kids at the mall or at sporting events, or being able to speak with a parent on a 2 meter rig is a great motivator!

When Debbie decided to do a major project on ham radio for her fourth-grade class, she enlisted Mike's help. He suggested that she get a higher license before doing the project. Debbie's words were, "Sure, let's do it."

In August 1992, Debbie passed the written portion of her General license. Now the push for the CW speed was in order. Starting that September, at approximately 5 words per minute, she was taught all the character sounds at 20 wpm until she could recognize all the characters sent at 20 wpm with 5 wpm spacing. Slowly and very steadily the spacing was shortened to yield 20 wpm by mid-December. She practiced daily for a test session to be taken in early February of 1993. By that time, her code speed was in excess of 27 wpm and she had no problem in passing her 20 wpm code test. This gave her an



Photo A. Debbie Siegel N2SIJ.

upgrade to General with a CSCE for the 20 wpm of the Extra Class test.

After a few weeks of some well-deserved rest, Debbie started to study for the Advanced written test, which she passed on May 15, 1993. The very next day Mike asked her when she wanted to take the Extra license written exam. He never expected to hear her say, "I want to get my Extra Class license while I'm still nine years old and before I present my project to my class in June."

Mike figured he would need six weeks to go over the written material for the Extra exam. But Debbie insisted on aiming for the test session on June 7th, which would mean three weeks of study time, not six. A study routine was set up that required one and a half to two hours a day of studying, with double that on the weekend. On June 7th, at the tender age of nine years old, Debra Siegel passed her Extra Class written exam with a perfect score.

The following week, Debbie presented her ham radio project to her fourth-grade class and announced proudly to her classmates that she had made it to the top. Dur-

ing that presentation, Debbie called her dad on a local repeater and then gave a live demonstration with the children in my ham radio classes to her classmates and teacher. The sixth-, seventh- and eighth-graders at my end really enjoyed participating in the demo. "School-to-school" radio contacts are always terrific for kids. That's the whole premise of the "CQ All Schools" net every Tuesday and Thursday at 17:30 UTC (16:30 UTC winter time), on 28.303 MHz.

Debbie is an excellent student. She has been a member of a competitive dance group and studies jazz and tap dancing. Most of all, as her dad points out, "she's still a little girl." Even though she really likes ham radio and has a good station, one of her favorite pastimes is playing with her doll collection.

Debbie is the youngest member of an all-ham family. Her mother Elaine N2GET and brother Jeff N2IPU are both HF/Technicians. Mike WB2FCP is an Extra with over 30 years of ham radio experience. Needless to say, they are all proud of Debbie's performance. **RF**

## CHEST HARNESS and BELT HARNESS



### CHEST HARNESS

- Zippered/Padded Pocket for pens, note pads, extra battery, etc.
- Radio held chest height for hands free listening without earpiece

\$29.95

Both harnesses are MADE IN USA of 1000 Denier padded Cordura® from Dupont, with Velcro® adjustments to fit almost any size Handie-Talkie. Weatherproof, they won't deteriorate or rot from Rain, Snow, or Perspiration.

### BELT HARNESS

Handy for everyday use in carrying your Handie-Talkie on the belt.....\$18.95

Quantity Discount Available  
+\$3.50 S/H TX Res. +7.25% Sales Tax




Send Check or Money Order (USD)

**EMARS**

PO Box 781204 San Antonio TX 78278-1204  
Info: (210)493-7546


CIRCLE 353 ON READER SERVICE CARD



EUR-AM Electronics  
P. O. Box 990  
MEREDITH N.H.  
03253-0990

CIRCLE 83 ON READER SERVICE CARD

## UAI-10 AND UAI-20 UNIVERSAL REPEATER/LINK AUDIO INTERFACE



Detailed application manual  
Low power operation, 19ma @ 12v  
CTCSS decoder on the UAI-20 only  
Assembled, tested, one year warranty  
Link monitor-mix/monitor mute control  
Adjustable repeater/link/DTMF audio outputs  
Selectable DTMF mute on repeater and link audio  
Repeater, link, auxiliary and control audio inputs

UAI-10 \$44.00 UAI-20 \$89.00

CREATIVE CONTROL PRODUCTS

3185 Bunting Avenue  
Grand Junction, CO 81504  
(303) 434-9405



CIRCLE 146 ON READER SERVICE CARD

## Slow Scan Television

doesn't have to be expensive anymore.

Quality Color SSTV is easy and affordable with Pasokon TV

Pasokon TV \$229.95

Send and receive all popular modes.  
Hardware interface fits inside computer.

New - SSTV Snooper \$94.95

Small receive-only interface  
plugs into serial port.

Both require IBM PC/AT or compatible, '286 or better CPU, color VGA display, MS-DOS. Prices include free shipping to U.S.A. Write or call for complete details.

## Absolute Value Systems

115 Stedman St. #R  
Chelmsford, MA 01824-1823  
(508) 256-6907

CIRCLE 351 ON READER SERVICE CARD



# activities calendar

Send your announcements to: Radio Fun Activities Calendar, 70 Route 202-N, Peterborough NH 03458. We'll print as many as space allows, on a "first come-first listed" basis.

## OCT 2-3

**VIRGINIA BEACH, VA** Tidewater Radio Conventions, Inc., will present their 18th annual Virginia Beach Hamfest and Computer Fair/ARRL Virginia State Convention/Popular Communications SWL Convention, at the Virginia Beach Pavilion from 9 AM-5 PM Sat., and 9 AM-4 PM Sun. Speakers are Gordon West WB6NOA, and Roy Neal K6DUE. VE Exams, Flea Market, Tailgating, Forums, and more. Talk-in on 146.97. Order tickets (with SASE) from *Manny Steiner K4DOR, 3512 Olympia Ln., Virginia Beach VA 23452. Tel. (804) 340-6105.* Get Commercial info from *Lewis Steingold W4BLO, 1008 Crabbers Cove Ln., Virginia Beach, VA 23452. Tel. (804) 486-3800.*

## OCT 3

**ASHLAND, OH** The North Central Ohio Hamfest will be held from 8 AM-3 PM at Ashland County Fairgrounds, Flea Market, Forums, 2m Foxhunt. Talk-in on 147.105+. Contact *Wally Green, 3 East Liberty St., Ashland OH 44805. Tel. (419) 281-3903.*

**WARRINGTON, PA** The Mt. Airy VHF Radio Club, Inc., (Pack Rats) will sponsor their Hamarama at the Rt. 611 Drive In. Talk-in on 146.52 (simplex). Gates open at 7 AM. Set-up at 6 AM. Contact *K3EOD, (215) 742-3312.*

## OCT 8-9

**AUGUSTA, GA** The ARC of Augusta will sponsor a Special Event at the Augusta College Sports Complex, 3109 Wrightsboro Rd., from 6 PM-9 PM Fri.: 8 AM-5 PM Sat. Flea Market, VE Exams, Forums, Demos. Talk-in on 144.89/145.49, alt. 144.51/145.11. For tickets, tables, send check and SASE to *ARC of Augusta, P.O. Box 3072, Augusta GA 30914-3072.* For info, call *Ed Butorajac KM4QQ, (706) 798-1918.*

## OCT 9

**BELTON, TX** Ham Expo '93 will be held by the Temple ARC, at the Expo Center in Belton, from 7 AM-2 PM. VE Exams, Free Test Bench, Transmitter Hunt. Call *Eric N5WU, (817) 986-1257* or *Mike WA5EQQ, (817) 773-4768.* Write to *Temple ARC, 2014 S. 53rd, Temple TX 76504.*

**LIMA, OH** The Northwest Ohio ARC will host a Hamfest at the Allen County Fairgrounds. Contact *WB8BND, P.O. Box 211, Lima OH 45802.* VE Exams; pre-register with completed 610 and fee of \$5.60 to *ARRL-VEC, W8TY, 1370 N. Stevick Rd., Lima OH 45807.*

**TEANECK, NJ** The Bergen ARA will hold its annual Fall Hamfest from 8 AM-2 PM at Fairleigh Dickinson Univ. Contact *Jim Joyce K2ZO, (201) 664-6725, before 10 PM.* FCC VE Exams; contact *BARA VE Hotline, (201) 797-0151 before 10 PM.* Talk-in on 146.190/790 and 145.620 simplex.

**TITUSVILLE, FL** A Hamfest will be held at Sandpoint Park from 9 AM-5 PM, by the Titusville ARC. Advance

registration is required. Contact *John Lowe KE4BBC, (407) 267-2000, or Bud Hughes K4CWG, (407) 267-3450.* Talk-in on 146.910 (-600 kHz).

## OCT 9-10

**EL PASO, TX** The annual Internat'l Hamfiesta will be held at the Texas Nat'l Guard Bldg., 9100 Gateway Blvd., North. Sat. from 8 AM-5 PM; Sun. 8 AM-3 PM. Seminars. QCWA Breakfast. VE Exams both days. Talk-in on 146.88. Contact *Milly Wise W5OVH, P.O. Box 31628, El Paso TX 79931. Tel. (915) 751-4160.*

**MEMPHIS, TN** MemFest '93 Greater Memphis Amateur Radio and Computer Show, will be held at Shelby Farms Show Place Arena, 105 Germantown Road So., by the Mid-South ARA. Time: Sat. 9 AM-4 PM; Sun. 9 AM-2 PM. VE Exams both days, 9 AM-Noon. Flea Market Info: *Steve Cheeseman NX3W, 3290 New Getwell Suite 202, Memphis TN 38118. Tel. (901) 365-6621 (W); (901) 368-6781 (H).* General and Exhibitor Info: *Nita Wofford N4DON, 2966 Cordell, Memphis TN 38118. Tel. (901) 363-4971.*

## OCT 10

**DURHAM, CT** The Meriden ARC, the Middlesex ARS, and the Shoreline ARC, will jointly sponsor the "Nutmeg Hamfest" at the Fairgrounds in Durham. VE Exams. Talk-in on 147.96/36. Contact *Jim McCandless N1JZF, (203) 349-3353, 6 PM-10 PM; packet: N1JZF @ WINRG.CT.USA.NOAM. Mail: P.O. Box 193, Durham CT 06422.*

**WALL TOWNSHIP, NJ** The 6th annual Shore Area Ham and Computerfest, sponsored jointly by the Jersey Shore ARA (JSARS), Neptune ARA, Ocean-Monmouth ARC (OMARC), and Garden State ARA (GSARA), will be held at the Allaire Airport. Doors open 0800-1600. VE Exams. Talk-in on 145.110 (NK20) for cars; UNICOM 123.00 MHz for aircraft. Get details from *Al Jackson NK20, (908) 922-8121.* For tables/tickets, write to *Shore Area Hamfest, P.O. Box 635, Eatontown NJ 07724-0635.*

**WAUKESHA, WI** The Kettle Moraine RAC Inc., will hold its 15th annual Ham and Computer Swapfest at the Waukesha County Exposition Center, Hwy 5 & FT. Doors open 8 AM-1 PM. VE Exams by the Badger Examiners. Advance tickets \$4; 4' tables \$5; send a SASE and check payable to *KMRA Swapfest, P.O. Box 411, Waukesha WI 53187-0411.*

## OCT 16

**FRANKLIN, PA** The Fort Venango Mike & Key Club will hold a Ham Auction/Flea Market at the Venango County 4-H Fairgrounds, RT # 62, starting at 8 AM. Auction begins at 10 AM. Talk-in on 147.12+, 145.23-, and 145.19- MHz. Contact *Jerry Almes W3DTW, (814) 432-3647, or Bruno Wolozyn K3MHB, (814) 677-8694.* Or write to *The Ft. Venango Mike & Key Club, RD #1, P.O. Box 591, Cranberry PA 16319.*

**GRAND FORKS, ND** Forx ARC will sponsor a Hamfest at Grand Forks Civic Auditorium, 615-1 Ave. N., beginning at 8 AM. VE Exams at 10 AM, walk-ins welcome. Talk-in on 146.94. Contact *Bob Smith ND1H, 1203 Shakespeare Rd., Grand Forks ND. Tel. (701) 746-9498.*

**GRAY, TN** The 13th annual Tri-Cities Hamfest will be held at the Appalachian Fair Grounds, located off I-181 in Gray. Flea Market. Sponsors: Kingsport, Bristol, and Johnson City Radio Clubs. Mail inquiries to *Tri-Cities Hamfest, P.O. Box 3682 CRS, Johnson City TN 37602.*

**SANFORD, NC** A Fall Festival will be held from 8 AM-4 PM by the Central Carolina ARS. Location: Lions Club Fairgrounds, 7th & Weatherspoon Sts. Contact *April Maggart KD4QMU, 8512 Deep River Rd., Sanford NC 27330.*

**STARKE, FL** Bradford County Fairgrounds, US 301 North of Starke, will be the location for the 3rd annual Starke Hamfest, sponsored by the ARC - Bradford Area. Time: 0800-1600 hrs. Talk-in on 145.150- and 146.520 simplex. Contact *Donna KC4MXX, (904) 964-9491, or Tony WB2FGL, (904) 964-9328.* For reservations, make check payable to *ARC - Bradford Area, c/o Tony Spatafore WB2FGL, P.O. Box 852, Starke FL 32091.*

## OCT 17

**CAMBRIDGE, MA** A Tailgate Electronics, Computer and Amateur Radio Flea Market will be held from 9 AM-2 PM at Albany and Main Sts. Call (617) 253-3776. Mail reservations before Oct. 5th to *WIGSL, P.O. Box 82 MIT BR., Cambridge MA 02139.* Sponsors: MIT Radio Soc., and the Harvard Wireless Club. Talk-in on 146.52 and 449.725/444.725 pl 2A W1XMR.

**CENTRALIA, IL** The Centralia Wireless Assn., Inc., will hold its annual Hamfest at the Kaskaskia College Gym, 3 mi. NW of Centralia. Doors open at 8 AM. Talk-in on 147.27/87 and 443.2/448.2. VE Exams at 11 AM, walk-ins accepted. Contact *Bud King WA9U, (618) 532-6606.* Mail ticket orders with an SASE to *Centralia Wireless Assn., Inc., Hamfest Tickets, P.O. Box 1166, Centralia IL 62801.*

**MILAN, OH** The firelands Area Repeater Assn. will hold their 2nd annual Hamfest at the Ehoove Career Center, from 8 AM-4 PM. Talk-in on WB8LLY Rptr. 146.805. Contact *Carol Richards A18V, (419) 433-6624.*

**TUCSON, AZ** The 5th annual Tucson Hamfest, sponsored by Old Pueblo RC. ARRL. ARCA, will be held from 7 AM-1 PM at DeAnza Drive-In, 22nd St. & Alvernon Way. Talk-in on 146.22/82, 146.28/88, and 146.52 simplex. Contact *A.J. Pawlowski KB7KZ, 3418 W. Green Trees Dr., Tucson AZ 85741. Tel. (602) 742-2605.*

## OCT 23

**GRANDVIEW, MO** The Southside ARC will hold its annual Octoberfest at the Grandview Middle School, 12650 Manchester St., from 8 AM-2 PM. VE Exams. Talk-in on 147.12+. Contact *Southside ARC, P.O. Box 1142, Grandview MO 64030, or Marvin Munson W0GHN, (816) 761-3238.*

**SUMTER, SC** The Sumter ARA will present their 7th annual Hamfest and South Carolina's 1993 ARRL Convention, from 8 AM-4 PM at Sumter County Exhibition Center, 700 W. Liberty St. VE Exams for Walk-ins Only. For

VE Exam info, call *Dan Mask WB5SGH, (803) 775-9106.* Dealers, call *Hap Griffin WA4UMU, (803) 469-6381.* For written info, write to *S.A.R.A. - Hamfest, P.O. Box 193, Sumter SC 29150.*

## OCT 23-24

**CHATTANOOGA, TN** The Hamfest Chattanooga Amateur Radio & Computer Convention will be sponsored by the Chattanooga ARC. Sat. 9 AM-5 PM; Sun. 9 AM-3 PM. Talk-in on 146.19/79. General info contact *Charles E. Curle AD4F, 8719 Snow Hill Rd., Ooltewah TN 37363.* Dealer info/reservations: *Barbarra Gregory, 8619 Smokerise Ln., Chattanooga TN 37421. Tel. (nights) (615) 892-8889.* Flea Market info: *Lou Carter, 107 South Bragg Ave., Lookout Mountain TN 37350. Tel. (nights) (615) 821-4043.*

**MOBILE, AL** The Mobile ARC will hold a Ham and Computer fest at Abba Shrine Temple, 7700 Hitt Rd., off Shillinger Rd. Time: Sat. 8 AM-4 PM; Sun. 8 AM-3 PM. VE Exams both days at 9 AM. Contact *Louis AC4EN.* Talk-in on 146.82/22. Rag-Chew 149.94/34. For details, call *Richard Ireland KD4ITD, (205) 824-2749, or write M.A.R.C., P.O. Box 81791, Mobile AL 36689.*

**PALM BEACH, FL** The West Palm Beach ARC will sponsor their 1st annual High Speed CW Contest, beginning at 1 PM at the Palm Beach County Fairgrounds. For details, contact *Ted Herrman AE8G, 301 North M St., Lake Worth FL 33460. Tel. (407) 586-7940; FAX (407) 585-3466.*

## OCT 24

**GOLDEN, CO** The Rocky Mountain Radio League, Inc., will present the 1993 RMRL Hamfest from 8 AM-2 PM at Jefferson County Fairgrounds, 15200 W. 6th Ave. VE Exams. ARRL Forum. Talk-in on 144.62/145.22 MHz. Contact *Joe Dickinson W7OC, (303) 795-3397.*

**WARREN, MI** The Utica Shelby Emergency Comm. Assn. will hold their USECA Swap from 8 AM-2 PM, at Student Community Center (K-Bldg.), Macomb Community College, South Campus. VE Exams (pre-registration required) call *Bill N8CVC, (313) 468-8345.* Table info: *Dave N8OE, (313) 792-0791; or Virginia N8NLS, (313) 268-0691.* Talk-in on 147.18+, 147.42 simplex. For Club info, call *Dave KF8CT, (313) 268-6730.* Mail pre-registration payments with an SASE to *Virginia Przekacka N8NLS, 34473 Coachwood, Sterling Hts MI 48312.*

**WESTMINSTER, MD** The Radio Clubs of Carroll County MD and Penn-Mar PA, will be holding the 4th annual Mason-Dixon Computer & Hamfest at the Carroll County Ag Center, starting at 8 AM. VE Exam registration begins at 8 AM; pre-registration requested; contact *Page Evans NE3P, (717) 359-7610.*

## OCT 30

**EAST LYME, CT** The Tri-City ARC will hold its annual Fall Auction at the Senior Citizens Center, Waterford Municipal Complex, from 10 AM till sold out. Bring your equipment to be auctioned. Talk-in on 146.07/67 Rptr. For info call *KA1BB at (203) 739-8016.*

**FREDERICKSBURG, VA** VE Exams will be given at the Rappahannock Library in Fredericksburg. For details, call *AC4SK at (703) 373-7076, or AC4MB at (703) 891-5581.*

## SCARED OF THE CODE?

IT'S A SNAP WITH THE ELEGANTLY SIMPLE MORSE TUTOR ADVANCED EDITION FOR BEGINNERS TO EXPERTS—AND BEYOND

Morse Code teaching software from GGTE is the most popular in the world—and for good reason. You'll learn quickest with the most modern teaching methods—including Farnsworth or standard code, on-screen flashcards, random characters, words and billions of conversations guaranteed to contain every required character every time—in 12 easy lessons.

Sneak through bothersome plateaus in one tenth of a word per minute steps. Or, create your own drills and play them, print them and save them to disk. Import, analyze and convert text to code for additional drills.

Get the software the ARRL sells and uses to create their practice and test tapes. Morse Tutor Advanced Edition is approved for VE exams at all levels. Morse Tutor is great—Morse Tutor Advanced Edition is even better—and it's in user selectable color. Order yours today.

For all MS-DOS computers (including laptops).

Available at dealers, thru QST or 73 or send \$29.95 + \$3 S&H (CA residents add 7.75% tax) to:

GGTE, P.O. Box 3405, Dept. MS, Newport Beach, CA 92659  
Specify 5 1/4 or 3 1/2 inch disk  
(price includes 1 year of free upgrades)

CIRCLE 193 ON READER SERVICE CARD.

## GREAT RADIO READS!

TIARE

Low Power Communications  
Vol. 1 - Basic QRP..... \$14.95

Basic Guide to VHF/UHF  
Ham Radio ..... \$ 6.95

Weather Radio NOAA, Volmet,  
Fax, Satellites, more ..... \$14.95

\$ U.S. only.

Add \$2 s/h (\$3 foreign) plus  
\$1 each additional book.  
VISA/Mastercard welcome.  
Catalog \$1 (free with order).

Order Now


Tiare Publications  
P.O. Box 493  
Lake Geneva, WI 53147

CIRCLE 119 ON READER SERVICE CARD


## PCB and SCHEMATIC C.A.D.

### EASY-PC

\$195



- Runs on PC/XT/AT/386/486 with Hercules, CGA, EGA or VGA display and many DOS emulations.
- Design Single sided, Double sided and Multilayer boards.
- Provides Surface Mount support.
- Exceptionally fast operation.
- Standard output includes Dot Matrix / Laser / Inkjet Printers, Pen Plotters, Photo-plotter and N.C. Drill.
- Award winning EASY-PC is in use in over 17,000 installations in 70 Countries World-wide.
- Very easy to learn and use.
- Not Copy Protected.



Options - 500 Piece Surface Mount Library \$112  
1000 Piece Library \$75.00 Gerber Import facility \$195.00

For full details write, call, fax or use inquiry #

### Number One Systems Ltd. 1

REF:- RFUS, HARDING WAY, SOMERSHAM ROAD, ST. IVES, HUNTINGDON, CAMBS, ENGLAND, PE17 4WR

Telephone  
USA: 011 44 480 461778 (7 lines)  
Intnl: +44 480 461778  
FAX: 011 44 480 494042

BRITISH  
DESIGN  
AWARD  
1989

AMERICAN EXPRESS,  
MASTERCARD and VISA  
WELCOME.

CIRCLE 1 ON READER SERVICE CARD

## HUGE NEW CATALOG

Call or write Universal today to receive your free 100 page catalog with prices!

- Communications Receivers
- Portable Receivers
- Amateur Transceivers
- Amateur & SWL Antennas
- Scanners
- RTTY and FAX Equipment
- Books and Manuals
- All major lines: Kenwood, Icom, Yaesu, Alinco, MFJ, Japan Radio, AEA, Sony and Sangean.

This catalog is available FREE by fourth class mail, or for \$1 by first class mail.

Universal Radio  
6830 Americana Pkwy.  
Reynoldsburg, OH 43068  
◆ Tel. 614 866-4267  
◆ Tel. 800 431-3939  
◆ FAX 614 866-2339

Universal-quality equipment since 1942!



**ST. PAUL, MN** The Hamfest Minnesota & Computer Expo, sponsored by the Twin Cities FM Club, will be held in the Main Arena at the St. Paul Civic Center, 143 West 4th St.: Flea Market. VE Exams. Educational and Fun Seminars. Talk-in on 146.16/76 Rptr. For info, write to *Twin Cities FM Club*, P.O. Box 5598, Hopkins MI 55343, or call the *Hamfest Minnesota Info Line*, (612) 535-0637.

#### OCT 31

**LEBANON, IN** The Boone & Clinton County ARCs will co-sponsor a Hamfest from 8 AM-4 PM at the Boone County 4-H Fairgrounds, Warm & Dry Community Bldg. Flea Market. VE Exams near by. Talk-in on 147.105 and 443.150. Contact *Tim French KA9WDJ*, (317) 324-2618; *Don Jackman N9ILX*, (317) 482-5211; or *Don Lecklitner N9GBO*, (317) 654-6580. Or write to *Boone County ARC*, P.O. Box 186, Lebanon IN 46052.

**MARION, OH** The Marion ARC will present its 19th annual "Heart of Ohio Hamfest and Computer Show" at the Marion County Fairgrounds Coliseum, from 8 AM-3 PM. Talk-in on 147.90/30 Rptr. Contact *Steve Eckard WS8S*, 6583 South St. Meeker, Marion OH 43302. Tel. (614) 499-3565.

#### NOV 6

**CARTHAGE, MO** The Carthage AR Soc. Hamfest will be held at the Carthage Memorial Hall at the intersection of Oak & Garrison Sts., from 8 AM-1 PM. Talk-in on 147.42 simplex. Contact *Jim Dixon WX0J*, or write to *Carthage ARC*, P.O. Box 783, Carthage MO 64836. Tel. (417) 358-4126.

**COOKEVILLE, TN** The Cookeville Rptr. Assn. and The Tennessee Tech ARS will co-sponsor the 3rd annual Cookeville Hamfest at Hooper Eblen Center on the campus of TTU. Time: 8 AM-4 PM. Talk-in on 147.21+. VE Exams at 10 AM. Contact *Rich KD4ABC*, (615) 528-7171 or *TTARS*, WA4UCE, TTU Box 5262, Cookeville TN 38505. Tel. (615) 372-3043.

**ENID, OK** Hoover Bldg., Garfield County Fairgrounds at Oxford St. and N. 4th, is the location for a Hamfest being sponsored by the Enid ARC. VE Exams at 10 AM (walk-ins welcome). Talk-in on 145.29/144.69. Contact *Fred N5QJX*, (405) 242-3551, or *Tom NSLWT*, (405) 233-8473.

**EUSTIS, FL** The Lake AR Assn. will hold their annual Hamfest and Electronics Expo at the Lake County Fairgrounds from 9 AM-5 PM. W5YI Testing for all classes, starting at 1 PM. Radio and ATV Demos. Contact *Cole A. Ruck KC4UIG*, (407) 273-1624 (eves); or *Pat Paris WD4LXN*, (904) 669-7279 (eves).

**FERNDALE, WA** The Washington Mt. Baker ARC Flea Market will be held from 9 AM-4 PM at Ferndale Band Boosters Bingo Hall, NW corner of Interstate 5 and Smith Rd. overpass. VE Exams. Contact *Terry Andrew VE7BUSW7*, 1009 Glenning St., Lynden WA 98264. Tel. (206) 354-5868.

**MILWAUKEE, WI** The Milwaukee Repeater Club will sponsor the 9th annual "6.91 Friendly Fest" from 8 AM-Noon at St. John the Evangelist Congregation, 8500 W. Cold Spring Rd. Talk-in on 146.91- and on 146.52. VE Exams. Contact *The Milwaukee Repeater Club*, P.O. Box 2123, Milwaukee WI 53201. Reservation deadline Oct. 28th.

#### NOV 6-7

**LONG ISLAND, NY** "HamExpo '93 Weekend" and ARL Section Convention, sponsored by the Radio Central ARC, will be held at Suffolk Community College from 9 AM-4 PM. Flea Market. Computer Show. VE Exams, and more. Group hotel rates. Talk-in on 145.150-4Z or 449.525-2A. Contact *Valerie DeRicco N2NYB*, (516) 874-3669 or *John Mark KB2QQ*, (516) 689-6343.

#### SPECIAL EVENT STATIONS

##### OCT 2

**ALAMOGORDO, NM** The Alamogordo ARC will conduct their 3rd Special Event operation, sponsored by the International Space Hall of Fame, to honor new inductees. Station WA5IPS will operate from atop the Space Hall. Frequencies: SSB - 28.480/490 MHz from 1600-1800 UTC. General phone bands on 15 and 20 meters from 1800-2300 UTC. We will operate in the 20 meter phone band if propagation is poor. Special QSLs will be sent from the Space Hall of Fame and will be certified by A.A.R.C. members. Mail QSL requests to *International Space Hall of Fame*, Route 2001 - P.O. Box 533, Alamogordo NM 88311-0533. SWL requests will be honored.

**MATTOON, IL** The Moultrie ARC will operate W9BIL to commemorate the annual Chocolate Harvest Celebration. Operation will be in the General 40, 20, and 15 meter bands, and the Novice 10 meter subband. For a certificate, send QSL and a SASE to *Bryon Abrams KB9BWS*, P.O. Box 242, Findlay IL 62534-0240.

**RICHARDSON, TX** The Alcatel ARA will operate Station N5TBQ (Texas Best Quality) 1500Z-2100Z, from the Open House site of Alcatel Network Systems, Inc. Operation will be in the General phone portions of 40, 20, 15, and 10 meters. For a unique QSL card, send contact report to *Alcatel Network Systems, Inc.*, AARA, M/S 401-212, 1225 North Alma Rd., Richardson TX 75081-2206.

##### OCT 6-10

**HILLSBOROUGH, NC** The Orange County Radio Amateurs will commemorate the bicentennial of the founding of the Univ. of North Carolina at Chapel Hill. SE Stations will operate, with a /UNC suffix, on the lower 25 kHz of the General portions of the 80, 40, 20, and 15 meter bands SSB, from 2300Z-0300Z on Oct. 6-8. In addition to the above band segments, SSB operation on the lower 50 kHz of the Novice portion of 10 meters (propagation allowing), will take place Oct. 9-10, from 1200Z-0000Z. An 8 1/2" x 11" certificate will be endorsed for all bands worked, with a special endorsement for UNC graduates. For a certificate, mail an SASE to *David J. Snyder N2MLU*, 600 S. Churton St., Apt. #66, Hillsborough NC 27278.

##### OCT 9-10

**CAMANO ISLAND, WA** The 3rd annual "Slug, Oyster and DX Festival" honors our friends the Mollusks, and is sponsored by the West Seattle ARC (W7AW). Operation will be Oct. 9 1500-0400 UTC to Oct. 10, 1500-2100 UTC. Frequencies: 21.052 MHz CW, 14.235 MHz SSB, 7.045 MHz CW, 3.930 MHz SSB. For a colorful certificate showing a slug and oyster at play, send your QSL and a large

SASE to *West Seattle ARC*, c/o F. Tate, 10230 4th Ave. SW, Seattle WA 98146.

**SAN GABRIEL MTNS., SO. CA** The 3rd annual "Mountain Top Mobile" will operate from Table Mountain, to celebrate radio for radio's sake. Operators: KC6TAZ, N6XOG, N6RNX, KM6TJ and N6PQB. QSL via individual operators (call followed by "Mountain Top Mobile").

**TORRANCE, CA** The South Bay ARC will operate KN6JN 1700Z-2400Z from the 2nd annual Torrance Air Fair in So. CA. Operations will be on General phone portions of 15 and 20 meters and Novice portion of 10 meters; also on 145.77 simplex and 224.38 rptr. For a certificate, send QSL and 9" x 12" SASE to *SBARC*, P.O. Box 536, Torrance CA 90508.

##### OCT 15-16

**ST. LAWRENCE COUNTY, NY** The North Country ARC will operate N2PSL to commemorate the Founding of the NCARC. Operation will be in the lower 25 kHz of the General portion of 80, 40, 20 meters, and the 10 meter Novice subband. For a QSL, send QSL and SASE to *NCARC*, c/o Pete Baltradis N2IJW, Rt. 1 Box 206, Norwood NY 13668 USA.

##### OCT 15-17

**UNION, KY** The Northern Kentucky ARC will operate K4CO 1400Z-2200Z from Big Bone Lick State Park, in conjunction with the annual Salt Festival. Operation will be on 40, 20, and 10 meters; also, 146.375+ Rptr. For a certificate, send 4" x 9" SASE and contact number to *NKARC*, P.O. Box 1062, Covington KY 41012-1062.

##### OCT 16

**SAN BERNADINO, CA** The Citrus Belt ARC will be operating Station W6JBT from the Patton State Hosp., to commemorate the admission of the first patient to the hospital 100 years ago. Operation will be from 1500 UTC Oct. 16th-1500 UTC Oct. 17th. Frequencies: Phone - 7.270, 14.270, 21.350, 28.350; 145.850 144-148 MHz band; 224.860 222-225 MHz band. For a certificate, send QSL and a 9" x 12" SASE to *Citrus Belt ARC*, P.O. Box 3788, San Bernardino CA 92413-3788.

**SANTA ROSA ISLAND, FL** The Serious Hams ARC will operate N4MAD from Ft. Pickens State Park 1200Z-2000Z on 40, 20, 15, and 10 meters in the CW and voice portions of the bands, near the lower edge of the General portion of each band. Santa Rosa Island is IOTA-142. For a special QSL, send SASE and contact number to *AD4BU*, 10697 Bridge Creek Dr., Pensacola FL 32506.

##### OCT 16-17

**DETROIT, MI** The Wayne County ARPSC will operate WY3Q/8 from 1400Z Oct. 16-2200Z Oct. 17, to commemorate the 16th annual running of the Detroit Free Press/Mazda Internat'l Marathon. Operation will be in the General 80-15 meter phone subbands and the Novice phone subbands on 10 meters. For a QSL card, send QSL and SASE to *Bill Gilbert*, 222 Cleveland, Trenton MI 48183.

##### OCT 16-23

**FORT WORTH, TX** The Menasco ARC will be on the air as a special event Station celebrating Menasco Aerosystems' 37 years of operating in the State of Texas. Operation will

be at 28.425 and 21.060 or 21.125 plus or minus QRM. To receive a special 8 1/2" x 11" certificate, send a large SASE to the control operator.

##### OCT 20-22

**NEW YORK CITY, NY** The "22 Crew" will operate WB2KJ from the HQ of the Radio Club of Junior HS 22, to celebrate the 13th Anniversary of NYC's largest Ham Club and EDUCOM (Education Thru Communication). Join them on 7.238 MHz, from 1200-1300 UTC, then on to 21.395 till 2000 UTC, Oct. 20-22. For an outrageous QSL and surprise package, write to *RC of JHS 22*, P.O. Box 1052, New York, NY 10002, or FAX to (516) 674-9600.

##### OCT 23

**EDISON, NJ** The Piscataway ARC will operate Station AA2KS 1300Z-2200Z, to celebrate Edison's discovery of the electric light bulb. Operation will be on the General portion of 40, 20, 15 meters and Novice 10 meters. For a special QSL card send QSL and SASE to *Piscataway ARC*, P.O. Box 1233, Piscataway NJ 08854.

##### OCT 23-24

**RIVERSIDE, CA** The Moreno Valley ARA, Team March ARC, and the March Air Force Base MARS station will operate K16GD during the March AFB Open House. Operations will be 1600Z-2200Z both days, on the General CW and phone sub-bands of 40, 20, and 15 meters. Also the Novice section of 10 meters. For a special certificate, send \$100 and contact number to *MVARA*, P.O. Box 7642, Moreno Valley CA 92552. For more info, contact *MVARA* or packet *N6YIH* @ *N6YIH*.#soca.ca.usa.na.

##### OCT 30

**ACCOMACK COUNTY, VA** The OH-KY-IN ARS will activate an IOTA during the CQ WW contest. The operation will be on all bands. The ITA will be one of the offshore islands in Virginia. Activity during the contest will be from Chincoteague Island, NA83. On Oct. 28 there will be a one day operation from Asateague Island, NA139. The call used will be K8SCH/4. The QSL route for both will be *John Hugentober, Sr. N8FU*, 4441 Andreas Ave., Cincinnati OH 45211. Please enclose an SASE.

##### OCT 30-31

**RIVERSIDE, CA** Moreno Valley ARA, Team March ARC, and the March Air Force Base MARS station will operate K16GD during the March AFB Open House. Operations will be 1600Z-2200Z both days, on the lower 25 kHz of the General subbands and Novice 10 meters. Operations will be SSB phone and CW; plus 145.560s and 146.655R pl 103.5. For a special USAF Certificate, send QSL and \$1.00 to *MVARA*, P.O. Box 7642, Moreno Valley CA 92552.

##### OCT 31-NOV 1

**BREYARD, NC** The Transylvania County ARC will operate W4ZCB to celebrate Halloween from the Devil's Courthouse in Transylvania County. Operation will be from 2000Z Oct. 31-0200Z Nov. 1. Frequencies: 7.234, 14.295, 21.365, 28.335 SSB, and 146.52 FM simplex. For a certificate, send a legal size or 9" x 12" SASE to *Harold Johnson W4ZCB*, 115 Kindy Forest Dr., Hendersonville NC 28739. **RF**

**WEFAX To The Max**



**PC GOES/WEFAX 3.0 \$250**

PC GOES/WEFAX 3.0 is a professional fax reception system for the IBM PC. It includes an AM/FM demodulator, software, cassette tutorial and 325 page manual. Check this partial list of our advanced features:

Res. up to 1280x800x256	APT Lat/Lon. Grids
Unattended Operation	Orbital Prediction
Colorization	Frame Looping
Zoom, Pan, Rotation	PCX & GIF Export
Contrast Control	Grayscale Printing
Tuning Oscilloscope	Infrared Analysis
Photometry/Histograms	Variable IOC & LPM

**PC HF FACSIMILE 6.0 \$99**

PC HF Facsimile 6.0 is a complete shortwave FSK fax system for the IBM PC. It includes an FSK Demodulator, software, 250 page manual and tutorial cassette. Call or write for a complete catalog of products.

**Software Systems Consulting**  
615 S. El Camino Real, San Clemente, CA 92672  
Tel: (714) 498-5784 Fax: (714) 498-0568

**VISA** **MasterCard** **ICOM**

**VHF COMMUNICATIONS**

453 Buffalo Street  
Jamestown, New York 14701

Listen to "Let's Talk Radio" 7 nights a week 6pm to 12 pm on Spacenet-3, Transponder-21, Audio 6.2

**9:00 am - 5:30 pm weekdays**  
**Weekends and evenings by appointment.**

Western New York's finest amateur radio dealer.  
PH. (716) 664-6345  
(800) 752-8813 for orders only

CIRCLE 14 ON READER SERVICE CARD

**GET ON PACKET RADIO... FAST and EASY...**

**With the "PC Packet Station"**

By PKT Electronics, Inc.

More than just a TNC, the "PC Packet Station" is a complete packet radio station for the IBM PC including:

- > **VHF Radio Transceiver** by Motorola < -  
- > **1200 baud modem** < - > **TNC Software** < -

You just plug the PC Packet Station into a half slot in your PC, plug in your VHF antenna into the card, load the software and you're on packet, it's just that easy!

PC PACKET STATION FEATURES: \* Fast, easy installation \* Selectable, Com 1 through Com 4 with selectable interrupts \* **Built in the USA** \* The Radio is totally shielded from the computer \* Have a custom application or a commercial use? Call us about Motorola radio modules, Motorola Telemetry Radios and Motorola Telemetry Modems. Dealer inquiries welcome.

PKT Electronics, Inc. 2668 Haverstraw Ave. Dayton, Ohio 45414 Voice and Fax 1-513-454-0242

CIRCLE 394 ON READER SERVICE CARD

Sell your used gear in the

**Radio Fun Flea Market**

Call Judy Walker today.

**1-800-274-7373**

**BATTERIES**

Nickel-Cadmium, Alkaline, Lithium, Sealed Lead Acid For Radios, Computers, Etc. And All Portable Equipment

**YOU NEED BATTERIES? WE'VE GOT BATTERIES!**

CALL US FOR FREE CATALOG

**E.H.YOST & CO.**  
7344 TETIVA RD.  
SAUK CITY, WI 53583  
(608) 643-3194  
FAX 608-643-4439



CIRCLE 114 ON READER SERVICE CARD



## ROOF-TOP TOWER

The IDEAL starter tower for EVERY new amateur radio operator. For HF arrays The RT 936 can handle 85 mph winds with a 28 square foot wing load. The lighter RT-832 handles up to 8 sq. ft. of wind load at 85 mph. With light weight and easy UPS shipping, you can have this tower up and operating on your QTH next week!

**You've wanted to put up a tower:  
Now you CAN!**

**Glen Martin Engineering:**  
Manufacturer of the HAZER tram system

Model	RT-832	RT-936
Height	8 Ft.	9 Ft.
Maximum Wind Load (Sq. Feet)	8 Sq. Ft.	28 Sq. Ft.
Shipping Weight	37 Lbs.	78 Lbs.
Price	\$189.95	\$328.75

We accept Mastercard, VISA or COD  
Order yours TODAY!



Route 3, Box 322 Boonville, MO 65233  
Phone 816-882-2734 Fax 816-882-7200

CIRCLE 72 ON READER SERVICE CARD

## Printed Circuits in Minutes Direct From Photocopier or Laser Printer!

8 1/2" x 11" Sheets Use household iron to apply.



### PnP BLUE

For High Precision Professional PCB Layouts

1. LaserPrint
2. Iron-On
3. Peel-Off
4. Etch

Adds an Extra Layer of Resist for Super Fine Lines on Std Clad Bds

### PnP WET

Easy Hobby Quality PCB's

1. LaserPrint
2. Iron-On
3. Soak-Off w/ Water
4. Etch

Transfers Toner from Laser Printer or Copier as Resist on Std Clad Bds

20Sh\$30/40Sh\$50/100Sh\$100  
PnP Blue or PnP Wet (No Mixing)  
Sample Pack 5 Shts Blue + 5 Shts Wet \$20  
VISA/MC/PO/CK/MO \$4 S&H -- 2nd Day Mail

Techniks Inc.

P.O. Box 463 Ringoes NJ 08551  
(908)788-8249

100% Money Back Guarantee-Dealer Inquiries Invited

CIRCLE 245 ON READER SERVICE CARD

## Radio Fun flea market

Turn your old ham and computer gear into cash now. Sure, you can wait for a hamfest to try and dump it, but you know you'll get a far more realistic price if you have it out where 30,000 active ham potential buyers can see it, rather than the few hundred local hams who come by a flea market table. Check your attic, garage, cellar, and closet shelves and get cash for your ham and computer gear before it's too old to sell. You know you're not going to use it again, so why leave it for your widow to throw out? That stuff isn't getting any younger!

The *Radio Fun Flea Market* costs you peanuts (almost)—comes to 25 cents a word for individual (noncommercial) ads, and 80 cents a word for commercial ads. Don't plan on telling a long story. Use abbreviations, cram it in. But be honest. There are plenty of hams who love to fix things, so if it doesn't work, say so.

Make your list, count the words, including your call, address and phone number. Include a check or your credit card number and expiration. If you're placing a commercial ad, include an additional phone number, separate from your ad. This is a monthly magazine, not a daily newspaper, so figure a couple of months before the action starts; then be prepared. If you get too many calls, you priced it too low. If you don't get many calls, too high.

So get busy. Blow the dust off, check everything out, make sure it still works right, and julybe you can help make a ham newcomer or retired old-timer happy with that rig you're not using.

Send your ads and payment to *Radio Fun Flea Market*, Judy Walker, 70 Route 202 N, Peterborough NH 03458, and get set for the phone calls.

**The Deadline for the November 1993 Flea Market is September 22, 1993.**

**HELP WANTED—EMPLOYMENT OPPORTUNITY AT RADIO FUN.** The Publisher of this magazine is currently accepting resumes for the following position.

**ADVERTISING SALES REPRESENTATIVE—**Display advertising sales for the only magazine devoted to newcomers in the amateur radio hobby. Intensive customer contact over the telephone, with an emphasis on developing new accounts. Must be available for weekend travel approximately six times per year. An amateur radio license, while helpful, is not necessary. Salary Range: teens, plus commissions.

To be considered for this position, send (no phone calls) your resume and cover letter to: **MR. D. CASSIDY, WGI**, 70 Route 202 North, Peterborough NH 03458.

RF198

**SENSATIONAL NEW WAY TO LEARN CODE—Do Aerobics, Sing, Jog, or Drive while learning code! Now the secret is yours! Order THE RHYTHM OF THE CODE—Morse code music cassette today! \$9.95 ppd KAWA RECORDS, P.O. Box 319-R, Weymouth MA 02188. The HIT of the 1993 Dayton Hamvention!**

RF247

Wayne is mad as hell ...  
...and he doesn't want you to take it anymore!

### Declare War!

On Our Lousy Government

Fed up with the mess in Washington?  
The mess in your state capital?  
Poverty, crime, our failing schools?  
Wayne Green has solutions.  
Clever solutions.

Wayne Green's unique reasoning is intriguing — even delightful. Whether you are horrified by his proposals or you embrace them, it is impossible to ignore the basic lesson he presents: It is time to bring logic — not emotions — to bear on America's dilemmas. His spin on America in the 90's helps us to understand how simple the seemingly complex issues are. All it takes is looking at them from an entirely new viewpoint.

Now available in one complete volume, *Declare War!* is full of thought provoking ideas and solutions to some of the most difficult problems facing our country today.

Regular price: \$12.95

Special For RF Readers

only — \$10.00 (plus \$3.50 shipping & handling)

Order Toll-Free: 800-234-8458

**MINIATURE POLICE RADAR TRANSMITTER** one mile range, \$41 assembled, \$31 kit, (219)489-1711. P.O. Box 80096, Fort Wayne IN 46898.

RF251

**AMIGA, MACINTOSH, ATARI XL/XE/ST** Amateur Radio PD Software \$4.00 disk. Two-stamp SASE brings catalog. Specify computer! **KINETIC DESIGNS HAMWARE** Box 1646, Orange Park FL 32067-1646.

RF266

**HOME BREW COMPONENTS.** Large SASE brings catalog. **KA7QJY COMPONENTS**, Box 3893, Logan UT 84323

RF271

**WANTED:** 4 pin tubes 211/VTA4C, 845, 2A3, etc. Garrard 301, 401, **SME RMA**, 309, 3012 Arms Ortofon SPU. Oil Caps. Call (201)751-5959. Paul Gil, 180 Union Ave., Belleville NJ 07109.

RF320

**IBM SHAREWARE!** Huge selection! \$1.00 Disk! \$.35 Specials! Catalog \$1.00. **PMA-RF**, Box 2424, Scottsdale AZ 85252.

RF360

**SATELLITE EQUIPMENT WHOLESALE.** Drake IRD's, start \$494.00; Toshiba IRD's, start \$494.00; IRD, LNB, FEED, ACTUATOR, \$633.00; LNB's, \$59.00; Actuators, \$59.00; VCRS Modules, \$389.00. Large inventory. **SATELLITE WAREHOUSE**, PO Box 85601, Tucson AZ 85754-5601. Orders, (800)851-6534; Fax, (602)624-1629; Info, (602)623-5748.

RF380

**MILITARY RADIO EQUIPMENT WANTED** PP32T/GRC9 A.C. Power Supply; AA-18 Alimentation Power Supply; Microphone SW-109; RT70/GRC; AM65; PP281; AB-86 Antenna Mast; PP-1104/G Power Supply; AN/URM-48 Sig Gen; Antenna Mounts M652/GR. **KA1ZQR**, 348 N. Main St., Stonington CT 06378, (203)535-1286.

RF390

**BROWNIES QSL CARDS** since 1939. Catalog and Samples \$1 (refundable with order). 3035 Lehigh Street, Allentown PA 18103.

RF475

**KIT BUILDERS!** Complete list of 150 + kit vendors. SASE + \$3 USD to: **RUTENBER ENGINEERING**, 38045 10th St. E. #H75-AR, Palmdale CA 93550. RF485

**PASS THE NO CODE TEST.** "Easy Method." Send \$4 and SASE to **L.W. SERVICE**, P.O. Box 91, Hillside NJ 07205-2702. RF500

**INEXPENSIVE HAM EQUIPMENT.** Send stamp for list. **WA4DSO**, 3037 Audrey Drive, Gastonia NC 28054. RF559

**LICENSE PLATE HOLDERS** (Chrome or Black) with message plates. Your name and call letters engraved. Designed mail box plate 12 1/2" X 4 1/4" black. Name and Number engraved. Chrome or black license plate holder, \$10.50; mail box plate, \$12.50. Each order S&H, \$2.50. **N.E. MARION ENGRAVING**, R.F.D. 2, Box 360, Peterborough NH 03458. RF590

**PRINTED CIRCUIT BOARDS** for projects in 73, *Ham Radio*, *QST*, *ARRL Handbook*. List, SASE. **FAR CIRCUITS**, 18N640 Field Ct., Dundee IL 60118. RF595

**VIDEO SYNC GENERATOR** Restores horizontal & vertical sync lines from distorted analogue video formats. For information on completed units & pricing, write: **R.C. DISTRIBUTING**, Box 552, South Bend IN 46624. Phone: (219)236-5776

RF610

**WANTED: BUY & SELL** All types of Electron Tubes. Call (612)429-9397, Fax (612)429-0929. **C & N ELECTRONICS**, Harold Bramstedt, 6104 Egg Lake Road, Hugo MN 55038. RF620

**INTERESTED IN PUBLIC SERVICE?** Join REACT TODAY! For information write, **KA3PDQ, c/o REACT**, P.O. Box 8797, Allentown PA 18105. RF630

**DO YOU WANT TO EASILY GET \$30?** Send me the name and the address of the company that built color lamps to be installed under cars. **Francesco Fontana**, via Salerno 11, 35142 Padova, Italy. RF690

**RADIO TRANSCRIPTION DISCS WANTED.** W7F1Z, Box 724, Redmond, WA 98073-0274. RF700

**FREE Ham Gospel Tracts.** SASE. **N3FTT**, 5133 Gramercy, Clifton Heights PA 19018. RF960

**CONNECTICUT'S favorite ham store.** **ROGUS ELECTRONICS**, 250 Meriden-Waterbury Turnpike, Southington CT 06489. (203)621-2252. RF994

**SECRET SCANNER** Frequencies: Federal, Police, Aero, Military, Cellular, Surveillance, also SWL & CB Books. Big FREE catalog! **CRB RESEARCH**, Box 56-RF, Commack NY 11725. RF996

**AMATEUR RADIO REPAIR!!** All makes & models. Reasonable rates. **W7HBF, DAN RUPE**, 1302 S. Upland Dr., Camano WA 98292. (206)387-3558. RF999



# Uncle Wayne's Bookshelf

## BOOKS FOR BEGINNERS

- 02D42 Digital Novice** by Jim Grubbs Geared to make you a more knowledgeable participant. \$8.50
- 01A87 Shortwave Listener's Antenna Handbook** Primer antenna theory. \$13.95
- 05C25 Basic A.C. Circuits** A step-by-step approach for the beginning student. \$24.50
- 20N018 Technician Class License Manual: New No-Code** by Gordon West This book covers everything you need to become a Technician Class Ham. Every question and answer on the examinations is found in this one book. FCC Form 610 application. \$9.95
- 20N092 The Wonderful World of Ham Radio** by Richard Skolnik, KB4LCS Simple, clear, and fun. Introduces young people to amateur radio. \$7.95
- 20N100 Electronics Build and Learn (2nd Ed.)** by RA Penfold Combines theory and practice so that you can "learn by doing." \$12.50
- 20N099 Digital Electronics Projects for Beginners** by Owen Bishop Contains 12 digital electronics projects suitable for the beginner to build with the minimum of equipment. \$12.50
- AR2871 W1FB's Help for New Hams** by Doug DeMaw W1FB Complete for the newcomer. Put together a station and get on the air. \$10.00
- AR2286 First Steps in Radio** by Doug DeMaw W1FB Series of QST articles. \$5.00

## SHORTWAVE

- 06S57 1993 Passport to World Band Radio** by International Broadcasting Services, Ltd You'll get the latest station and time grids. \$16.50
- 03S11 Shortwave Receivers Past and Present** edited by Fred J. Osterman Guide to 200+ shortwave receivers manufactured in the last 20 years. The Blue Book of shortwave radio value. \$8.95
- 07R25 The RTTY Listener** by Fred Osterman New and expanded. This specialized book compiles issues 1 through 25 of the *RTTY Listener Newsletter*. Contains up-to-date, hard-to-find information on advanced RTTY and FAX monitoring techniques and frequencies. \$19.95
- 03C09 Shortwave Clandestine Confidential** by Gerry L. Dexter Covers all clandestine broadcasting, country-by-country: tells frequencies, other unpublished information: spy, insurgents, freedom fighters, rebel, anarchist radio, secret radio. \$8.50
- 03M221 US Military Communications (Part 1)** US Military communication channels on shortwave. Covers frequencies, background on point-to-point frequencies for the Philippines, Japan and Korea, Indian and Pacific Oceans, and more. \$12.95
- 03M222 US Military Communications (Part2)** Covers US Coast Guard, NASA, CAP, FAA, Dept. of Energy, Federal Emergency Management Agency, Disaster Communications, FCC, Dept. of Justice. From 14 KC to 9073 KC. \$12.95
- 03M223 US Military Communications (Part 3)** Completes the vast overall frequency list of US Military services, from 8993 KC to 27,944 KC. \$12.95
- 09S42 The Scanner Listener's Handbook** by Edward Soomre N2BFF Get the most out of your scanner radio. \$14.95
- 11T88 Tune in on Telephone Calls** by Tom Kneitel K2AES Formatted as a frequency list with detailed description of each service and its location in RF spectrum. \$12.95
- 03K205 Guide to Radioteletype (RTTY) Stations** by J. Klingentuss Updated book covers all RTTY stations from 3MHz-30MHz. Press, Military, Commercial, Meteor, PTTs, embassies, and more. \$12.95
- 11AS10 Air Scan Guide to Aeronautical Communications (5th Ed.)** by Tom Kneitel K2AES Most comprehensive guide to monitoring US aeronautical communications. Covers all Canadian land airports and seaplane bases, plus listings for Central America, the Caribbean, North Atlantic, and the Pacific Territories. \$14.95
- 15A002 Scanner and Shortwave Answer Book** by Bob Grove Most frequently asked questions by hobbyists. \$13.95

**07A66 Aeronautical Communications Handbook** by Robert E. Evans Exhaustive, scholarly treatment of shortwave aeronautical listening. \$19.95

**11RF13 The "Top Secret" Registry of US Government Radio Frequencies (7th Ed.)** by Tom Kneitel K2AES This scanner directory has become the standard reference source for frequency and other important information relating to the communications of federal agencies. \$19.95

**11F52 Ferrell's Confidential Frequency List, New Revised Edition** compiled by A.G. Hallikey All frequencies from 4 MHz-28MHz covering ship, embassy, aero, Volmet, Interpol, numbers, Air Force One/Two, more. \$19.50

**11SR97 National Directory of Survival Radio Frequencies** by Tom Kneitel K2AES Handy and concise reference guide to high interest communications frequencies required by survivalists. \$8.95

**11SM11 Scanner Modification Handbook, Vol. 1** by Bill Creek provides straightforward step-by-step instructions for expanding the operating capabilities of VHF scanners. \$17.95

**11EE06 Guide to Embassy Espionage Communications** by Tom Kneitel K2AES Candid and probing examination of worldwide embassy and (alleged) espionage communications systems and networks. \$10.95

**20N094 A Flick of the Switch, 1930-1950** by Morgan E. McMahon Discover the fast-growing hobby of radio collecting. \$8.95

**07R26 World Wide Aeronautical Communications** by Robert E. Evans Aircraft/Air Traffic Control, Aircraft/Company Operations, Aviation Weather Broadcasts, Aeronautical Flight Tests, Worldwide Military Air Forces, Aero Search & Rescue, Aero Law Enforcement, NASA Flight Support, Aero Terms & Abbreviations and Aero Tactical Identifiers. \$6.95

**11T89 Scanner Modification Handbook Vol. 2** by Bill Creek Here it is—a companion to Vol. 1. In fact, Vol. 2 has a section that provides improved approaches and updated techniques for the mods in Vol. 1. There's 18 new exciting modifications for popular scanners. \$17.95

**03R01 World Press Services Frequencies (RTTY) New 5th Ed** A comprehensive manual covering radioteletype news monitoring—contains all information—antenna, receiving, terminal units, plus three extensive frequency lists. \$8.95

## ARRL BOOKS

- AR1993 ARRL 1993 Handbook (70th Ed.)** 39 chapters, featuring 2,100 tables, figures and charts. Comprehensive, well organized and affordable. \$25.00
- AR1086-4 ARRL Operating Manual (4th Ed.)** Information on how to make the best use of your station, including: interfacing home computers. OSCAR, VHF-UHF. \$18.00
- AR0194 Antenna Compendium Vol. 1** Materials on verticals, quads, loops, yagis, reduced size antennas, baluns, Smith Charts, antenna polarization. \$10.00

**AR2545 Antenna Compendium Vol. 2** Covers verticals, yagis, quads, multiband and broadband systems, antenna selection. \$12.00

**AR4017 Antenna Compendium Vol. 3** More verticals, yagis, quads, plus loops, arrays, mobile, direction finding, controlled currents, computerized, installation, overloads, plus 40 new articles for beginner's to advanced. \$14.00

**AR2626 Companion Software for Antenna Compendium Vol. 2** 5 1/4" MS-DOS floppy. \$10.00

**AR0488 W1FB's Antenna Notebook** by Doug DeMaw W1FB Get the best performance out of unobtrusive wire antennas and verticals. Build tuners and SWR bridges. \$9.50

**AR0348 QRP Notebook** by Doug DeMaw W1FB Presents construction projects for the QRP operator. \$9.50

**AR4141 W1FB's Design Notebook** by Doug DeMaw W1FB Filled with simple practical projects that can be built using readily available components and common hand tools. \$10.00

**AR2200 Antenna Impedance Matching** by Wilfred N. Caron Most comprehensive book written on using Smith Charts in solving impedance matching problems. \$15.00

**AR4002 Solid State Design** Good, basic information, circuit designs and applications; descriptions of receivers, transmitters, power supplies, and test equipment. \$12.00

**AR3193 Weather Satellite Handbook (4th Ed.)** by Dr. Ralph Taggart WB8DOT Expanded and revised to reflect today's weather-fax satellite technology. \$20.00

**AR3290 Companion Software for Weather Satellite Handbook** 5 1/4" MS-DOS Floppy. \$10.00

**AR3291 Now You're Talking! All You Need To Get Your First Ham Radio License (2nd Edition)** A complete study guide for the Technician and Novice written exam. Practical information every beginner needs is written clearly and simply and in small doses. \$19.00

**AR3292 Your Introduction to Morse Code: Practice Cassettes** Kit includes two 90 minute cassette tapes. Prepares you for the 5 WPM Morse code exam to earn your Novice license or add high-frequency worldwide communications privileges to your code-free Technician license. \$10.00

**AR0437 ARRL Repeater Directory 1993-1994** 19,000+ listings with digipeaters, bandplans, CTCSS (PL(TM)) tone chart, frequency coordinators, ARRL special service clubs, and beacon listings from 14 MHz to 24GHz. \$6.00

**AR1033 The DXCC Companion** by Jim Kearman KR1S Spells out in simple, straightforward terms what you need to be a successful DXer. \$6.00

**AR1250 Log Book—Spiral** \$3.50

**ARA341 Interference Handbook** RFI sleuth's experience in solving interference problems. \$12.00

**AR2197 ARRL Data Book** Valuable aid to the RF design engineer, technician, radio amateur, and experimenter. \$12.00

**AR2960 Transmission Line Transformers (2nd Ed.)** by Dr. Jerry Sevick W2FMI Practical designs and specific information on construction techniques and sources of material. \$20.00

**AR0410 Yagi Antenna Design** A Ham Radio series polished and expanded by Dr. Lawson. \$15.00

**AR2171 Hints and Kinks** Ideas for setting up your gear for comfortable, efficient operation. \$8.00

**AR3169 QRP Classics** Compilation of ARRL publications on building receivers, transmitters, transceivers, accessories. \$12.00

**ARRL License Manuals** Complete FCC question pools with answers.

AR2375	Technician Class	\$6.00
AR2383	General Class	\$6.00
AR0166	Advanced Class	\$6.00
AR2391	Extra Class	\$8.00

**AR3185 The Satellite Experimenter's Handbook, (2nd Ed.)** by Martin Davidoff K2UBC Expanded and revised. Focusing on satellites built by and for the international radio amateur community. \$20.00

**AR2456 FCC Rule Book (9th Ed.)** A must for every active radio amateur. \$9.00

**AR2030 Your Gateway to Packet Radio (2nd Ed.)** Tells everything you need to know about this popular new mode. \$12.00

**AR2103 Satellite Anthology** The latest information on OSCARS 9 through 13 as well as the RS satellites, the use of digital modes, tracking antennas, RUDAK, microcomputer, and more! \$5.00

**AR2898 Space Almanac** by Anthony R. Curtis K3KXX Recent news from space. \$20.00

**AR2083 Complete DX'er (2nd Ed.)** by Bob Locker W9KNI Learn how to hunt DX and obtain hard-to-get QSL cards. \$12.00

**AR2065 ARRL Antenna Book** The new 16th Edition represents the best and most highly regarded information on antenna fundamentals, transmission lines, design, and construction of wire antennas. \$20.00

**AR3293 Morse Code: The Essential Language** by L. Peter Carron Jr. W3DKY Expanded and revised in its 2nd edition. How to handle distress calls heard not only on the hambands but on maritime and aircraft frequencies. \$6.00

**AR4114 Low Profile Amateur Radio** For the Ham who lives where antennas are frowned upon. From hiding your antenna to operating with low power. This book tells you how to get on the air using these techniques—and others—without calling attention to yourself. \$8.00

## STUDY AIDS

**VIS Study Cards** Compact, up-to-date Flash Cards with Key Words, Underlined, Quiz on back. Formulas worked out. Schematics at your fingertips. Used SUCCESSFULLY by ages 6 to 81!

NOVICE	VIS01	\$11.95
TECH	VIS02	10.95
GENERAL	VIS03	9.95
ADVANCED	VIS04	15.95
EXTRA	VIS05	14.45

## REFERENCE

**20N102 Practical Digital Electronics Handbook** by Mike Tooley BA Contains nine digital test gear projects. Digital circuits, logic gates, bistables and timers, microprocessors, memory and input/output devices. \$14.50

**20N103 Electronic Power Supply Handbook** by Ian R. Sinclair Covers many types of supplies—batteries, simple AC supplies, switch mode supplies and inverters. \$16.25

**20N104 Electronic Test Equipment Handbook** by Steve Money A guide to electronic test equipment for the engineer, technician, student and home enthusiast. \$18.00

**20N105 Digital Logic Gates and Flip-Flops** by Ian R. Sinclair A firm foundation in digital electronics. Treats the topics of gates and flip-flops thoroughly and from the beginning. \$18.00

**01C80 Master Handbook of 1001 Practical Electronic Circuits** Tried and proven solid state circuits. \$19.95

**01P68 Pirate Radio Stations** by Andrew Yody Tuning in to underground broadcasts. \$12.95

**01T01 Transmitter Hunting** by Joseph Moell and Thomas Curlee Radio direction finding simplified. \$19.95

**03R02 Rtty Today** by Dave Ingram Modern guide to amateur radio-teletype. \$8.50

**05E03 First Book of Modern Electronics** Unique projects that are money saving. \$12.95

**09D22 The World Ham Net Directory** by Mike Witkowski New—2nd edition. Introduces the special interest ham radio networks and shows you when and where you can tune them in. \$9.50

**09P33 Pirate Radio Directory** by George Zeller Where to tune in on secret entertainment stations. \$7.95

**10F093 1993 International Callbook** The new 1993 International Callbook lists 500,000+ licensed radio amateurs in the countries outside North America. It covers South America, Europe, Africa, Asia, and the Pacific area (exclusive of Hawaii and the U.S. possessions). \$29.95

**10D093 1993 North American Callbook** The 1993 North American Callbook lists the calls, names, and address information for 500,000+ licensed radio amateurs in all countries of North America. \$29.95

**05H24 Radio Handbook, 23rd Ed.** by William I. Orr W6SAI 840 pages of everything you wanted to know about radio communication. \$39.95

**02B10 Heath Nostalgia** by Terry Perdue K8TP 124 page illustrated history of the Heath Company. Includes many fond memories contributed by long-time Heathkit employees. \$9.50

**10DF92 1993 Callbook Supplement** An update to the 1992 International and American callbooks. \$10.00

**12E76 Basic Electronics** Prepared by the Bureau of Naval Personnel Covers the important aspects of applied electronics and electronics communications. \$10.95

**12E41 Second Level Basic Electronics** Prepared by the Bureau of Naval Personnel Sequel to Basic Electronics, thorough treatment of the more advanced levels of applied electronics. \$9.95

**01D45 The Illustrated Dictionary of Electronics, 5th Ed** by Rufus P. Turner and Stan Gibilisco An exhaustive list of abbreviations, and appendices packed with schematic symbols and conversion tables. \$26.95

**20N091 Most-Often-Needed Radio Diagrams and Servicing Information, 1926-1938, Volume One** compiled by M.N. Beitman An invaluable reference for anyone involved in Vintage Radio restoration. \$11.95

**20N096 How To Read Schematics (4th Ed.)** by Donald E. Herrington Written for the beginner in electronics, but it also contains information valuable to the hobbyist and engineering technician. \$14.95

**20N097 Radio Operator's World Atlas** by Walt Stinson, W0CP This is a compact (5x7), detailed, and comprehensive world atlas designed to be a constant desk top companion for radio operators. \$17.95

**20N020 Secrets of RF Circuit Design** by Joseph J. Carr Written in clear non-technical language, covers everything from antennas to transistors. \$19.50

**20N109 73 Magazine Index 1960-1990** A complete index to every article published in 73 Magazine through 1990. Book \$15.00 IBM software (specify type) \$20.00

**20N110 Product Reviews Since 1945** Contains an index to 3,400 product reviews that have appeared in QST, CQ, HR, 73 and Radcom. Book \$12.95 IBM Software 5.25 \$10.00

## WAYNE'S PICKS

**SS8756 Warning! The Electricity Around You May Be Hazardous To Your Health** by Ellen Sugarman An invaluable guide to the risks of electromagnetic fields, and steps you can take to protect yourself and your family. \$11.00

**"We The People" Declare War! On Our Lousy Government.** by Wayne Green A "must read" for every american taxpayer. Solutions to every problem facing our government today. \$12.95

**ED86751 Dumbing Us Down: The Hidden Curriculum Of Compulsory Schooling** by John Gatto If you enjoyed "Declare War", you'll enjoy this also. A Wayne Green recommended reading. 9.95.

## NEW STUFF

**AR3762 Your QRP Operating Companion** No special rigs or expensive equipment to enjoy the excitement and challenge of low-power operating. \$6.00

**AR3878 Your VHF Companion** Explore the fascinating activities on the VHF bands: FM and repeater, packet, CW, & SSB, satellites, ATV, transmitter hunting, and more. \$8.00

**AR3959 Your Packet Companion** Perfect for the packet newcomer. \$8.00

## Uncle Wayne's Bookshelf Order Form

You may order by mail, telephone, or fax. All payments are to be in US funds. Allow 3 weeks for delivery.

Item #	Title	Qty.	Price	Total

Shipping: All orders add \$5.00 shipping. U.S. orders shipped UPS.  
(Alaska & Hawaii shipped via mail.) Airmail to Canada and all overseas orders  
FOB Peterborough, NH. Make checks payable to "Uncle Wayne's Bookshelf."

SHIPPING  
TOTAL

Name \_\_\_\_\_

Street \_\_\_\_\_

City \_\_\_\_\_ State \_\_\_\_\_ Zip \_\_\_\_\_

TOTAL \$ \_\_\_\_\_ ☐AE ☐MC ☐VISA ☐Check/Money Order

Card # \_\_\_\_\_ Expiration Date \_\_\_\_\_

Mail: 73 Magazine, Attn. Uncle Wayne, PO Box 3080, Peterborough, NH 03458

Telephone: (603) 924-4196 (800) 234-8458 FAX: (603) 924-8613

RF1093

## UHF/VHF PACKET

**01P22-2 The Packet Radio Handbook (2nd Ed.)** by Jonathan L. Mayo KA3T "...the definitive guide to amateur packet operation."—Gwyn Reedy W1BEL Only \$16.95

**09V11 The Basic Guide to VHF/UHF Ham Radio** by Edward M. Noll Provides a first rate introduction to the 2.6 and 1.25 meter bands as well as 23, 33, and 70cm. \$6.50

**20N019 U.S. Repeater Mapbook** by William Smith N6MQS The Guide for traveling radio amateurs. \$9.95

**03R02 RTTY Today** by Dave Ingram K4TWJ Most comprehensive RTTY guide ever published. \$8.50

## ANTENNAS

**20N108 The Easy Wire Antenna Handbook** by Dave Ingram K4TWJ. Gives you all of the needed dimensions for a full range of easy to build and erect "sky wires." \$9.50

**01A70 Practical Antenna Handbook** by Joseph J. Carr Design, build, modify, and install your own antennas. \$22.95

**10A342 All About Verticle Antennas** by William Orr Comprehensive coverage of amateur communications. \$10.95

**10A343 All About Cubical Quad Antennas** by William Orr and Stuart Cowan "The Classic" on Quad design, theory, construction, operation. New feed and matching systems. New data. \$11.95

**10A345 Beam Antenna Handbook** by William Orr and Stuart Cowan Everything you need to know about beam design, construction, and operation. \$11.95

**10A346 Simple, Low-Cost Wire Antennas For Radio Amateurs** by William Orr and Stuart Cowan All New! Low-cost, multi-band antennas; inexpensive beams, "invisible" antennas for hams in "tough" locations! New data. \$11.95

## SOFTWARE

**04M54 GGTE Morse Tutor** From beginner to Extra class in easy self-paced lessons. Code speeds from 1 to over 100 words per minute. Standard or Farnsworth mode. Adjustable tone frequency. Create your own drills, practice or actual exams. Exams conform to FCC requirements. 5 1/4" floppy for IBM PC, XT, AT, PS/2 or compatibles. \$19.50

**04M55 Advanced Edition** \$29.95

**20N021 No Code Ham Radio Education Package** Computer software package. Includes computer aided instruction software (IBM compatible), 200 page Ham Radio Handbook. \$28.95

**20N022 Ham Operator Education Package** Computer software contains five IBM compatible discs with all questions for all license classes, plus "Morse Academy" code teaching software that takes you from 0-20 wpm. \$28.95

**LANZE Code Programs—(Available on 5 1/4" disk.)** Inexpensive complete study guide code programs for both the C64/128 Commodores and the IBM compatibles. Programs include updated FCC questions, multiple choice answers, formulas, schematic symbols, diagrams, and simulated (VE) sample test.

	IBM Part#	Commodore Part#	Price
Novice	IBM01	COM01	\$14.95
Tech	IBM02	COM02	\$14.95
General	IBM03	COM03	\$14.95
Advance	IBM04	COM04	\$19.95
Extra (New Pool)	IBM05	COM05	\$19.95

**IBM06, COM06 IBM/Commodore Tech No Code—Lanze Code Program** Contains all the authorized FCC questions and answers used in testing formulas, schematic symbols, diagrams, and sample test for passing the new Technician No Code license. \$24.95

**IBM97 Amateur Radio Part 97 Rules** New Edition, complete FCC rules. \$9.00

## CODE TAPES

**73T05 "Genesis"** \$5.95  
5 wpm—This beginning tape, takes you through the 26 letters, 10 numbers, and necessary punctuation, complete with practice every step of the way.

**73T06 "The Sticker"** \$5.95  
13+ wpm—This is the practice tape for those who survived the 5 wpm tape, and it's also the tape for the Novice and Technician licenses. It is comprised of one solid hour of code. Characters are set at 13 wpm and spaced at 5 wpm.

**73T13 "Back Breaker"** \$5.95  
13+ wpm—Code groups again, at a brisk 13+ wpm so you'll be really at ease when you sit down in front of a steely-eyed volunteer examiner who starts sending you plain language code at only 13 per.

**73T20 "Courageous"** \$5.95  
20+ wpm Congratulations! Okay, the challenge of code is what's gotten you this far, so don't quit now. Go for the extra class license. We send the code faster than 20 per.



# new products

## PIONEER HILL SOFTWARE

Hams with a personal computer using Microsoft Windows 3.1 and a Sound Blaster or compatible sound board will appreciate having an Audio Spectrum Analyzer at their fingertips. This new program allows you to analyze audio signals in near real time by digitizing the audio using the sound board, performing a Fast Fourier Transform (FFT) and displaying the resulting spectra. The program makes good use of the Windows graphics environment—clicking the left mouse button on a peak shows its frequency; pressing the right mouse button and dragging

between two peaks measures the frequency offset.

The user can select the FFT size, sampling rate, and mark key frequencies. Its averaging mode is especially useful as random noise is reduced to allow the signal characteristics to be more clearly discerned. In fact, injecting white noise into the antenna terminals and averaging for a few minutes will show the radio filter's response. The program sells for \$39. For more information, please contact: *Pioneer Hill Software, 24460 Mason Rd., Poulsbo WA 98370; (206) 697-3472. Or circle Reader Service No. 201.*

## AEA

AEA has recently introduced the IT-1 AutoTuner, an accessory for their popular IsoLoop 10-30HF antenna. The IsoLoop is a high quality, high efficiency antenna with a mere 35-inch diameter.

The IT-1 AutoTuner will automatically tune an IsoLoop in just a few seconds. When more control is necessary, there is a thumbwheel for manual tuning and fine adjustments.

The IT-1 AutoTuner features a 12-button keypad with an audible beep to announce completion of tuning. It has eight programmable memories, as well as a 10-segment LED bar that monitors the tuning process and indicates the selected memory number. Memory backup and a built-in serial interface are also included.

The suggested retail price is \$279 at your local amateur radio dealer. The unit comes




with a one-year warranty. For more information contact: *Advanced Electronic Applications, P.O. Box C2160, Lynnwood WA 98036; (206) 774-5554, Fax: (206) 775-2340. Or circle Reader Service No. 203.*

## THE TOOL RESOURCE

Hexacon's HTC Series Soldering Stations are now available at The Tool Resource. These provide superior thermal capacity and outperform other soldering stations at an economical price. The heating elements are located in the tips for quick temperature response. The units are built to be spike- and static-free, well-grounded, and ESD-safe.

The clever sponge holder includes a dross tray which eliminates the need to touch the potentially hazardous metal material. It holds three times as much water as ordinary sponge trays. A wide selection of tips are available, and custom tips can be ordered.

For more information, contact: *The Tool Resource, P.O. Box 1106, W. Dundee, IL 60118;*




*Voice or Fax: (708) 468-0849. Or circle Reader Service No. 205.*

## CREATIVE CONTROL PRODUCTS

Here is a brand-new, low-cost, easy-to-interface repeater audio interface circuit from Creative Control Products. The UAD-100 Universal Audio Delay board features complete DTMF tone mute, and squelch tail elimination.

This board is inserted in the repeater receiver audio path before any audio switching circuitry. It then delays the audio before it arrives in the repeater transmitter, resulting in a pleasant-sounding transmitter drop. No more crashing, clunking, or snapping. Finally: a great sounding system, made easy.

The UAD-100 comes fully-assembled and tested with a detailed application manual and one-year warranty for \$99. For more information, please contact: *Creative Control Products, 3185 Bunting Avenue, Grand Junction CO 81504; (303) 434-9405. Or circle Reader Service No. 206.*




## j-COM

DXers will be impressed at how easy it is to use the new j-Com W9GR DSP-II Audio Filter. A single rotary switch selects any one of the 11 available filters on this dandy.

Now available for use by SSB operators are four filters which enhance the intelligibility of speech signals while reducing hiss, static, ignition and power-line noise, white and pink noise, and other random interference. For CW operators, four brick-wall linear-phase 120th order FIR bandpass filters will extract the weakest signals from adjacent QRM. Three special use bandpass filters are also provided: 2075-2345 Hz for RTTY, 1550-1850 Hz for HF pack-

et, and 1150-2350 Hz for SSTV.

A 10-segment bar graph displays the input audio signal level for performance optimization. The gain control is adjustable for comfortable listening. A 2 watt amplifier is built into the unit to drive the external speaker. The W9GR DSP II Audio Filter installs easily between the receiver speaker output and an external speaker. It's being introduced at \$299.95 plus \$5 S&H in the US (\$15 S&H overseas). For more information contact: *j-Com, 793 Canning Parkway, Victor NY 14564; (716) 924-0422, Fax: (716) 924-4555. Or circle Reader Service No. 202.*



## JENSEN TOOLS

Wouldn't it be nice to always have an entire tool chest right at your fingertips? Well, now you can have the next best thing—the new SOG ToolClip from Jensen Tools, Inc. This unique pocket tool combines 13 functions in one neat little package.

The SOG ToolClip features a full-jaw

pliers, a combination gripper and wire cutter that can easily handle chain link fencing, a razor-sharp spear-point blade, a utility blade, a serrated-edge blade, a pair of screwdrivers, a pair of wire strippers, a file, a pry bar, and a bottle opener, all in a sturdy housing complete with a belt clip. The pliers, wire cutters, and grippers can all be accessed with only one hand—a mighty helpful feature when climbing towers

or holding materials.

The SOG ToolClip is constructed of durable stain-resistant steel and is guaranteed for life against defective workmanship and materials. The price is \$59.95. For more information, or to receive a free catalog, contact: *Jensen Tools Inc., 7815 S. 46th St., Phoenix AZ 85044; (602) 968-6231. Or circle Reader Service No. 204.*



## TRIMBLE NAVIGATION

You'll never get lost again with Trimble Navigation's satellite-based hand-held GPS

(Global Positioning System) Scout. It is perfect for amateur radio applications, search and rescue, backpacking, and off-road driving. The low-cost Scout GPS receives positioning data from 24 orbiting satellites to pinpoint your location around the clock, anywhere on earth, in any weather.

The GPS was designed and developed by the US Department of Defense to benefit both military and civilian users. Hams will enjoy the Scout GPS, which is based on the Maidenhead Grid Locator, displaying location information in language familiar to many amateurs. Scout uses the ARRL's grid square locator technique.

The Scout GPS kit contains four AA batteries, a user's manual, cordura carrying case, lanyard, and the Trimble Atlas. The whole package retails for \$795 and an external antenna kit accessory is available for \$150. For more information contact: *Trimble Navigation, 645 North Mary Avenue, P.O. Box 3642, Sunnyvale CA 94088-3642; (408) 481-8000, Fax: (408) 730-2997. Or circle Reader Service No. 207.*



## FT-2200/7200 2-m/70-cm Mobiles

### • Frequency Coverage:

FT-2200

RX: 110-180 MHz

TX: 144-148 MHz


FT-7200

RX/TX: 430-450 MHz

- 50 Memory Channels
- Wide Receiver Coverage: 110-180 MHz
- AM "Aircraft" Receive: 110-139 MHz
- Built-In DTMF Paging/Coded Squelch
- Power Output 50/25/5 Watts
- CTCSS Encode Built-In
- 10 Memory DTMF Auto Dialer
- Selectable Channel Only Display
- Remote Operation w/ Optional MW-2
- Optional Digital Voice Storage System
- Backlit DTMF Mic
- **Accessories:**
  - FTS-27** CTCSS Decode Unit
  - DVS-3** Digital Voice System Unit
  - MW-2** Remote Control/Wireless Mic
  - SP-7** External Speaker

"The FT-2200 answers my problem! It fits anywhere, and the 3 power levels are great!"

"Yaesu did it again!"



"I like the FT-2400H!"

"Rugged performance is my answer!"

## FT-2400/7400H 2-m/70-cm Mobiles

### • Frequency Coverage:

FT-2400H

RX: 140-174 MHz

TX: 144-148 MHz

FT-7400H

RX/TX: 430-450 MHz

- Rugged Mil-Spec Design
- Advanced Track Tuning (ATT)
- 31 Memory Channels
- Wide Receiver Coverage: 140-174 MHz
- Selectable Alpha-Numeric Display
- Largest 2-Meter Display Available
- CTCSS Encode Built-In
- Power Output 50/25/5 Watts
- Flip Up Front Control Panel Hides Seldom Used Buttons
- Backlit DTMF Mic
- **Accessories:**
  - FTS-17A** CTCSS Decode Unit
  - FRG-6** DTMF Paging Unit
  - SP-4** External Speaker
  - FP-700** Power Supply

For your sleek compact car, the sculptured FT-2200 looks terrific. With leading-edge features, performance and reliability too, it's the perfect answer to your 2-m needs.


At 5.5"W x 1.6"H x 6.5"D the FT-2200 installs nearly anywhere. And, it does "lead" with features like optional Remote Control Wireless Mic – first in the world for any 2-m mobile and AM Aircraft Receive – first in a Yaesu mobile. Performance? The FT-2200 has more than twice the memories of the competition! Reliability? Its bright, new LCD display and backlit DTMF Mic makes night mobilizing safe. Features, performance, reliability – in a powerful little package. See your dealer for *this* answer to your 2-m needs.

The Yaesu FT-2400H set the standard by which all 2-m mobiles are judged. The first and only amateur radio to pass rugged MIL STD 810D tests for shock and vibration, its one-piece die-cast chassis with extra large heat sink gives years of trouble-free operation.

With 50 watts of TX power, large alpha-numeric display, auto display dimmer, exclusive backlit DTMF Mic and advanced track tuning front end for superior receiver performance, the popular FT-2400H is the choice of amateurs in the know.

Features, performance, reliability – ready to go anywhere. See your dealer for *this* answer to your 2-m needs.

NEW



# Yaesu answers your 2-m mobile needs.



# YAESU

Performance without compromise.™

© 1993 Yaesu USA, 17210 Edwards Road, Cerritos, CA 90701 (310) 404-2700

Specifications subject to change without notice. Specifications guaranteed only within amateur bands. Some accessories and/or options are standard in certain areas. Check with your local Yaesu dealer for specific details.



# A New Way To Learn About A New Radio:

## 1-206-450-6088

ICOM's new 2iA is *so* new, and *so* different, we had to find a new and different way of telling you about it. Introducing **I-COM LINE**.  
Your hotline for new radio info!

### The NEW! **I-COM LINE**

*No buttons, no hassles, pure fun!*

Our I-COMLINE is free, it's fun, and it's the best way ever of making intelligent radio buying decisions.

Here's all you do:

1. Dial 1-206-450-6088.

2. Leave your name, address, and the name of the product you're interested in – in this case, the 2iA.

Within 24 hours, we'll send you REAL info about the 2iA: how and why it was designed, spec sheets, field tests, reviews – everything you need to decide if this is the radio for you.

Give it a try! See how easy it is to communicate with the world leader in amateur radio communications.

**I-COM LINE: uniquely ICOM!**



Actual size!

### The NEW! **IC-2iA**

*No buttons, no hassles, pure fun!*

Tiny on the outside, lots of radio on the inside. We challenged our designers to build the smallest, lightest, *skinniest* handheld ever – but without sacrificing the big-radio features. Putting a big radio in a small space meant that something had to go.

Not the big display, of course.

Not the super audio speaker.

And we obviously couldn't cut corners on features and still call it an ICOM.

So we got rid of the buttons.

When you really think about it, you want what buttons do, not necessarily the buttons themselves, right?

So we put the controls on the inside, where they belong.

To find out how we did it and how it works, call the I-COM LINE

**The IC-2iA: uniquely ICOM!**



**P Series**  
P2AT - 2M  
P3AT - 220MHz  
P4AT - 440MHz

**SRA Series**  
2SRA -  
2M/WideBand  
Receiver,  
4SRA -  
440MHz/WideBand  
Receiver

ICOM's HT Family – also available on the **I-COM LINE!**

**SAT Series**  
2SAT - 2M  
3SAT - 220MHz  
4SAT - 440MHz

**GAT Series**  
2GAT - 144MHz  
4GAT - 440MHz  
12GAT - 1.2GHz

**0AT Series**  
02AT - 2M  
03AT - 220MHz

**AT Series**  
2AT - 144MHz

**Dual Band**  
W2A - 2M/440MHz  
W2I - 2M/440MHz  
X2A - 440MHz/1.2GHz  
24AT - 2M/440MHz

ICOM America, Inc., 2380 116th Ave. N.E., Bellevue, WA 98004 All stated specifications subject to change without notice or obligations. All ICOM radios significantly exceed FCC regulations limiting spurious emissions. The Icom Logo is a registered trademark of ICOM America. 21A793Y

# ICOM®

*Experience the Quality®*